

DCP-110VAC-2000VDC-2000W

2000 W High Voltage Power Supply - 110V AC Input, 2000V DC Output - 1000 mA Max Output

Product ID: 319412

Please see last page for supporting documentation for this product(certificates, CAD files & drawings, IES files, wiring diagrams, etc).



Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

DCP-110VAC-2000VDC-2000W High Voltage Power Supply

Line In Voltage: 110 V AC $\pm 10\%$ @ 50/60 Hz

Line Out: 2000 V DC @ 1 Amps, Adjustable (0-2000V DC)

Watts: 2000W

Power Supply Polarity: Negative

Front Panel Controls: Voltage and current are continuously adjustable by potentiometers with lockable counting dials, ON/OFF circuit breaker/lamp, high voltage ON switch/indicator and high voltage OFF switch/indicator

Voltage Regulation: Load: 0.005% of maximum voltage +500mV for full load change.

Line: $\pm 0.005\%$ of full voltage +500mV over specified input range

Voltage Regulation Resolution: ≤ 10 mV

Voltage Regulation Accuracy: Better than $\pm 0.02\% \pm 1$ V

Voltage Monitoring Resolution: ≤ 10 mV

Voltage Monitoring Accuracy: Better than $\pm 0.02\% \pm 1$ V

Current Regulation: Load: 0.01% of maximum current $\pm 100\mu\text{A}$ for full voltage change. Line: $\pm 0.005\%$ of maximum current for a $\pm 10\%$ input line change.

Current Regulation Resolution: ≤ 10 nA.

Current Regulation Accuracy: Better than $\pm 0.2\% \pm 2$ A

Current Monitoring Resolution: ≤ 10 nA

Current Monitoring Accuracy: Better than $\pm 0.2\% \pm 2$ A

Ripple: < 8 mV from 10 Hz to 1 kHz, and < 5 mV from 1 kHz to 20 MHz

Temperature Coefficient: Better than ± 100 ppm/ $^{\circ}\text{C}$

Stability: Long-term stability (1 week after warmup) of better than $\pm 0.02\%$ of full scale

Features

IP67 Rated Waterproof

Overload, Short Circuit, Over Voltage, Over Temperature Protection

NRTL Certified to UL1012

NRTL Certified to UL60950-1

International Lighting Safety Standards Compliant

Suitable For LED Moving Signs

Suitable For Wet or Damp Locations

Local/Remote Control: Supports both via TCP/IP over ethernet

Metering: Digital voltage and current meters, 31/2 digit ± 1 least significant digit.

Interface Connector: 25 pin male D connector

Output Cable: 10' of shielded high voltage cable removable at the rear panel

AC Line Input Cable: 6' cable is permanently attached to the unit

Protection: Short Circuit/Overload/ Over Voltage/Over Temperature

Operating Temperature Range: 5°C ~ +45°C

Humidity: 0 to 80% relative humidity, non-condensing

Mounting: Mounted on a standard 19" rack

Dimensions: 31 1/2"H(2U) x 19"W x 19"D

Weight: 17 lbs

Special Orders - Special Requirements

Contact us for special requirements

Toll Free: 1-800-369-6671

Intl: 1-903-270-1187

Fax: 1-903-498-3364

E-mail: sales@larsonelectronics.com

The DCP-110VAC-2000VDC-2000W from Larson Electronics is a Waterproof Power Supply that converts commonly used 110 V AC electrical current to 2000 V DC @ 1 Amps. This converter is designed to be hardwired into building, boat, or vehicle electrical supplies where the voltage is typically within the 110 V AC range and reduces it to 2000 V DC, allowing users to use standard AC power to operate equipment like our LED light bars and spotlights that require 2000 V DC current.

The DCP-110VAC-2000VDC-2000W power converter provides a safe and effective way for users to tap into and utilize common 110 Volt AC power sources and convert this voltage to 2000 Volts DC for use with equipment that requires 2000 volt DC electrical power. This unit can be operated with input current ranging from 110 V AC and will output 2,000-watt 2000 Volt DC current. This power converter features an IP67 rated waterproof design, making it suitable for indoor or outdoor use and is wet-damp area approved. This converter includes integral short circuit, over voltage, over temperature and overload protection that will shut down the unit or reduce output in case of faults and overloads to protect the unit and connected equipment from damage.

The small size and wide input voltage range of this unit make it ideal for indoor-outdoor operation of Larson Electronics LED light bars and other equipment that requires 2000 V DC current and anywhere 2000 volt DC power is not readily available. The unit is mounted with two conventional screws via slots that allow removal and repositioning simply by loosening the screws.

This converter comes with clearly labeled input and output leads that are approximately 1 foot long and stripped and tinned for hardwired connections using butt splice connectors, wire screws, plates, etc.

This power converter has a -40°C - +90°C operating temperature range and is NRTL certified to UL 1012 and UL 60950-1 standards as well as compliant with worldwide safety regulations for lighting. This unit has a 90% conversion efficiency and is suitable for use with moving LED signs and similar LED equipment. These units also feature Power Factor Correction, adjustable output current range from 0 ~ 3 A either through the output cable or internal potential meter and have an input frequency range of 47 ~ 63Hz.

NOTE: In order to obtain the best performance and the longest operational life from these units, it is recommended that you do not exceed 75% of the unit's output amperage. To determine if this converter suits your desired application, add together the total wattage of the equipment you intend to use with this unit and divide this total by 2000 volts to find the total amperage draw that will be placed upon the converter. Running these units at 100% of their capacity can create excess heat and lead to shortened converter life.

At Larson Electronics, we do more than meet your lighting needs. We also provide replacement, retrofit, and upgrade parts as well as industrial grade power accessories. Our craftsmen can custom build any lighting system and/or accessories to fit the unique demands of your operation. A commitment to honesty, quality, and dependability has made Larson Electronics a leader in the lighting and electronics business since 1973. Contact us today at 800-369-6671 or message sales@larsonelectronics.com for more information about our custom options tailored

to meet your specific industry needs.

Frequently Asked Questions (FAQ)









Export Control Classification Number (ECCN): EAR99

Links (Click on the below items to view):

- [HigResPic1](#)
- [HigResPic2](#)
- [HigResPic3](#)
- [HigResPic4](#)
- [HigResPic5](#)
- [HigResPic6](#)
- [HigResPic7](#)
- [HigResPic8](#)
- [HigResPic9](#)
- [ISO 9001 Certification](#)
- [Business Certificate](#)
- [Shipping Time Map](#)