25W Blue LED Warning Light
2250 Lumens - 12-24V DC - Strobing Safety Light - IP67
Instruction Manual

Thank you for your purchase of the LEDWL-STRB-BLUE-1224 Warning Light. Do not attempt installation until you are familiar with all warnings, precautions, and procedures outlined within this instruction sheet.

Safety Warnings

For personal safety, always follow the safety instructions in this manual to ensure safe and long- term use. Failing to do so can result in damage to the product or serious bodily injury.

WARNINGS

To prevent serious damage to eyesight, never look into spotlight when light is on. **DO NOT** shine light into the face of someone else.

DO NOT touch lens of spotlight when light is on or if it was recently on.
DO NOT use this product for other than its intended use.
DO NOT operate in close proximity of Combustible or flammable materials.
DO NOT attempt to operate this light if cord, lens, bulb or any part of the light is damaged or corroded.

MOUNTING AND ADJUSTMENTS:

The LEDWL-STRB-BLUE-1224 is suspended within a form fitting trunnion (yoke-type) mount. This trunnion mount allows the LED light to be adjusted into any position once mounted. Simply loosen the Pivot Adjustment Bolt shown in **FIGURE 1**, angle, and tighten once desired position is achieved.

A single stainless steel tightening bolt protrudes from the mount, enabling the operator to install the light using a single through-hole. Mount the unit in a location free from obstructions and potential obstructions of machines. Utilize an existing ½ inch hole or drill a new hole where applicable.

This LED warning light comes pre-configured in selected output color from factory indicated on product part number.



FIGURE 1

WIRING AND PLUG:

The LEDWL-STRB-BLUE-1224 LED warning/indicator strobing spotlight is equipped with Deustch connector and a 20` wiring harness. The external power supply is remote mountable. Operators can install the power supply between the light and the control station. The external power supply is designed to be hardwired and operates on voltages ranging from 12-24V DC.







For info on **Warranty** and **Returns** please contact us by phone or email sales@larsonelectronics.com