# LEDBLT-18W-5C

## 18 Watt LED Fixture for Industrial Lighting
## Instruction Manual

Thank you for your purchase of the LEDBLT-18W-5C LED Fixture for Industrial Lighting, the following instructions are intended for this part number only.

**MOUNTING:**

Mounting for this unit is provided by an included aluminum trunnion yoke that allows vertical adjustment of the light once installed. The mounting yoke is predrilled with thru-hole for easy and secure mounting to flat surfaces or pipe mounting. The entire assembly weighs 2 lbs. and measures only 2.3" in diameter and approximately 4.75" long.



To adjust the pivot of the light, use a screw driver to loosen or tighten the fastening screws holding the light to the mounting bracket.

**WIRING/POWER:**

These industrial LED lights are equipped with 5’ of 16/3 chemical and abrasion resistant SOOW cable with customer specified cord cap or flying leads. These lights are universal voltage capable and can be operated with 100-277 VAC, 50/60Hz. We also offer a low voltage version of this LED fixture that operates on low voltage from 12-24 volts AC/DC. This light draws 0.15A at 120V, 0.075A at 240V, 0.065A at 277V, 1.5A at 12V, or 0.75A at 24V. Check product label for correct voltage.

**Connect incoming power as follows:**

- Green to safety ground
- Neutral to white
- Line to black
- Restore power and verify operation




## Safety Warnings

For personal safety, always follow the safety instructions in this manual to ensure safe and long- term use. Failing to do so can result in damage to the product or serious bodily injury

## Warnings

To prevent serious damage to eyesight, never look into spotlight when light is on. **DO NOT** shine light into the face of someone else.
**DO NOT** touch lens of spotlight when light is on or if it was recently on. The lens will be hot and could cause serious burns.
**DO NOT** allow children to handle or operate this light.
**DO NOT** use this product for other than its intended use.
**DO NOT** operate in close proximity of Combustible or flammable materials.
**DO NOT** attempt to operate this light if cord, plug, battery, bulb or any part of the light is damaged or corroded.

For info on **warranty** and **returns** please visit our website: www.Larsonelectronics.com