

21W C1D2 LED Fixture - 3' Low Profile Light Strip

120-240V AC/DC High Voltage - No Cord

Instruction Manual

INSTALLATION

This light fixture can run on voltages of 120V-240 AC. The installation environment must not exceed the Ingress Protection IP65 rating of the luminaire.

We strongly recommend that only a licensed electrician install this product.

1. Mount fixture in desired location using 1/4" screws (not included).
2. To position, loosen the bolt at the end without the cord, adjust fixture to desired angle, and re-tighten to hold in place.
3. Rotate the front cover of junction box counter-clockwise to remove for wiring.
4. Run power source to NPT hub following local and national electric codes. Wire terminations and connections must be approved for the environment. The field wiring terminations are to be made following acceptable practices as outlined by the NEC/CEC for either the specific ordinary or hazardous locations as dictated by the installation location.
5. Energize luminaire.


**See drawing for mounting dimensions.*

Features

21 Watts
120-240V AC
50,000+ Hour Life Expectancy

Voltage: 120V-240V AC
Beam Type: 100° Flood OR 30° Spot

Loosen bolt to adjust to
desired angle.



MAINTENANCE

Caution: To avoid personal injury, disconnect power before performing maintenance.

Perform visual, mechanical and electrical inspections on a regular basis. We recommend routine checks to be made on a yearly basis. Frequency of use and environment should determine this. It is recommended to follow an Electrical Preventive Maintenance Program as described in NFPA 70B: Recommended practice for Electrical Equipment.

Should further information not covered by these instructions be required, please contact Larson Electronics at 1-800-369-6671 or sales@larsonelectronics.com for further assistance.

Please visit LarsonElectronics.com for **Warranty** and **Return** information.