84W Vapor Proof LED 2' Light for Outdoor Applications
5250 Lumens - IP67 - (4) 50 lb Magnets
Instruction Manual

CAUTION

- Risk of fire/electrical shock. If not qualified, consult an electrician.
- Disconnect power at fuse or circuit breaker before installing or servicing.
- Edges may cut. Handle with care.

SAFETY INSTRUCTIONS (Read Carefully for your Protection)

- ETL approved for wet locations.
- Connect fixture to universal 120-277VAC 50/60 Hz or 11-25V AC/DC power source depending on model. (Any other connection may void warranty.)
- A qualified electrician or person with experience in household wiring should install this fixture. The electrical system and the method of connecting to electricity must be in accordance with the National Electrical Code and local building codes.
- Keep away from flammable objects. Do not position fixture within one inch of any combustible materials.
- Your light fixture is prewired for easy installation.
- This fixture is rated for 50,000 hours.
- To avoid hazard to children, account for all parts and destroy packing materials.

PREPARATION

- This fixture comes preconfigured to work in the selected Voltage and contains the selected cord cap, and color temperature. It is preassembled and ready for operation.
- Simply mount the fixture via the four 50lb. magnets in a location that can support the weight.
- Run cord to a power source outputting the voltage listed on product nameplate. Make sure cord is out of the way to prevent any hazards.
- Light is “instant on” and will illuminate once energized.

TROUBLESHOOTING

PROBLEM	POSSIBLE CAUSE	CORRECTIVE ACTION
Light does not come on	No power to the fixture	Check if circuit breaker is tripped
Wiring to the unit is loose	---	Confirm fixture is properly grounded

QUESTIONS, PROBLEMS, MISSING PARTS

Before returning your fixture, please call Larson Electronics at 1-800-369-6671 or log on to http://www.larsonelectronics.com for replacement parts.

WARNING

- Always hire a licensed electrician for proper installation.
- Always mount this fixture to a grounded junction/breaker box.

LIGHT ASSEMBLY

1. Turn off the power at the main fuse or breaker box.
2. Thread wires through wire gland and back cover wire hole.
3. Connect the wires to the wire terminal L to L, N to N then fasten the wire gland.
4. Attach to the LED tubes to the lamp holder.
5. Put the tube fixing board in the back cover, fixing poles through the board's holes. Then turn around the head of fixing poles 90° to fix the board to back cover.
6. Use the lens and back cover clips to attach lens to back cover.
7. Use the wall fixing clips to fix the light fixture to the wall.
8. Turn on power at main fuse breaker box.

