Portable, Rechargeable LED Light Tower
2, 10-Watt LEDs - Telescoping Mast, 3 - 8 Feet
Instruction Manual

Do not attempt operation until you are familiar with all warnings, precautions, and procedures outlined within this instruction sheet. Read carefully before operating. Retain these instructions for future reference.

BATTERY SPECIFICATIONS:

- 12 volt output
- 33 Amp hour AGM sealed lead acid
- Built-in automatic charger rated for continuous duty
- Voltage indicator gauge with push-to-test button
- External charge cord receptacle, U.S. or foreign power cord supplied
- Battery rated for 300+ full discharge cycles
- 3-5 year estimated service life

SET-UP

1. Charge unit for 24 hours when new and every three months thereafter to maintain a full charge (Charge monthly in hot weather).
2. Do not charge or use this light in hazardous location.
3. Extended retractable legs if necessary for uneven terrain.
4. Extend aluminum pole to desired height and tighten each pole section into position.

OPERATION

1. Single head light will operate over 40 hours on a full charge.
2. Dual head light will operate over 20 hours on a full charge.
3. The power port provided can be used to operate a cell phone, a laptop computer, or any of Larson Electronics' handheld light with cigarette plug. The power port can be used a quick charge inlet for the light from an automobile's 12-volt power port.
4. Order Larson Electronics' power port duel end cable for connection from vehicle to light.

SAFETY AND USAGE INFORMATION

1. Read these instructions completely before using the products and save them for future reference.
2. Do not use unit to recharge dry cell batteries.
3. Do not jump-start or attempt to recharge a frozen battery.
4. Charge unit in a well-ventilated area.
5. All batteries are affected by temperature changes, and the unit's small, lightweight battery is more sensitive to storage temperature than a standard automotive battery. Temperatures above 68F degrees (20degrees C) decrease amperage output. The ideal storage environment for emergency use is at room temperature.

BATTERY STATUS GAUGE

1. Press the RED push button momentarily to turn the gauge on:
2. The GREEN shaded indicator bar indicates the unit is capable of normal operation.
3. The YELLOW shaded indicator bar indicates the unit needs to be recharged.
4. The RED shaded indicator bar indicates the unit must be recharged before use.

RECHARGING

1. Plug the unit into 115 VAC and note the lighted gauge indicator for battery status.
2. The unit may be recharged by using an optional accessory power port cord with two male ends.
3. Plug one end into the unit's 12V outlet and the other end into the vehicle's 12V power port socket. The vehicle must be running to charge with this method.

STORAGE:

- Unit may be stored virtually anywhere, and in any position

BATTERY REPLACEMENT:

- This unit contains a sealed non-spill able lead acid battery. The battery must be recycled.
- Contact Larson Electronics' for replacing battery.

THESE INSTRUCTIONS MAY NOT COVER ALL DETAILS OR VARIATIONS OF THIS PRODUCT FOR YOUR EQUIPMENT OR INSTALLATION REQUIREMENTS. SHOULD FURTHER INFORMATION NOT COVERED BY THESE INSTRUCTIONS BE REQUIRED, PLEASE CONTACT LARSON ELECTRONICS BY EMAIL AT SALES@LARSONELECTRONICS.COM OR BY PHONE AT 1-800-369-6671 FOR FURTHER ASSISTANCE.

PLEASE VISIT LARSONELECTRONICS.COM FOR **WARRANTY** AND **RETURN** INFORMATION.