

General Area Usage Weatherproof Receptacle Outlet 125 Volt AC - 20 Amp Rated Instruction Manual

WARNING:

READ CAREFULLY BEFORE OPERATING. RETAIN THESE INSTRUCTIONS FOR FUTURE REFERENCE.

CRITICAL SAFETY INSTRUCTIONS:

USER SHOULD BE TRAINED IN THE PROPER USE AND MAINTENANCE OF THIS DEVICE.

IMPROPER USE OF THIS RECEPTACLE CAN LEAD TO SERIOUS INJURIES OR DEATH TO PERSONNEL.

PERIODIC INSPECTION OF THE RECEPTACLE AND/OR ATTACHED CORD/CONDUIT IS NECESSARY.

CORD MUST BE ROUTINELY CHECKED FOR CUTS, BREAKS, OR ANY SEVERE ABRASIONS, AND IF ANY ARE FOUND, CORD MUST BE REPLACED BEFORE RESUMING USE.

GENERAL INFORMATION

Open junction box by removing screw near receptacle. Remove top cover and wire accordingly. Once connected, replace top cover. The receptacle can be mounted to flat by opening the top cover and attach via through holes on the back.

CAUTION: Disconnect power before installing. Never wire energized electrical components.

1. **NOTICE:** For installation by a qualified electrician in accordance with national and local electrical codes and the following instructions.
2. **CAUTION:** RISK OF ELECTRIC SHOCK. Disconnect power before installing. Never wire energized electrical components.
3. **CAUTION:** USE COPPER CONDUCTORS ONLY.
4. Check that the device's type and rating are suitable for the application.
5. Select conductors having 90°C or higher rated insulation having sufficient ampacity in accordance with the 60°C column of National Electrical Code Table 310-16 or Canadian Electrical Code.
6. **Wiring Instructions**
 - a. Strip conductors using strip gauge on receptacle. If receptacle does not have a strip gauge, then strip conductor 1 inch (25 mm). DO NOT TIN CONDUCTORS.
 - b. Loosen terminal screws. Insert conductors fully into proper terminals per Table 1 and center under terminal screw.

Table 1	
TERMINAL	CONDUCTOR
Green, Grid, G, 	Equipment grounding conductor, (bare, green or green/yellow)
White, W	NEUTRAL (White or Gray)
Black, Brass (Other Than White or Green)	HOT terminal (NOT White NOT Green)

- c. **TAKE EXTREA CAUTION THAT THERE ARE NO LOOSE STRANDS.**
 - d. Tighten terminal screws.
7. Mount receptacle in box with screws provided and enclose with cover/wall plate.

Should further information not covered by these instructions be required, please contact Larson Electronics at 1-800-369-6671 or sales@larsonelectronics.com for further assistance.

Please visit LarsonElectronics.com for **Warranty** and **Return** information.