Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

MTPC-HD-RB-208V-7.5HP-3HP-N1

Rotary Phase Converter for 3HP Hard Loads, 208V 1PH to 3PH, 9 Amps Output, 7.5HP Idler, NEMA 1

Product ID: 243146

Please see last page for supporting documentation for this product (certificates, CAD files & drawings, IES files, wiring diagrams, etc).



Image: MTPC-HD-RB-208V-7.5HP-3HP-N1

Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

MTPC-HD-RB-208V-7.5HP-3HP-N1 Rotary Phase Converter

Unit Type: Rotary Phase Converter
Phase Conversion: Single Phase to Three Phase
Kilowatt Rating: 5.6 KW
Kilo Volt-Amp Rating: 7.5 KVA
Idle Motor Horse Power: 7.5 HP
Single Phase Voltage Input: 208V
Minimum Fuse/Circuit Breaker Size: 20
Maximum Fuse/Circuit Breaker Size: 40
Minimum Wire (Input) to Converter: 8 AWG
Minimum Electrical Service Required: 10 KVA
Idle Amps: -
Service Load Type: Hard motor loads
Three Phase Voltage Output: 208
Maximum Single Motor Load HP: 3 HP
Recommended Combined HP: 3 HP
Optimal Output Amps: 9A
Maximum Output Amps: 23.2A
Maximum Resistive Amps: 10A
Voltage Balance: 2-5%
Minimum Wire to Device Load: 10 AWG

Ratings/Approvals

Indoor Use (NEMA 1)
Built-in Motor Starter
Start/Stop Push Button Switch
Accurate Voltage Balancing
Power Indicator Light

Made in the USA

Form Factor: Rectangular Enclosure, Cylindrical Idler w/ Four Legs
Color: Natural Gray
Weight: Motor - 67 lbs, Panel - 30 Lbs
Dimensions: Motor - 14.8" x 11.2" x 10.3", Panel - 12" x 12" x 8"
Shipping Weight: - lbs
Shipping Dimensions: -

Special Orders - Special Requirements
Contact us for special requirements
Toll Free: 1-800-369-6671
Intl: 1-903-270-1187
Fax: 1-903-498-3364
E-mail: sales@larsonelectronics.com

Made in the USA

The Larson Electronics MTPC-HD-RB-208V-7.5HP-3HP-N1 7.5 horsepower rotary phase converter is designed to convert single phase power to three phase power for Hard motor loads. This phase converter accepts a single-phase 208V input and provides a three-phase 208V output. Operators may use this rotary phase converter to power equipment and machines with Hard motor loads up to 3 horsepower and 9 amps that require three phase power in locations where only single phase power is available.

Applications: The MTPC-HD-RB-208V-7.5HP-3HP-N1 is ideal for applications that utilize Hard motor loads. This includes CNC laser table, CNC lathe, CNC mill, CNC plasma table, CNC router, CNC turning machine, CNC waterjet, cooling fan, exhaust fan, gearhead lathe, industrial fan, laser cutter, laser table, plasma cutter, plasma table, plastic grinder, printing press and any other application that induces a Hard motor load up to a recommended 3 horsepower.

The MTPC-HD-RB-208V-7.5HP-3HP-N1 rotary phase converter is suitable for converting single phase 208V on-site power to three phase 208V power for equipment. This 7.5 HP idler motor phase converter connects to existing 208V/* single phase. After conversion, the phase converter provides three-phase 208V on the output side at 9 continual amps with a maximum of 23.2 inrush amps. All MTPC series phase converters provide +/- 2-5% voltage balance on the output side, depending on the single phase input power, for maximum efficiency and reduced stress on the motor. This rotary phase converter features a built-in motor starter with a start/stop push button switch for seamless activation. The power distribution blocks are oversized for easy installation in the preferred location.

The MTPC-HD-RB-208V-7.5HP-3HP-N1 control panel is housed in a NEMA 1 enclosure, making it suitable for indoor environments. This level of protection allows the rotary phase converter to withstand the ingress of solid objects, such as falling dirt. All of Larson Electronics LLC`s phase converter control panels are NRTL certified to UL 508A.

The MTPC series of rotary phase converters are designed to operate based on overall load size. This includes operating multiple devices from one rotary phase converter, providing the combined horsepower of all devices being operated simutaniously does not exceed the horsepower rating for the load type. This includes fractional motors up to 3 HP motors, and any combination of motor sizes in between. Instant reversal motors are no problem for the MTPC series phase converters. Each phase converter comes ready to install.

Rotary Sizing: The MTPC-HD-RB-208V-7.5HP-3HP-N1 is sized for heavy/hard motor loads up to 3 horsepower. When correctly sized, Larson Electronics phase converters will provide years of trouble free service for your equipment. Larson Electronics offers single phase to three phase static and rotary phase converters for easy, medium, hard, and very hard motor loads. The motor load is dependant on the devices intended to operate on the phase converter. For additional load types or for additional sizes, please see the below links or call us today.

- Single Phase to Three Phase Rotary Converters for Easy Motor Loads
  - Single Phase to Three Phase Converters for Medium Motor Loads
  - Single Phase to Three Phase Converters for Hard Motor Loads
  - Single Phase to Three Phase Converters for Very Hard Motor Loads

At Larson Electronics, we do more than meet your lighting and power distribution needs. We also provide

replacement, retrofit, and upgrade parts as well as industrial grade power accessories. Our craftsmen can custom build any lighting or power distribution system and/or accessories to fit the unique demands of your operation. A commitment to honesty, quality, and dependability has made Larson Electronics a leader in the lighting and electronics business since 1973. Contact us today at 800-369-6671 or message sales@larsonelectronics.com for more information about our custom options tailored to meet your specific industry needs.

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

Frequently Asked Questions (FAQ)

There are no Faqs

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364



Image: MTPC-HD-RB-208V-7.5HP-3HP-N1

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364



Image: MTPC-HD-RB-208V-7.5HP-3HP-N1

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364



Image: MTPC-HD-RB-208V-7.5HP-3HP-N1



Image: MTPC-HD-RB-208V-7.5HP-3HP-N1

Export Control Classification Number (ECCN): EAR99

Links (Click on the below items to view):

- **Catalog Page - Product Series**(https://www.larsonelectronics.com/images/product/CatalogPage/243146.PDF)
- **MSDS (Material Safety Data Sheet**(https://www.larsonelectronics.com/images/product/Msds/243146.PDF)
- **Operations Manual**(https://www.larsonelectronics.com/images/product/Manual/243146.PDF)
- **Wiring Diagram**(https://www.larsonelectronics.com/images/product/WiringDiagram/243146.PDF)
- **HigResPic1**(https://www.larsonelectronics.com/images/product/HigResPic1/243146.JPG)
- **HigResPic2**(https://www.larsonelectronics.com/images/product/HigResPic2/243146.JPG)
- **HigResPic3**(https://www.larsonelectronics.com/images/product/HigResPic3/243146.JPG)
- **HigResPic4**(https://www.larsonelectronics.com/images/product/HigResPic4/243146.JPG)
- **HigResPic5**(https://www.larsonelectronics.com/images/product/HigResPic5/243146.JPG)
- **HigResPic6**(https://www.larsonelectronics.com/images/product/HigResPic6/243146.JPG)
- **HigResPic7**(https://www.larsonelectronics.com/images/product/HigResPic7/243146.JPG)
- **HigResPic8**(https://www.larsonelectronics.com/images/product/HigResPic8/243146.JPG)
- **HigResPic9**(https://www.larsonelectronics.com/images/product/HigResPic9/243146.JPG)
- **HigResPic10**(https://www.larsonelectronics.com/images/product/HigResPic10/243146.JPG)
- **Video1**(https://www.youtube.com/watch?v=OpGTt_iZfvg)
- **ISO 9001 Certification**(http://larsonelectronics.com/images/pdfdocs/ISO9001.PDF)
- **Business Certificate**(https://www.larsonelectronics.com/images/pdfdocs/w9.PDF)
- **Shipping Time Map**(https://www.larsonelectronics.com/images/product/ShippingTimeMap/ShippingTimeMap.pdf)