

### DCP-32x12-15A-WP

**Encapsulated DC to DC Stepdown Transformer - 32V DC to 12V DC - 15 Amps - Flying Leads - Waterproof**

**Product ID: 273501**

**Please see last page for supporting documentation for this product(certificates, CAD files & drawings, IES files, wiring diagrams, etc).**



**Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.**

#### DCP-32x12-15A-WP - DC to DC Step-down Transformer

Line In Voltage: 32V  
Line Out Voltage: 12V DC @ 15 Amps  
Watts: 180  
DC Input Connector: 6" Pigtail, Flying Leads  
DC Output Connector: 6" Pigtail, Flying Leads  
Voltage Accuracy: +/- 1.5%  
Output Frequency: 43 KHz  
Line-In Regulation: +/- 0.2%  
Line-Out Regulation: +/- 0.2%  
Temperature Coefficient: +/- 0.03% /°C  
Protection: Short Circuit/Overload/ Over Voltage  
Operating Temp: -10°C to +60°C  
Efficiency: 95%  
Dimensions: 3"-L x 3"-W x 1.25"-H  
Mounting: (2) Side Located Thru-Holes  
Weight: 0.75 Lbs

#### DCP-32x12-15A-WP Features

IP68 Rated Waterproof  
Overload, Short Circuit, Over Voltage Protection  
International Lighting Safety Standards Compliant  
Suitable For LED Moving Signs  
Suitable For Wet or Damp Locations

#### Special Orders - Special Requirements

Contact us for special requirements

Toll Free: 1-800-369-6671

Intl: 1-903-270-1187

Fax: 1-903-498-3364

E-mail: [sales@larsonelectronics.com](mailto:sales@larsonelectronics.com)

**The Larson Electronics DCP-32x12-15A-WP Waterproof DC to DC Step-down Transformer converts 32V DC electrical current to 12V DC at 15 amps max. This converter includes flying leads to hard wire this unit inline. This unit takes 32 volts DC and reduces it to 12 volts DC, allowing**

---

**users to use 32 volt DC power to operate equipment like our LED light bars and Golights that require low voltage 12 volts DC current.**

The DCP-32x12-15A-WP 180 watt power converter provides a safe and effective way for users to tap into and utilize 32 Volt DC power sources and step down this current to 12 Volts DC for use with equipment that requires 12V DC electrical power. This unit can be operated with input current ranging from 32V and will output 12 Volt DC current to power lights and equipment up to 180 watts and 15 amps at 12V DC. This power converter features an encapsulated IP68 waterproof design, making it suitable for indoor or outdoor use and is wet-damp area approved. This converter includes integral short circuit, over voltage, and overload protection that will shut down the unit or reduce output in case of faults and overloads to protect the unit and connected equipment from damage.

The small size and wide input voltage range of this unit make it ideal for indoor-outdoor operation of Larson Electronics LED light bars, Golights and other equipment that requires 12V DC current in locations where 32 volt DC power is readily available.

This converter is equipped with two 6" wires on the input side and two 6" wires on the output side. All leads are stripped and tinned for equip installation.

**Features:** The DCP-32x12-15A-WP converter features full range, universal DC input capability and can be operated with 32V. The unit converts this DC power input to 180 watt, 15 Amp 12VDC. IP68 rated, this unit is waterproof, wet and damp area approved and suitable for indoor or outdoor applications. Integrally designed protection includes overload, short circuit, and over voltage safeguards to prevent overheating and unit damage in case of faults or overly heavy current draw. This unit will limit current when an over current condition is encountered and recovers when the condition is removed. This unit will enter hiccup mode under short circuit conditions and recover when the fault is removed.

This transformer is enclosed a cast aluminum housing for heat distribution. All electronic components are encapsulated within the housing. This power converter has a -10°C to +60°C operating temperature range. This unit has a 95% conversion efficiency and is suitable for use with moving LED signs and similar LED equipment. These units have a fixed switching frequency at 43KHz.

**NOTE:** In order to obtain the best performance and the longest operational life from these units, it is recommended that you do not exceed 75% of the unit's output amperage. To determine if this converter suits your desired application, add together the total wattage of the equipment you intend to use with this unit and divide this total by 12 volts to find the total amperage draw that will be placed upon the converter. For example, if you are using two of our LEDP10W-120E 120 watt LED lights, 120 watts divided by 12 volts is 10 amps. This would mean the DCP-16-DP is well suited as it would run at under 75% capacity to produce the necessary 10 amps. Running these units at 100% of their capacity can create excess heat and lead to shortened converter life.

---

## Frequently Asked Questions (FAQ)



Export Control Classification Number (ECCN): EAR99

Links (Click on the below items to view):

- [HigResPic1](#)
- [HigResPic2](#)
- [ISO 9001 Certification](#)
- [Business Certificate](#)
- [Shipping Time Map](#)