Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

MT-UPM-R7-1P-GNF-15KVA-SZ-BB-A6-BM-CS-A-M1

15 KVA Overhead Distribution Transformer, Pole Mount, 4160GrdY/2400 Grounded Wye Pri., 120/240V Sec., Mineral Oil, Copper, ONAN, Arrestors, 304 Stainless

Product ID: 293217

Please see last page for supporting documentation for this product(certificates, CAD files & drawings, IES files, wiring diagrams, etc).



Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

MT-UPM-R7-1P-GNF-15KVA-SZ-BB-A6-BM-CS-A-M1 Pole Mount Overhead Transformer

Transformer Type: Overhead Distribution Transformer, Conventional Type
Transformer Configuration: Liquid Filled Pole Mounted
Transformer Polarity Type: Subtractive
Phase: Single Phase
Capacity: 15 KVA
Primary Voltage: 4160GrdY/2400
Primary Voltage Switch: N/A
Primary Voltage Class: 5 kV Class
Primary Phasor: Grounded Wye
Primary BIL: 60 kV
Secondary Voltage: 120/240V (L-N-L)
Secondary Voltage Class: 1.2 kV Class
Secondary Phasor: Dual Winding Single Phase
Secondary BIL: 30 KV
Frequency: 60 Hz
Temperature Rise: 65°C
Insulation Rating: Class E Insulation - 120°C, 248°F
Forced Air (Fans): None
Cooling Class: ONAN; Self-Cooled
Tap Changer: 5-Position Tap Changer w/ External Operating Handle
Tap Qty: (2) FCAN Above, (2) FCBN Below
Tap %: 2.5%
Tap Changer Switch Location: Middle of Tank Body, Left of Mounting Provisions
Impedance: 1.0-4.5% Typical

Ratings

Meets/Exceeds DOE 2016 Efficiency Ratings
Meets/Exceeds CSA Efficiency Ratings
Complies with ANSI / IEEE C57 12.00
Complies with ANSI / IEEE C57 12.20
Complies with ANSI / IEEE C57 12.30
Complies with ANSI / IEEE C57 12.31
Complies with ANSI / IEEE C57 12.35
Complies with ANSI / IEEE C57.12.70
Complies with ANSI / IEEE C62.11
Complies with ANSI / IEEE C62.22
Complies with ANSI / IEEE C2
Complies with ANSI / IEEE C37.47
Complies with ANSI Z535.4
Complies with ASTM D3487
Complies with ASTM D6871
Complies with 10 CFR Part 431
Complies with CSA C2.2:06
Complies with CAN / CSA C50
Complies with CAN / CSA C233.1-87
Complies with CAN / CSA C802.1-13
Complies with C2.1-06

Features:
Non-PCB Insulating Fluid

Primary Connection Type: Live Bushing Lug
Primary Termination: Porcelain High Voltage Bushing
Primary Connection Qty: (2)
Primary Lightning Arrestors: (2) Bolt-on High Voltage MCOV Lightning Arrestors, w/ Bird Guards, Side Mounted to Tank
Primary Lightning Mounting Provision: Mounting Provisions for Installing Lightning Arrestor on H1 & H2 Primary Terminals
Primary Lightning Arrestors Voltage Rating: 3 kV
Primary Lightning Arrestors MCOV Rating: 2.55 kV
Secondary Connection Type: Live Bushing Lug
Secondary Connections: Threaded Stud Terminals
Secondary Connection Qty: (3)
Secondary Neutral Connection: Secondary X2 Neutral Grounded to Tank via 1/2"-13 UNC Tapped Hole, 7/16" Deep Bung & Copper Ground Strap
Terminals: Tin Plated Primary and Secondary - Accepts Copper or Aluminum Connections
Grounding Provisions: (1) Lug w/ Grounding Strap, Tank Grounding Lug
Transformer Protection: N/A
Load Break Switch: N/A
Efficiency Standard(s): Meets DOE 2016 Standards, Meets CSA Standards Meets ANSI/IEEE Standards
K-Factor Rating (Harmonic Mitigation): K-1 (Standard)
Pulse Drive Rating: N/A
Insulation Fluid: Mineral Oil - Non PCB Fluid
Fluid Capacity*: 7.33 Gallons
Fluid Weight*: 66.14 lb
Liquid Level Indicator: Internal In-Tank Oil Level Line
Temperature Indicator: N/A
Pressure/Vacuum Indicator: N/A
Pressure Relief Device: Included, Automatic Action
Fault Indicator: N/A
Oil Level Marking: Internal
Fill Valve: N/A (Tank Filled via Removable Lid)
Drain Valve: 1/2" NPT Port w/ Removable Bolt
Winding Material: Copper
Ambient Temperature Rating: 40°C
Ambient Operating Temperature Range: -40°C to +40°C (-50°F to +104°F)
Sound Level: 48 dBA
Elevation Level: N/A
Core Material: Grain Oriented Steel
Tank Material: 304 Stainless Steel
Housing Material: 304 Stainless Steel w/ Corrosion Resistant Cover Band, Removable Top Cover
Hardware Material: Stainless Steel Hardware
Paint Type: Weatherproof and UV Resistant Epoxy Coating and Undercoating
Finish Color: White
Mounting: Double Hanger Bracket
Mounting: Pole Mount via Hangar Brackets
Lifting Lugs: Included
Dimensions*: 19.69"-W x 22.83"-D x 38.19"-H
Tank Diameter*: 16.14" OD
Dry Weight*: 132.28 lb
Total Weight (Liquid Filled)*: 256 lb
*Please note that numbers are approximate and subject to change

Lifting Lugs Included
Corrosion Resistant Cover Band

Efficiency: 98.50%

Based on transformer operating at 50% of nameplate base kVA.

Load Losses Based on 85°C Reference Temp.
No Load Loss (in watts): +/- 65W
Full Load Loss (in watts): +/- 254W
Total Load Loss (in watts): +/- 319W

Note: Losses offered are typical only, not guaranteed

Labeling:
Externally Stencilled (Painted) KVA Rating
Externally Stencilled (Painted) Voltage Rating
External Non-PCB Label
External Barcode Label
Stainless Steel Riveted Nameplate
100% Stainless Steel Construction, Corrosion Resistant

Factory Tests:
Winding Resistance Test
Insulation Resistance Test
Voltage Ratio Error Test
Short-circuit Impedance Test
No-load Loss (Wattage) Test
Load Loss (Wattage) Test
Induced Voltage Withstand Test
Separate Source Voltage Withstand Test
Pressure Integrity Test Test

Shipping:
Shipped on pallet on open flatbed
Palletized on Wooden Pallet w/ Skid Pockets
Pallet Skid Facing Outward Sides of Truck
Note: For low quantity purchases, enclosed truck can be requested
Note: Crated shipping in lieu of palletizing can be done upon request for an additional fee

Special Orders - Special Requirements
Contact us for special requirements
Toll Free: 1-800-369-6671
Intl: 1-903-270-1187
Fax: 1-903-498-3364
E-mail: sales@larsonelectronics.com

The MT-UPM-R7-1P-GNF-15KVA-SZ-BB-A6-BM-CS-A-M1 Overhead Distribution Pole Mounted Transformer from Larson Electronics offers powerful, reliable and efficient power distribution in outdoor and public locations. The low operating costs, low heat emissions and low cost of ownership makes this transformer ideal for a wide range of applications and businesses. This power distribution system is designed for overhead, pole mount installations and use.

PLEASE NOTE: ANY FREE SHIPPING OFFERS DO NOT APPLY TO POWER DISTRIBUTION PANELS, TRANSFORMERS, OR SUBSTATIONS*

Transformer Features: With a transformer rating of 15 kVA, the industrial transformer features a primary voltage of 4160GrdY/2400 Grounded Wye and a secondary voltage of single-phase 120/240V (L-L-N). This transformer connects to

a three phase electrical grid system to provide single phase low voltage power for indoor distribution. This pole mount transformer features porcelain high-voltage, dual bushings on the primary side and three bushings on the secondary side. Equipped with Copper windings and a grain oriented steel core, this overhead distribution transformer consists of one coil and two core loops. Tin plated terminals on the primary and secondary side accepts copper or aluminum connections.

The MT-UPM-R7-1P-GNF-15KVA-SZ-BB-A6-BM-CS-A-M1 is air cooled and does not have fans or mounting provision for fans. This unit features a 65°C temperature rise for reduced heat waste, increased reliability and longer life. The combination of low temperature rise and high efficiency makes this unit suitable for use in electrical rooms, air conditioned spaces in buildings, underground vaults and similar locations, in addition to outdoor areas.

Insulation Fluid: The MT-UPM-R7-1P-GNF-75KVA-SZ-BF-A6-BM-CZ-2ZZ-M1 features mineral oil insulation fluid. Internal marking is available for proper oil level monitoring. We offer transformers with FR-3 oil fluid, if needed.

Gauges: There are no gauges on this transformer. We can add liquid level, temperature and pressure/vacuum gauges at an additional cost. Standard liquid level, temperature and pressure/vacuum gauges are analog, manual reading types.

Pressure Relief Device: An automatic pressure relief device is included with this transformer.

Rapid Rise Relay: There are no rapid rise relays on the unit. This safety component is designed for protection when a rapid increase in tank pressure occurs. The relay is suitable for detecting sudden pressure fluctuations above predetermined safe limits.

Surge arresters: This system is not equipped with lightning arresters. Mounting provisions for installing customer provided lightning arrestor on the H1 and H2 primary terminal are included for installing arresters in-field.

Valves: The MT-UPM-R7-1P-GNF-15KVA-SZ-BB-A6-BM-CS-A-M1 is not equipped with fill or dtrain valves. The transformer can be filled via removing the top lid. A drain port w/ bolt plug is equipped.

Protection Fuses: This transformer does not contain fuses or circuit breakers. For units without protection fuses, up stream protection is provided. We recommend provisions for protection fuses when possible, as blown fuses may require more frequent oil changes.

Mount: The heavy-duty enclosure makes the unit suitable for and outdoor applications. Equipped with hangar brackets and lifting lugs, this overhead power distribution system can be mounted on poles.

Benefits: The MT-UPM-R7-1P-GNF-15KVA-SZ-BB-A6-BM-CS-A-M1 heavy-duty transformer offers many benefits to consumers. This transformer provides owners with significant energy savings, as well as offering environmental benefits. Higher efficiency not only extends the life of the transformer, but also turns into cost savings for owners in the form of lower energy bills and decreased cost of ownership.

We offer completely self protected (CSP) pole mount overhead transformers at an additional cost.

Applications: General purposes, industrial sites, electrical rooms, public locations, manufacturing facilities, steel plants, offshore, commercial, military, processing plants, electric power distribution, utilities, public locations and more. Larson Electronics is a manufacturer and as such can build stationary and portable transformer systems to your specifications. Although we carry several models of power distribution transformer systems, we can deliver custom ordered units almost as quickly as our prebuilt units. If this model does not meet your needs, please contact us at 1-800-369-6671 or sales@larsonelectronics.com to discuss your specific requirements.

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

Frequently Asked Questions (FAQ)

Q. What type of transformers does Larson Electronics offer?

A. Larson Electronics offered dry type transformers and liquid filled transformers. For liquid filled transformers, Larson Electronics' offers overhead distribution transformers (utility pole mount), pad mounted distribution transformers (mounts to a concrete pad), pad mounted power transformers, underground submersible distribution transformers, and substation transformers.

Q. What are the main benefits of a liquid filled transformer?

A. Liquid filled transformers have higher energy efficiency, durability, short circuit strength, low sound level, lower maintenance costs, and longer useful life expectancy compared to dry type transformers.

Q. What types of transformer liquids does Larson Electronics use?

A. Larson Electronics offered mineral oil fluid (ONAN) and biodegradable fluid (KNAN). On request we can provide brand name FR3 fluid or other brand name fluids for additional cost and lead time. All fluids offered by Larson Electronics are non-PCB containing fluids.

Q. What is the difference between mineral oil (ONAN) and biodegradable fluid (KNAN)?

A. Mineral oil has a flash point of 147-165°C. Biodegradable insulation fluids have a higher flash point up to 350°C. Using biodegradable fluids reduce the risk of potential fire due to the transformer overheating. Utilizing biodegradable fluids extends the lifespan on the transformer due to better insulation, higher flash point, better moisture resistance, and higher maximum voltage breakdown points over mineral oils.

Q. What is the difference between FR3 fluid and biodegradable fluid?

A. Envirotemp FR3 is a brand name of biodegradable ester oils made by Cargill. Cargill is not the only manufacturer of biodegradable ester fluids used for cooling liquid filled transformers. Larson Electronics stocks RAPO biodegradable fluid that exceeds testing for ASTM D6871. Cargill Envirotemp FR3 can be used in substitution of the standard biodegradable fluid. This substitution will increase cost and lead times.

Q. Do Larson Electronics transformers contain PCB?

A. All dry-type and liquid filled transformers manufactured by Larson Electronics are PCB (polychlorinated biphenyl) free at the time of shipment. Mixtures of polychlorinated biphenyls (PCB's) were banned commercially for use as transformers cooling fluids in 1977 due to being toxic, bio-accumulative, not at all biodegradable, and difficult to dispose of safely. None of Larson Electronics transformers contain PCB and only use PCB-free fluids.

Q. What are the transformer ratings?

A. IEEE Std C57.12.20 (Overhead Type), IEEE Std C57.12.34 (Three-Phase Pad-Mounted Compartmental), IEEE Std C57.12.38 (Single-Phase Pad-Mounted), IEEE Std C57.12.36 (Distribution Substation Transformers). For more detailed list of standards, please see the ASTM Certificate 1 link.

Q. Is this transformer UL Listed? Is this transformer CSA Listed?

A. By default, no. The majority of medium voltage transformer installations do not require certification by a Nationally Recognized Testing Laboratory (NRTL) unless being installed inside a building. Medium voltage equipment is built to and complies to ANSI, ASTM, DOE, IEEE, and NETA standards. UL is one of multiple NRTLs per OSHA certification for testing

facilities for USA standards. CSA is one of multiple NRTLs per Canada certification standards. For an additional fee, we can submit your order for NRTL testing after completion of build. This testing service is per order, requires payment of testing fees, and will increase lead time.

Q. What is the lifespan of a transformer?

A. The average lifespan of a liquid filled transformer is 25 years. Many transformers will survive past the 25 year mark and are still in service for up to 35 years.

Q. What is the difference between Loop Feed and Radial Feed?

A. Radial feed Transformers will have three high voltage bushings (H1, H2, and H3). There is one bushing for each phase to allow for the incoming high voltage cables. On Wye and Grounded Wye connected Transformers, there will also be an H0 bushing. Loop feed Transformers will have six high voltage bushings (H1A, H2A, H3A, H1B, H2B, and H3B). There are two bushings for each phase. This allows the customer to connect all of their Transformers in a loop configuration. It will also allow the customer to bring two feeds to the Transformer. A four position switch can be used to switch between the A feed and the B feed.

Q. What is the difference between Dead Front and Live Front?

A. Live-front: The voltage-carrying parts are exposed. Live-front terminations have high voltage connectors, arresters, or fuses are exposed to the operator after cabinet has been opened. Dead-front: Often referred to as dead-front bushings. Safety is enhanced as there are no current-carrying parts exposed to the operator. For overhead distribution transformers and underground submersible transformers, live front is common. For pad mount transformers, the primary is typically dead front and the secondary is live front. Protection barriers can be added to live front pad mounted transformers

Q. What is the difference between copper and aluminum windings inside the transformer?

A. Transformers wound with aluminum or copper wire have similar losses and performance. The choice of using copper or aluminum windings depends upon the application and the individual preferences. The type of winding material does not affect the transformer's reliability. A transformer's life is defined by the life of its insulation system.

Q. How many BTU's of heat does a transformer generate?

A. The heat a transformer generates is dependent upon the transformer losses. To determine air conditioning requirements multiply the sum of the full load losses (obtained from factory or test report) of all transformers in the room by 3.41 to obtain the BTUs/hour. For example: A transformer with losses of 2000 watts will generate 6820 BTUs/hour.

Q. Do you have to ground this transformer?

A. In most cases the enclosure of the transformer is grounded for safety reasons. However, a transformer will function properly without being grounded. Be sure to research all grounding requirements for your specific application against the NETA and NEC as well as any local electrical codes.

Q. What types of transformer protection are available?

A. For over-current protection, Larson Electronics offers Fuses, breakers and interrupters. For over-voltage protection, Larson Electronics offers arresters. Larson Electronics can provide both Primary and Secondary protection equipment.

Q. What is required for mounting this transformer?

A. This unit mounts via hanging brackets to a utilty pole. Additional brackets can be purchased for mounting multiple

transformers to a single pole.

Q. Does my primary and secondary voltage matter for a transformer?

A. Yes, this matters greatly. For primary voltage, most transformers will be equipped with a tap changer for small primary voltage changes due to voltage drop for losses experienced in the transmission line. Some transformers will be equipped with dual voltage primaries with a voltage selector switch to choose which voltage to operate the transformer on. In both cases, these are designed to provide a steady output voltage. It is very important to confirm what voltage your primary voltage being delivered from the utility provider and what the required electrical voltage for the building or house is. You cannot only provide the KVA size, or the abbreviated primary voltage as there is not standardized voltage across the country and each region can be different. Once manufacturing has started, these cannot be changed.

Q. Where is the detailed dimensional drawing for this unit?

A. We can provide a feature drawing that shows accessories and estimated form factor. Due to the variety of options and varying voltages, an exact dimensional drawing for the specific unit you have ordered is not available until after purchase and engineering has completed the drawing for your sales order. We do not offer completed detailed engineered drawings before purchase. The feature drawings are detailed enough for concrete pad designs and preliminary engineering site designs.

Q. What is the warranty of this transformer?

A. 12 months from point of connecting electrical service to the transformer or 18 months from point of ordering, whichever comes first.

Q. Can this transformer be customized?

A. Yes, Larson Electronics allows for customization of all transformers. Please send customization requests to sales@larsonelectronics.com. If you have an engineered specification or engineered drawings, please provide those at the time of request.


MISTER

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364




100
LARSON
ELECTRONICS



Harmonized System (HS) Code: 85043300
Export Control Classification Number (ECCN): EAR99

Links (Click on the below items to view):

- **ANSI Certificate 1**
- **FCC Certificate (Federal Communications Commission, USA)**
- **MSDS (Material Safety Data Sheet**
- **HigResPic1**
- **HigResPic2**
- **HigResPic3**
- **HigResPic4**
- **HigResPic5**
- **HigResPic6**
- **HigResPic7**
- **Video1**
- **ISO 9001 Certification**
- **Business Certificate**
- **Shipping Time Map**