Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

Product ID: 313432

Please see last page for supporting documentation for this product (certificates, CAD files & drawings, IES files, wiring diagrams, etc).

Image:

Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

IND-SFC-3P-200KVA-480V-60HZ-400V-50HZ-M1 Voltage-Frequency Converter

Unit Type: Solid-State Static Voltage Frequency Converter
Dimensions: 47.24" x 29.52" x 50.00"
Weight: 1267.6 lb
Input Voltage: 480V 3PH +/- 5% 3P3W+G
Input Frequency: 60 Hz +/- 10%
Input Current Distortion: 5%
Power Factor: 0.99
Inrush Current: 50% of full load current
Capacity: 75 kVA - 100% Load - 30 Mins
Output Voltage: 400V 3PH +/- 2% 3P3W+G
Output Frequency: 50 Hz +/- 10%
Over Load: 100% continues , 110% for 60 min, 125% for 10 min, 150% for 2 min, 200% for 20 sec
Voltage Regulation: ±1.0% under all conditions
Frequency Regulation: ±0.01 % under all conditions
Crest Factor: 1.414 ±3%
Rectification: IGBT
Efficiency Ratio: @ full load 92%
Phase Angle Regulation: ±2° for balanced loads, ±4° for unbalanced loads
Harmonic Distortion: 3% maximum (linear loads)
Load Stabilization Rate: < +/- 1%
Harmonic Distortion: Pure Sine Wave < 2%

Features/Ratings

NRTL Listed to UL 508A
Advance Microprocessor Control
True Online Double Conversion
Smart Fan Control
Low Input THDi < 3%

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

4-digit Meters: Digital Frequency Meter- Resolution 0.1Hz/Step; Digital Voltage Meter- Resolution 0.1V; Digital Ammeter- Resolution 0.1A; Digital Watt Meter- Resolution 0.1W
Enclosure Protection Class: NEMA 3RX
Protection: Over/Under voltage, Loss of Phase, Over Current, Short Circuit, Transient Voltage
Noise Level: <65 dBA at 5 feet
Operating Temp. Range: -40°C TO +55°C
Relative Humidity: 0-95% (Non-condensation)
Mounting: Mobile Cart w/ Wheels
Color: Tan

Special Orders - Special Requirements

Contact us for special requirements
Intl: 1-903-270-1187
Toll Free: 1-800-369-6671
Fax: 1-903-765-7664
E-mail: sales@larsonelectronics.com

The IND-SFC-3P-200KVA-480V-60HZ-400V-50HZ-M1 from Larson Electronics is a Solid-State Voltage Frequency Converter that is designed for voltage and frequency rectification in industrial locations. This 200 kVA static converter comes with an input voltage/frequency of 480 V three-phase 60 Hz and an output voltage/frequency of 400 V three-phase 50 Hz. This unit is mobile via four wheels at the bottom of the enclosure.

The IND-SFC-3P-200KVA-480V-60HZ-400V-50HZ-M1 can be used to accurately convert voltages and frequencies in industrial sites. This 75 kVA unit offers three-phase 480 V, 60 Hz on the input side and three-phase 400 V, 50 Hz on the output side. During operation, rectification is completed via IGBT. The static frequency converter provides robust microprocessor control, true online double conversion, and active input power factor correction.

This solid-state frequency converter is equipped with several protective features, including overload, short circuit, over temp, instant power failure connection and alarm. For efficient operation, the unit features smart fan control and ultra high efficiency (98% in Smart Eco Mode). Operators are provided access to a panel, which houses various controls for meters. Available meter components include digital frequency meter, digital voltage meter, digital ammeter, and digital watt meter.

Mounting: The IND-SFC-3P-200KVA-480V-60HZ-400V-50HZ-M1 is secured inside a mobile enclosure with wheels for seamless mobility around the work site.

Applications: Industrial facilities, laboratories, air compressor testing, power supply testing, motor equipment testing, quality assurance, lighting systems, and more.

At Larson Electronics, we do more than meet your lighting needs. We also provide replacement, retrofit, and upgrade parts as well as industrial grade power accessories. Our craftsmen can custom build any lighting system and/or accessories to fit the unique demands of your operation. A commitment to honesty, quality, and dependability has made Larson Electronics a leader in the lighting and electronics business since 1973. Contact us today at 800-369-6671 or message sales@larsonelectronics.com for more information about our custom options tailored to meet your specific industry needs.

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

Frequently Asked Questions (FAQ)

There are no Faqs

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

Image:

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

Image:

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

Image:

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

Image:

Product ID: 313432

Export Control Classification Number (ECCN): EAR99

Links (Click on the below items to view):

- **Operations Manual**(https://www.larsonelectronics.com//images/product/Manual/313432.PDF)
- **HigResPic1**(https://www.larsonelectronics.com//images/product/HigResPic1/313432.JPG)
- **HigResPic2**(https://www.larsonelectronics.com//images/product/HigResPic2/313432.JPG)
- **HigResPic3**(https://www.larsonelectronics.com//images/product/HigResPic3/313432.JPG)
- **HigResPic4**(https://www.larsonelectronics.com//images/product/HigResPic4/313432.JPG)
- **HigResPic5**(https://www.larsonelectronics.com//images/product/HigResPic5/313432.JPG)
- **HigResPic6**(https://www.larsonelectronics.com//images/product/HigResPic6/313432.JPG)
- **HigResPic7**(https://www.larsonelectronics.com//images/product/HigResPic7/313432.JPG)
- **HigResPic8**(https://www.larsonelectronics.com//images/product/HigResPic8/313432.JPG)
- **HigResPic9**(https://www.larsonelectronics.com//images/product/HigResPic9/313432.JPG)
- **Video1**(https://www.youtube.com/watch?v=jVnTdFuOqt0)
- **ISO 9001 Certification**(http://larsonelectronics.com/images/pdfdocs/ISO9001.PDF)
- **Business Certificate**(https://www.larsonelectronics.com/images/pdfdocs/w9.PDF)
- **Shipping Time Map**(https://www.larsonelectronics.com/images/product/ShippingTimeMap/ShippingTimeMap.pdf)