Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

MT-PML-R7-3P-DMV-1.5MVA-YJ-LT-DF-A6-BMF-CZ-2B6-M1

1.5 MVA Pad Mount Transformer - 11000V Delta Primary, 415Y/240 Wye-N Secondary - ONAN/ONAF - Bell Green

Product ID: 314154

Please see last page for supporting documentation for this product(certificates, CAD files & drawings, IES files, wiring diagrams, etc).



Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

MT-PML-R7-3P-DMV-1.5MVA-YJ-LT-DF-A6-BMF-CZ-2B6-M1 3PH Pad Mount Transformer

Transformer Type: Pad Mounted, Compartmental-Type
Transformer Configuration: Liquid Filled Pad Mounted
Transformer Feed Type: Loop Feed
Phase: Three Phase
Capacity: 1.5 MVA (1500 KVA)
Vector Group: Dyn11
Primary Voltage: 11000V
Primary Voltage Class: 15 kV Class
Primary Phasor: Delta
Primary BIL: 95 KV
Secondary Voltage: 415Y/240
Secondary Voltage Class: 1.2 kV Class
Secondary Phasor: Wye-N
Secondary BIL: 30 KV

Frequency: 60 Hz

Temperature Rise: 65°C
Cooling Class: ONAN/ONAF; Self-Cooled/Fan-Cooled
Forced Air (Fans): Included
Tap Changer: 5-position Tap Changer
Tap Qty: (2) FCAN Above Taps, (2) FCBN Below Taps
Tap %: 2.5%
Tap Changer Switch Location: High Voltage (HV) Front Compartment
Impedance (Typical): 5.0-7.5% Typical

Ratings

Meets/Exceeds DOE 2016 Efficiency Ratings
Complies with ANSI / IEEE C57.12.00
Complies with ANSI / IEEE C57 12.28
Complies with ANSI / IEEE C57 12.34
Complies with ANSI / IEEE C57.12.70
Complies with ASTM D3487
Penta-head Entry Assembly
High-Fire Point Natural Ester Insulating Fluid
Non-PCB Insulating Fluid
Tamper Proof Housing
Hinged Front Compartment Doors, Pad Lockable
Hot Stick Included, HV Door Mount

Efficiency %: 99.30%
Based on transformer operating at 50% of nameplate base kVA.

Load Losses Based on 85°C Reference Temp.
No Load Loss (in watts)): +/- 1,900W
Full Load Loss (in watts) at 100%: +/- 10,500W
Total Load Loss (in watts) at 100%: +/- 12,400W

Total Losses at 55°C LL Temp.& 20°C NL Temp.
Total Load Loss (in watts) at 50%: +/- 4,375W

Primary Connection Type: Dead Front
Primary Termination: Standoff Well Bushings w/ Removable Studs, 600A Dead Break Elbows
Primary Connection Qty: (6) Primary Connections w/ (6) Standoff Brackets for Parked Elbows
Primary Surge Arrestors: (3) High Voltage Elbow Surge Arrestors
Primary Surge Arrestor Voltage Rating: 12 kV Class
Primary Surge Arrestor MCOV Rating: 10.2 kVrms
Primary Over Current Protection (OCP): Bayonet Fuses
Primary Over Current Protection Method: Fused
Primary Over Current Protection Holder: Bayonet Fuse Holder w/ Drip Shield
Secondary Connection Type: Live Font
Secondary Connections: NEMA Spade Terminals, 6-Hole Spade, Externally Clamped, Accepts up to (3) Double Lug connections with (3) cables per side of Spade connector
Secondary Connection Qty: (4), Staggered Terminal Arrangement
Secondary Over Current Protection (OCP): N/A
Grounding Provisions: (1) Grounding lug
Metering Current Transformer (CT): N/A
Metering Panel: N/A
Auxiliary Control Panel : N/A
Load Break Switch: 2-Position Load Break Switch
Load Break Switch Qty: (3)
Load Break Switch Location: High Voltage (HV) Front Compartment
Efficiency Standard(s): Meets DOE 2016 Standards, Meets ANSI/IEEE Standards
K-Factor Rating (Harmonic Mitigation): K-1 (Standard)
Pulse Drive Rating: N/A
Insulation Fluid: Mineral Oil Insulating Fluid, Non-PCB Fluid
Fluid Capacity: 281 Gallons
Liquid Level Indicator: Analog Dial Gauge
Temperature Indicator: Analog Dial Gauge
Pressure/Vacuum Indicator: Analog Dial Gauge
Pressure Relief Device: Included, Automatic Action
Fill Valve: Removable Bolt
Fill Valve Location: Front Compartment
Drain Valve: Included, Drain Valve w/ Sampler
Drain Valve Location: Front Compartment
Winding Material: Copper
Ambient Temperature Rating: 40°C
Sound Level: 60 dBA
Elevation Rating: 3300ft (1000 meters) Above Sea Level
Core Material: Grain Oriented Steel
Tank Material: Coated Steel
Cabinet Material: Coated Steel
Base Platform Material: Coated Steel
Enclosure Rating: NEMA 3R Weatherproof
Housing Type: Compartmental Air-Filled Cabinet w/ Locking Doors, HV Compartment Left, LV Compartment Right, Steel Barrier Separation
Paint Type: Weatherproof and UV Resistant Epoxy Coating and Undercoating
Finish Color: Munsell™ 7.0 GY 3.29/1.5 Bell Green

Note: *Losses offered are typical only, not guaranteed*

Mounting: Pad Mounted

Conduit Opening: Bottom Feed Underground Entry/Exit

Dimensions: 75"-W x 73"-D x 73"-H

Weight: 9,800 lbs

*Please note that numbers are approximate and subject to change

Special Orders - Special Requirements
Contact us for special requirements

Toll Free: 1-800-369-6671

Intl: 1-903-270-1187

Fax: 1-903-498-3364

E-mail: sales@larsonelectronics.com

The MT-PML-R7-3P-DMV-1.5MVA-YJ-LT-DF-A6-BMF-CZ-2B6-M1 from Larson Electronics is an Industrial Pad Mount Transformer that offers powerful, reliable, and efficient power distribution in indoor, outdoor, and public locations. The low operating costs, low heat emissions, and low cost of ownership makes this transformer ideal for a wide range of applications and businesses. An enclosed design caters to installations on concrete pads without protective fencing.

PLEASE NOTE: ANY FREE SHIPPING OFFERS DO NOT APPLY TO POWER DISTRIBUTION PANELS, TRANSFORMERS, OR SUBSTATIONS*

Transformer Features: With a transformer rating of 1500 KVA (1.5 MVA), the industrial transformer features a rated primary voltage of three-phase

11000V Delta and a secondary voltage of three-phase 415Y/240 Wye-N. The unit has a primary loop feed for dual installations and dead-front primary connections. This transformer features a 5-position tap changer with two, +/- 2.5% taps above and two, +/- 2.5% taps below to allow small changes for voltage.
Copper transformer winding material helps improve performance, reduce weight and lower cost. Compared to aluminum, copper windings have lower eddy losses due to higher resistivity. This transformer consists of rectangular coil and five-legged wound core design with three coils and four core loops (this is for three-phase transformers only; single-phase units have one coil and two core loops). The MT-PML-R7-3P-DMV-1.5MVA-YJ-LT-DF-A6-BMF-CZ-2B6-M1 has fans for forced air cooling.
Enclosure Design: This pad mounted transformer is a compartmental design. The tank and housing are fabricated from steel. The front electrical enclosure carries a NEMA 3R rating. The high voltage and low voltage compartments are located in front of the transformer tank, with the high voltage compartment on the left side and low voltage compartment on the right side. The HV and LV compartments are air filled and separated by a full length steel barrier between the compartments. A removable steel plate at the base of the HV and LV compartments prevents rodents and other intrusions from entering the enclosure once installed. This steel plate allows for underground conduit entry into the enclosure compartments. Two hinged exterior doors allows for access into the compartments. A single pad lockable handle on the low voltage compartment door allows for securing the transformer. A spring loaded pin within the low voltage compartment prevents the high voltage door from being opened without pulling the safety pin. A hot stick is included in the high voltage compartment, mounted to the HV door.
Temperature Rise: This unit features 65°C temperature rise for reduced heat waste, increased reliability and longer life. At 65°C temperature rise, the transformer offers 1500 KVA (1.5 MVA). The transformer meets standard efficiency requirements. The combination of low temperature rise and high efficiency makes this unit suitable for use in electrical rooms, air conditioned spaces in buildings, underground vaults and similar locations, in addition to outdoor areas.
Insulation Fluid: The MT-PML-R7-3P-DMV-1.5MVA-YJ-LT-DF-A6-BMF-CZ-2B6-M1 features mineral oil cooling fluid (ONAN/ONAF) with a capacity of 281 gallons. We offer transformers with biodegradable or FR-3 oil fluid, if needed.
Biodegradable Fluid: Biodegradable cooling fluid (vegetable oil) has a higher heat capacity compared to mineral oil, making the liquid safer to use and more reliable during operations. Vegetable oil has a higher flash point and fire point than mineral oil, hydrocarbon oil, silicone oil and synthetic ester. This cooling fluid is also non-toxic and can tolerate higher breakdown voltages than mineral oil. When operating at high temperatures, biodegradable cooling liquid sustains up to 120% loan conditions, which helps preserve the transformer's lifespan and performance.
Gauges: The following gauges are included with the system: liquid level, temperature and pressure/vacuum gauges. Standard liquid level, temperature and pressure/vacuum gauges are analog, manual reading types. These gauges do not have auxiliary contacts.
Fault Pressure Devices: This transformer features an automatic action fault pressure device. Fault pressure devices are used to detect high rates of pressure rise within the tank.
Rapid Rise Relay: There are no rapid rise relays on the unit. This safety component is designed for protection when a rapid increase in tank pressure occurs. The relay is suitable for detecting sudden pressure fluctuations above predetermined safe limits.
Surge arresters: This system comes with high elbow surge arresters on the primary side. Designed for over-voltage and transient voltage protection, the components prevent damage caused by lightning, internal switching or voltage surges. We can offer models without high elbow surge arresters that have mounting provisions for customer-provided surge arresters.

Load Break Switch: This transformer is equipped with three independently operated 2-position load break switches. One is for the transformer, one is for the Primary A lines, and one is for the Primary B lines.
Valves: The MT-PML-R7-3P-DMV-1.5MVA-YJ-LT-DF-A6-BMF-CZ-2B6-M1 is equipped with a pressure relief valve, fill valve, and drain valve with sampler port.
Protection Fuses: This transformer contains protection fuses. For units without protection fuses, up stream protection is provided. We recommend provisions for protection fuses when possible, as blown fuses may require more frequent oil changes.
Mount: The heavy-duty enclosure makes the unit suitable for both indoor and outdoor applications. This power distribution system can be pad mounted on concrete pads.
Benefits: The MT-PML-R7-3P-DMV-1.5MVA-YJ-LT-DF-A6-BMF-CZ-2B6-M1 pad mount transformer offers many benefits to consumers. This transformer provides owners with significant energy savings, as well as offering environmental benefits. Higher efficiency not only extends the life of the transformer, but also turns into cost savings for owners in the form of lower energy bills and decreased cost of ownership.
Applications: General purposes, industrial sites, electrical rooms, underground vaults, manufacturing facilities, steel plants, offshore, commercial, military, processing plants, electric power distribution, utilities, public locations, and more. Larson Electronics is a manufacturer and as such can build stationary and portable transformer systems to your specifications. Although we carry several models of power distribution transformer systems, we can deliver custom ordered units almost as quickly as our prebuilt units. If this model does not meet your needs, please contact us at 1-800-369-6671 or sales@larsonelectronics.com to discuss your specific requirements.

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

Frequently Asked Questions (FAQ)


Non PCB
NOTICE
WARNING
ADVERTENCIA

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364







Export Control Classification Number (ECCN): EAR99

Links (Click on the below items to view):

- HigResPic1
- HigResPic2
- HigResPic3
- HigResPic4
- HigResPic5
- HigResPic6
- HigResPic7
- HigResPic8
- HigResPic9
- HigResPic10
- Video1
- Video2
- ISO 9001 Certification
- Business Certificate
- Shipping Time Map