Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

MT-PML-R7-3P-DMQ-75KVA-YT-LT-DF-A6-BM-AS-2C6-M1

75 KVA Pad Mount Transformer - 13200V Delta Primary, 208Y/120 Wye-N Secondary, Aluminum, 304L Stainless Steel, ONAN, Bell Green

Product ID: 342311

Please see last page for supporting documentation for this product (certificates, CAD files & drawings, IES files, wiring diagrams, etc).



Image: MT-PML-R7-3P-DMQ-75KVA-YT-LT-DF-A6-BM-AS-2C6-M1

Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

MT-PML-R7-3P-DMQ-75KVA-YT-LT-DF-A6-BM-AS-2C6-M1 3PH Pad Mount Transformer

Transformer Type: Pad Mounted, Compartmental-Type
Transformer Configuration: Liquid Filled Pad Mounted
Transformer Primary Feed Type: Loop Feed
Phase: Three Phase
Capacity: 75 KVA
Vector Group: Dyn1
Primary Voltage: 13200V
Primary Voltage Class: 15 kV Class
Primary Phasor: Delta
Primary BIL: 95 KV
Secondary Voltage: 208Y/120
Secondary Voltage Class: 1.2 kV Class
Secondary Phasor: Wye-N
Secondary BIL: 30 KV
Frequency: 60 Hz
Temperature Rise: 65°C
Cooling Class: ONAN; Self-Cooled
Forced Air (Fans): None
Tap Changer: 5-position Tap Changer
Tap Qty: (2) FCAN Above Taps, (2) FCBN Below Taps

Ratings

Meets/Exceeds DOE 2016 Efficiency Ratings
Complies with ANSI / IEEE C57.12.00
Complies with ANSI / IEEE C57 12.28
Complies with ANSI / IEEE C57 12.34
Complies with ANSI / IEEE C57.12.70
Complies with ASTM D3487
Penta-Head Cabinet Hardware
Hot Stick Included, HV Door Mount
Non-PCB Insulating Fluid
Tamper Proof Housing
Hinged Front Compartment Doors, Padlockable

Factory Tests:

Winding Resistance Test
Insulation Resistance Test
Voltage Ratio Error Test
Short-circuit Impedance Test
No-load Loss (Wattage) Test
Load Loss (Wattage) Test
Induced Voltage Withstand Test

Tap %: 2.5%
Tap Changer Switch Location: High Voltage (HV) Front Compartment
Tap Changer Switch Rating: 100A, 15 kV
Impedance (Typical): 1.0-5.0% Typical, 5.75% Target
Primary Termination Style: Dead Front
Primary Bushings: (6) 200 amp Cooper bushing wells with removable studs
Primary Inserts: (6) 15 kV, 95 kV BIL load-break inserts
Primary Surge Arrestors: (3) High Voltage Varistar Elbow Arresters, 15 kV Class
Primary Surge Arrestor Voltage Rating: 10 kV Class
Primary Surge Arrestor MCOV Rating: 8.4 kVrms
Primary Over Current Protection (OCP): (3) Bayonet Expulsion Fuses in series with Partial-Range Current-Limiting Fuses
Primary Over Current Protection Method: Fused
Primary Over Current Protection Holder: (3) Copper Bayonet Fuse Holder w/ Drip Shield
Secondary Termination Style: Live Front
Secondary Feed Type: Radial Feed
Secondary Connections: 1" copper stud with 4-hole screw-on spade bushings
Secondary Connection Qty: (4), In-Line Terminal Arrangement
Secondary Connection Support: Included, Standard LV Bushing Support Assembly
Secondary Over Current Protection (OCP): N/A
Grounding Provisions: (3) IEEE standard one-hole ground pads
Metering Current Transformer (CT): N/A
Metering Panel: N/A
Auxiliary Control Panel: N/A
Load Break Switch: 2-Position Load Break Switch, 15-38 KV, 300A
Load Break Switch Qty: (3)
Load Break Switch Location: High Voltage (HV) Front Compartment
Efficiency Standard(s): Meets DOE 2016 Standards, Meets ANSI/IEEE Standards
K-Factor Rating (Harmonic Mitigation): K-1 (Standard)
Pulse Drive Rating: N/A
Insulation Fluid: Mineral Oil - Non PCB Fluid
Fluid Capacity: 75 Gallons
Liquid Level Indicator: Magnetic Dial Gauge
Temperature Indicator: Dial-Type Thermometer
Pressure/Vacuum Indicator: Analog Dial Gauge
Pressure Relief Valve: Included, 50 SCFM
Fill Valve: Removable Plug
Fill Valve Location: LV Compartment
Drain Valve: Included, 1" w/ 1" Sampler and lockable cover
Drain Valve Location: LV Compartment
Schrader Valve: Included
Ground Bus: Included, Copper, in HV & LV compartments
Nitrogen Blanket: Included
Winding Material: Aluminum
Ambient Temperature Rating: 40°C
Sound Level: 51 dBA
Elevation Rating: 3300ft (1000 meters) Above Sea Level
Core Material: Grain Oriented Steel
Tank Material: 304L Stainless Steel
Cabinet Material: 304L Stainless Steel
Base Platform Material: 304L Stainless Steel
Nameplate Material: Stainless Steel
Cover Type: Bolted Cover
Enclosure Rating: NEMA 3R Weatherproof
Hardware: Corrosion-proof cabinet hardware, Corrosion-proof bushing clamps and hardware, Corrosion-proof cover hardware
Housing Type: Compartmental Air-Filled Cabinet w/ Locking Doors, HV Compartment Left, LV Compartment Right, Steel Barrier Separation

Separate Source Voltage Withstand Test
Pressure Integrity Test
Dissolved Gas in Oil Analysis

Paint Type: Weatherproof and UV Resistant Epoxy Coating and Undercoating
Finish Color: Munsell™ 7.0 GY 3.29/1.5 Bell Green
Mounting: Pad Mounted
Conduit Opening: Bottom Feed Underground Entry/Exit
HV Compartment Base Wireway Dimensions: 20"-W x 5"-D

LV Compartment Base Wireway Dimensions: 16"-W x 5"-D

Cabinet Depth: 20"
Dimensions: 61"-W x 43"-D x 69"-H
Total Weight: 2,160 lbs
Packaging: Pallet
*Please note that numbers are approximate and subject to change

Special Orders - Special Requirements

Contact us for special requirements
Toll Free: 1-800-369-6671
Intl: 1-903-270-1187
Fax: 1-903-765-7664
E-mail: sales@larsonelectronics.com

The MT-PML-R7-3P-DMQ-75KVA-YT-LT-DF-A6-BM-AS-2C6-M1 Industrial Pad Mount Transformer from Larson Electronics offers powerful, reliable, and efficient power distribution in indoor, outdoor, and public locations. The low operating costs, low heat emissions, and low cost of ownership make this transformer ideal for a wide range of applications and businesses. An enclosed design caters to installations on concrete pads without protective fencing.

PLEASE NOTE: ANY FREE SHIPPING OFFERS DO NOT APPLY TO POWER DISTRIBUTION PANELS, TRANSFORMERS, OR SUBSTATIONS*

Transformer Features: With a transformer rating of 75 KVA, the industrial transformer features a primary voltage of three-phase 13200V Delta and a secondary voltage of three-phase 208Y/120 Wye-N. The unit has a primary loop feed for single installations and dead-front primary connections. We also offer systems with loop feed and live front primary connections. This transformer features a 5-position tap changer with two +2.5% taps above and two -2.5% taps below to allow small changes in voltage.

The system features aluminum windings for high strength and thermal/electrical conductivity. This transformer consists of a rectangular coil and a five-legged wound core design with three coils and four core loops (this is for three-phase transformers only; single-phase units have one coil and two core loops).

The MT-PML-R7-3P-DMQ-75KVA-YT-LT-DF-A6-BM-AS-2C6-M1 is air cooled and does not have fans or mounting provision for fans.

Enclosure Design: This pad mounted transformer is a compartmental design. The tank and housing are fabricated from 304L stainless steel. The front electrical enclosure carries a NEMA 3R rating. The high voltage and low voltage compartments are located in front of the transformer tank, with the high voltage compartment on the left side and low voltage compartment on the right side. The HV and LV compartments are air filled and separated by a full length steel barrier between the compartments. A removable stainless steel plate at the base of the HV and LV compartments prevents rodents and other intrusions from entering the enclosure once installed. This stainless steel plate allows for underground conduit entry into the enclosure compartments. Two hinged exterior doors allow for access into the compartments. A single pad lockable handle on the low voltage compartment door allows for securing the transformer. A spring loaded pin within the low voltage compartment prevents the high voltage door from being opened without pulling the safety pin. A hot stick is included in the high voltage compartment, mounted to the HV door.

Temperature Rise: This unit features 65°C temperature rise for reduced heat waste, increased reliability and longer life. At 65°C temperature rise, the transformer offers 75 KVA. The transformer meets standard efficiency requirements. The combination of low temperature rise and high efficiency makes this unit suitable for use in electrical rooms, air conditioned spaces in buildings, underground vaults and similar locations, in addition to outdoor areas.

Insulation Fluid: The MT-PML-R7-3P-DMQ-75KVA-YT-LT-DF-A6-BM-AS-2C6-M1 features mineral oil insulation fluid. We offer transformers with biodegradable or FR-3 oil fluids, if needed.

Biodegradable Fluid: Biodegradable cooling fluid (vegetable oil) has a higher heat capacity compared to mineral oil, making the liquid safer to use and more reliable during operations. Vegetable oil has a higher flash point and fire point than mineral oil, hydrocarbon oil, silicone oil and synthetic ester. This cooling fluid is also non-toxic and can tolerate higher breakdown voltages than mineral oil. When operating at high temperatures, biodegradable cooling liquid sustains up to 120% loan conditions, which helps preserve the transformer's lifespan and performance.

Gauges: The following gauges are included with the system: liquid level, temperature and pressure/vacuum gauges. Standard liquid level, temperature and pressure/vacuum gauges are analog, manual reading types.

Fault Pressure Devices: This transformer features an automatic action fault pressure device. Fault pressure devices are used to detect high rates of pressure rise within the tank.

Rapid Rise Relay: There are no rapid rise relays on the unit. This safety component is designed for protection when a rapid increase in tank pressure occurs. The relay is suitable for detecting sudden pressure fluctuations above predetermined safe limits.

Surge arresters: This system comes with high elbow surge arresters on the primary side. Designed for over-voltage and transient voltage protection, the components prevent damage caused by lightning, internal switching or voltage surges. We can offer models without high elbow surge arresters that have mounting provisions for customer-provided surge arresters.

Load Breaker Switch: The transformer is equipped with a load break switch [(3) two-position load break switch / 300A].

Valves: The MT-PML-R7-3P-DMQ-75KVA-YT-LT-DF-A6-BM-AS-2C6-M1 is equipped with a pressure relief valve, fill valve and drain valve with a sampler port.

Protection Fuses: This transformer contains bayonet protection fuses on the primary side. For units without protection fuses, upstream protection is provided. We recommend provisions for protection fuses when possible, as blown fuses may require more frequent oil changes.

Mount: The heavy-duty enclosure makes the unit suitable for both indoor and outdoor applications. This power distribution system can be pad mounted on concrete pads.

Benefits: The MT-PML-R7-3P-DMQ-75KVA-YT-LT-DF-A6-BM-AS-2C6-M1 pad mount transformer offers many benefits to consumers. This transformer provides owners with significant energy savings, as well as offering environmental benefits. Higher efficiency not

only extends the life of the transformer, but also turns into cost savings for owners in the form of lower energy bills and decreased cost of ownership.

Applications: General purposes, industrial sites, electrical rooms, underground vaults, manufacturing facilities, steel plants, offshore, commercial, military, processing plants, electric power distribution, utilities, public locations and more.

Larson Electronics is a manufacturer and as such can build stationary and portable transformer systems to your specifications. Although we carry several models of power distribution transformer systems, we can deliver custom ordered units almost as quickly as our prebuilt units. If this model does not meet your needs, please contact us at 1-800-369-6671 or sales@larsonelectronics.com to discuss your specific requirements.

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

Frequently Asked Questions (FAQ)

There are no Faqs

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Image: MT-PML-R7-3P-DMQ-75KVA-YT-LT-DF-A6-BM-AS-2C6-M1

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Image: MT-PML-R7-3P-DMQ-75KVA-YT-LT-DF-A6-BM-AS-2C6-M1

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Image: MT-PML-R7-3P-DMQ-75KVA-YT-LT-DF-A6-BM-AS-2C6-M1

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Image: MT-PML-R7-3P-DMQ-75KVA-YT-LT-DF-A6-BM-AS-2C6-M1

Export Control Classification Number (ECCN): EAR99

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

Links (Click on the below items to view):

- **HigResPic1**(https://www.larsonelectronics.com/images/product/HigResPic1/342311.JPG)
- **HigResPic2**(https://www.larsonelectronics.com/images/product/HigResPic2/342311.JPG)
- **HigResPic3**(https://www.larsonelectronics.com/images/product/HigResPic3/342311.JPG)
- **HigResPic4**(https://www.larsonelectronics.com/images/product/HigResPic4/342311.JPG)
- **HigResPic5**(https://www.larsonelectronics.com/images/product/HigResPic5/342311.JPG)
- **HigResPic6**(https://www.larsonelectronics.com/images/product/HigResPic6/342311.JPG)
- **HigResPic7**(https://www.larsonelectronics.com/images/product/HigResPic7/342311.JPG)
- **HigResPic8**(https://www.larsonelectronics.com/images/product/HigResPic8/342311.JPG)
- **HigResPic9**(https://www.larsonelectronics.com/images/product/HigResPic9/342311.JPG)
- **HigResPic10**(https://www.larsonelectronics.com/images/product/HigResPic10/342311.JPG)
- **Video1**(https://www.youtube.com/watch?v=hB81bMwOdsk)
- **Video2**(https://www.youtube.com/watch?v=mpt7J5hdJp8)
- **Video3**(https://www.youtube.com/watch?v=4-JEyYeYcn8)
- **Video4**(https://www.youtube.com/watch?v=KIzsyVtvSWM)
- **Video5**(https://www.youtube.com/watch?v=mN2qPmdLwW4)
- **ISO 9001 Certification**(http://larsonelectronics.com/images/pdfdocs/ISO9001.PDF)
- **Business Certificate**(https://www.larsonelectronics.com/images/pdfdocs/w9.PDF)
- **Shipping Time Map**(https://www.larsonelectronics.com/images/product/ShippingTimeMap/ShippingTimeMap.pdf)