Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

MT-PML-R7-3P-GMF.MR-1500KVA-YE-LT-DF-A6-BB-CZ-2BZ-M1

1500 KVA Pad Mount Transformer - 24940GrdY/14400 x 12470GrdY/7200 Dual Voltage Grounded Wye Primary - 480Y/277 Wye Secondary - Copper -KNAN/Bell Green

Product ID: 345139

Please see last page for supporting documentation for this product (certificates, CAD files & drawings, IES files, wiring diagrams, etc).



Image: MT-PML-R7-3P-GMF.MR-1500KVA-YE-LT-DF-A6-BB-CZ-2BZ-M1

Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

MT-PML-R7-3P-GMF.MR-1500KVA-YE-LT-DF-A6-BB-CZ-2BZ-M1 Pad Mount Transformer

Phase: Three Phase
Capacity: 1500 KVA (1.5 MVA)
Primary Voltage: 24940GrdY/14400 x 12470GrdY/7200 Grounded Wye, Dual Voltage
Primary Connection: Grounded Wye
Primary Voltage Class: 25 kV
Primary BIL: 125 kV
Secondary Voltage: 480Y/277 Wye
Secondary Connection: Wye
Secondary Voltage Class: 1.2 kV
Secondary BIL: 30 kV
Secondary Phase Angle: 0°
Primary Termination: (6) 200 Amp Bushing Wells w/ (6) 25 kV Class Inserts
Secondary Termination: 12-Hole Spade Bushings
Frequency: 60 Hz
Temperature Rise: 65°C
Capacity @ 65°C Temperature Rise: 1500 KVA (1.5 MVA)
Forced Air (Fans): None
Tap Changer: 5-position Tap Changer, (2) +/- 2.5% Taps Above and (2) +/- 2.5% Taps Below
Efficiency Standard(s): Meets DOE 2016 Standards, Meets ANSI/IEEE Standards
Impedance (Std): 1.5% - 5.75%

Ratings

Listed for United States and Canada
Conforms to NEMA, ANSI C57.12 Standards
Sealed Tank Construction w/ Welded On Cover
Padlockable Doors

Insulation Fluid: Biodegradable Cooling Fluid

Cooling Class: KNAN

Liquid Level Gauge: Analog

Temperature Gauge: Analog

Pressure/Vacuum Gauge: Analog

Fault Pressure Device: None

Pressure Relief Valve: Included

Fill Valve: Included

Drain Valve w/ Sampler Port: Included

Rapid Rise Relay: None

Surge Arrestors: High Voltage Elbow Surge Arrestors Included on Primary Side

Protection Fuses: Bayonet Fuses

Load Break Switch: None

Front: Dead-Front

Feed: Loop

Winding Material: Copper

Cabinet Type: Tamperproof

Enclosure Rating: NEMA 3R Weatherproof

Paint Type: Munsell 7.0 GY 3.29/1.5 Bell Green

Mounting: Pad Mount

Conduit Opening: -

Dimensions: -

Weight: -

Special Orders - Special Requirements

Contact us for special requirements

Toll Free: 1-800-369-6671

Intl: 1-903-270-1187

Fax: 1-903-765-7664

E-mail: sales@larsonelectronics.com

The MT-PML-R7-3P-GMF.MR-1500KVA-YE-LT-DF-A6-BB-CZ-2BZ-M1 Industrial Pad Mount Transformer from Larson Electronics offers powerful, reliable and efficient power distribution in indoor, outdoor and public locations. The low operating costs, low heat emissions and low cost of ownership makes this transformer ideal for a wide range of applications and businesses. An enclosed design caters to installations on concrete pads without protective fencing.

PLEASE NOTE: ANY FREE SHIPPING OFFERS DO NOT APPLY TO POWER DISTRIBUTION PANELS, TRANSFORMERS, OR SUBSTATIONS

Transformer Features: With a transformer rating of 1500 KVA (1.5 MVA), the industrial transformer features a dual-voltage primary of three-phase 24940GrdY/14400 or 12470GrdY/7200 Grounded Wye and a secondary voltage of three-phase 480Y/277 Wye. The unit has a primary loop feed and dead-front primary connections. We also offer systems with radial feed and live front primary connections. This transformer features a 5-position tap changer with two, +/- 2.5% taps above and two, +/- 2.5% taps below to allow small changes for voltage. There are no load break switches or rapid rise relays on the system. Bayonet protection fuses are included.

Copper transformer winding material provides high electrical conductivity, which helps reduce load losses and heat generation. Copper windings also offer high mechanical strength, which helps the coils withstand the forces of short-circuit conditions. This transformer consists of rectangular coil and five-legged wound core design with three coils and four core loops (this is for three-phase transformers only; single-phase units have one coil and two core loops).

The MT-PML-R7-3P-GMF.MR-1500KVA-YE-LT-DF-A6-BB-CZ-2BZ-M1 is air cooled and does not have fans or mounting provision for fans.

Enclosure Design: This pad mounted transformer is a compartmental design. The tank and housing are fabricated from steel. The front electrical enclosure carries a NEMA 3R rating. The high voltage and low voltage compartments are located in front of the transformer tank, with the high voltage compartment on the left side and low voltage compartment on the right side. The HV and LV compartments are air filled and separated by a full length steel barrier between the compartments. A removable steel plate at the base of the HV and LV compartments prevents rodents and other intrusions from entering the enclosure once installed. This steel plate allows for underground conduit entry into the enclosure compartments. Two hinged exterior doors allow access into the compartments. A single pad lockable handle on the low voltage compartment door allows for securing the transformer. A spring loaded pin within the low voltage compartment prevents the high voltage door from being opened without pulling the safety pin. A hot stick is included in the high voltage compartment, mounted to the HV door.

Temperature Rise: This unit features 65°C temperature rise for reduced heat waste, increased reliability and longer life. At 65°C temperature rise, the transformer offers 1500 KVA (1.5 MVA). The transformer meets standard efficiency requirements. The combination of low temperature rise and high efficiency makes this unit suitable for use in electrical rooms, air conditioned spaces in buildings, underground vaults and similar locations, in addition to outdoor areas.

Insulation Fluid: The MT-PML-R7-3P-GMF.MR-1500KVA-YE-LT-DF-A6-BB-CZ-2BZ-M1 features biodegradable cooling fluid (KNAN). We offer transformers with FR-3 oil fluid, if needed.

Biodegradable Fluid: Biodegradable cooling fluid (vegetable oil) has a higher heat capacity compared to mineral oil, making the liquid safer to use and more reliable during operations. Vegetable oil has a higher flash point and fire point than mineral oil, hydrocarbon oil, silicone

oil and synthetic ester. This cooling fluid is also non-toxic and can tolerate higher breakdown voltages than mineral oil. When operating at high temperatures, biodegradable cooling liquid sustains up to 120% load conditions, which helps preserve the transformer's lifespan and performance.

Gauges: The following gauges are included with the system: liquid level, temperature and pressure/vacuum gauges. Standard liquid level, temperature and pressure/vacuum gauges are analog, manual reading types. These gauges do not have auxiliary contacts.

Fault Pressure Devices: There are no fault pressure devices on this transformer. Fault pressure devices are used to detect high rates of pressure rise within the tank.

Rapid Rise Relay: There are no rapid rise relays on the unit. This safety component is designed for protection when a rapid increase in tank pressure occurs. The relay is suitable for detecting sudden pressure fluctuations above predetermined safe limits.

Surge Arresters: This system comes with high voltage elbow surge arresters on the primary side. Designed for over-voltage and transient voltage protection, the components prevent damage caused by lightning, internal switching or voltage surges. We can offer models without high voltage elbow surge arresters that have mounting provisions for customer-provided surge arresters.

Valves: The MT-PML-R7-3P-GMF.MR-1500KVA-YE-LT-DF-A6-BB-CZ-2BZ-M1 is equipped with a pressure relief valve, fill valve and drain valve with sampler port.

Protection Fuses: This transformer contains bayonet protection fuses. For units without protection fuses, upstream protection is provided. We recommend provisions for protection fuses when possible, as blown fuses may require more frequent oil changes.

Mount: The heavy-duty enclosure makes the unit suitable for both indoor and outdoor applications. This power distribution system can be pad mounted on concrete pads.

Benefits: The MT-PML-R7-3P-GMF.MR-1500KVA-YE-LT-DF-A6-BB-CZ-2BZ-M1 pad mount transformer offers many benefits to consumers. This transformer provides owners with significant energy savings, as well as offering environmental benefits. Higher efficiency not only extends the life of the transformer, but also turns into cost savings for owners in the form of lower energy bills and decreased cost of ownership.

Applications: General purposes, industrial sites, electrical rooms, underground vaults, manufacturing facilities, steel plants, offshore, commercial, military, processing plants, electric power distribution, utilities, public locations and more.

Larson Electronics is a manufacturer and as such can build stationary and portable transformer systems to your specifications. Although we carry several models of power distribution transformer systems, we can deliver custom ordered units almost as quickly as our prebuilt units. If this model does not meet your needs, please contact us at 1-800-369-6671 or sales@larsonelectronics.com to discuss your specific requirements.

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

Frequently Asked Questions (FAQ)

There are no Faqs

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Image: MT-PML-R7-3P-GMF.MR-1500KVA-YE-LT-DF-A6-BB-CZ-2BZ-M1

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Image: MT-PML-R7-3P-GMF.MR-1500KVA-YE-LT-DF-A6-BB-CZ-2BZ-M1

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Image: MT-PML-R7-3P-GMF.MR-1500KVA-YE-LT-DF-A6-BB-CZ-2BZ-M1

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Image: MT-PML-R7-3P-GMF.MR-1500KVA-YE-LT-DF-A6-BB-CZ-2BZ-M1

Export Control Classification Number (ECCN): EAR99

Links (Click on the below items to view):

- **HigResPic1** (https://www.larsonelectronics.com/images/product/HigResPic1/345139.JPG)
- **HigResPic2** (https://www.larsonelectronics.com/images/product/HigResPic2/345139.JPG)
- **HigResPic3** (https://www.larsonelectronics.com/images/product/HigResPic3/345139.JPG)
- **HigResPic4** (https://www.larsonelectronics.com/images/product/HigResPic4/345139.JPG)
- **HigResPic5** (https://www.larsonelectronics.com/images/product/HigResPic5/345139.JPG)
- **HigResPic6** (https://www.larsonelectronics.com/images/product/HigResPic6/345139.JPG)
- **HigResPic7** (https://www.larsonelectronics.com/images/product/HigResPic7/345139.JPG)
- **HigResPic8** (https://www.larsonelectronics.com/images/product/HigResPic8/345139.JPG)
- **HigResPic9** (https://www.larsonelectronics.com/images/product/HigResPic9/345139.JPG)
- **HigResPic10** (https://www.larsonelectronics.com/images/product/HigResPic10/345139.JPG)
- **Video1** (https://www.youtube.com/watch?v=mN2qPmdLwW4)
- **ISO 9001 Certification** (http://larsonelectronics.com/images/pdfdocs/ISO9001.PDF)
- **Business Certificate** (https://www.larsonelectronics.com/images/pdfdocs/w9.PDF)
- **Shipping Time Map** (https://www.larsonelectronics.com/images/product/ShippingTimeMap/ShippingTimeMap.pdf)