Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

LE-4100-A-F

LED Diffused Flood Light - 12-24V DC, 5000 Lumens - (2) Wireless Remotes - Stanchion Mount - White Housing - Anchor Light

Product ID: 264602



Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

LE-4100-A-F LED Diffused Flood Light w/ Stanchion Mount & (2) Wireless Remotes

Lamp Technology: LED
Light Dimensions: 5.9" x 7.1" x 7.5"
Base Dimensions: 6.06" x 6.06"
Remote Qty: (2)
Light Weight: 4.2 lb
Voltage: 12 V DC or 24 V DC
Total Watts: 50W
Lumens: 5,000
Candela: 550,000
Beam Distance: 4,915 Feet
Luminous Efficacy: 100 Lm/W
LED Life Expectancy: 50,000+ hours
LED Light Color: White
Correlated Color Temperature: 5,700-6,000K
Beam Angle: -
Lighting Configuration: Flood
Light Head Rotation: 360° - Continuous
Elevation Angle: 135°
Rotation Speed: 19° per Second (Fast), 19° per Second (Slow)
Elevation Speed: 11° per Second
Wireless Remote Control Frequency: 433.92 MHz
Remote Controls: On/Off, Up, Down, Left, Right, Speed Control
Wireless Remote Distance: 215'
Wireless Remote Batteries: (2) 23A Per Remote - Included
Amps: 4 A @ 12 V DC, 2 A @ 24 V DC
Ambient Operating Temp Range: -30°C to +70°C
Housing Material: Acrylonitrile Styrene Acrylate (ASA)

Ratings/Approvals

IP68 Rated LED Module
IP56 Rated Housing
FCC Approved
Auto-Home Return
White Anchor Light

Special Orders - Requirements

Contact us for special requirements

Lens Material: Hardened Polycarbonate
Mount: Stanchion Mount - 6", 12", 24", or 48" Post Length Options
Wiring: -
Housing Color: White

Toll Free: 1-800-369-6671
Intl: 1-214-616-6180
Fax: 1-903-498-3364
E-mail: sales@larsonelectronics.com

The LE-4100-A-F from Larson Electronics is a LED Diffused Flood Light w/ Stanchion Mount that provides intense output in outdoor locations and is recommended for lighting support during nighttime operations, emergencies, patrolling, and more. This LED light operates on 12 V or 24 V DC and provides 5000 Lumens of output during use. Equipped with two wireless remotes, the LED light with white housing is compatible with stanchion mounting installations and features a white anchor light.

The LE-4100-A-F is a powerful lighting solution for outdoor areas, rugged environments, and remote locations. A total of ten, 5-watt LEDs provide a flood light beam that can illuminate wide areas. The low voltage LED search light generates 5000 Lumens of output. During use, this unit rotates at a rate of 19° per second in fast mode and 12° per second in slow mode, as well as elevates at a rate of 11° per second. The LED module carries an IP68 rating and the housing is IP56 rated. Equipped with an acrylonitrile styrene acrylate (ASA) housing, the lens is made out of hardened polycarbonate.

Remote Control: This unit comes with two wireless handheld remote controls. One dash mount holster is also included to store one of the remotes in a convenient location. The wireless handheld remotes both operate on 433.92 MHz and enable on/off, up, down, left, right, and strobe on/off operation. Powered by two 23A batteries (included) each, the remotes have an operating distance of 213'. Up to four wireless remote controls can be used with the LED light.

LED Benefits: Unlike gas burning and arc type lamps that have glass bulbs, LEDs have no filaments or fragile housings to break during operation and/or transportation. Instead of heating a small filament or using a combination of gases to produce light, light emitting diodes (LEDs) use semi-conductive materials that illuminate when electric current is applied, providing instant illumination with no warm up or cool down time before re-striking. Because there is no warm up period, this light can be cycled on and off with no reduction in lamp life.

LED lights run at significantly cooler temperatures than traditional metal halide and high pressure sodium lights and contain no harmful gases, vapors, or mercury, making them both safer and more energy efficient. No extra energy is wasted in cooling enclosed work areas due to external heat emissions from bulb type lights, and the operator risks associated with traditional lighting methods, such as accidental burns and exposure to hazardous substances contained in the glass bulbs, are eliminated. In addition, LEDs are also safer for the environment as they are 100% recyclable, which eliminates the need for costly special disposal services required with traditional gas burning and arc type lamps.

Voltage: The LED diffused flood light operates on 12 V DC or 24 V DC.

Mount: The LE-4100-A-F is a stanchion mount LED diffused flood light. The spotlight is mounted on a stanchion post. Stanchion posts are available in the following sizes: 6 inch, 12 inch, 24 inch, or 48 inch. A stanchion mount enables the light to be installed and removed for storage. The included running lights are always on when the mount is receiving power. The wireless remote controls only control the LED diffused flood light.

Applications: Outdoor locations, vehicles, boats, law enforcement, emergency services, and more.

At Larson Electronics, we do more than meet your lighting needs. We also provide replacement, retrofit, and upgrade parts as well as industrial grade power accessories. Our craftsmen can custom build any lighting system and/or accessories to fit the unique demands of your operation. A commitment to honesty, quality, and dependability has made Larson Electronics a leader in the lighting and electronics business since 1973. Contact us today at 800-369-6671 or message sales@larsonelectronics.com for more information about our custom options tailored to meet your specific industry needs.









Frequently Asked Questions (FAQ)

Q. Should I order a 12V or 24V light?

A. Most customers need a 12V light. Standard vehicles and ATVs operate on 12V. Military vehicles operate on 24V. 24V does not mean it will be brighter. Operating a 24V light on a 12V power source will make halogen lights half as bright while LED lights will not operate. The motors will rotate very slowly and the light will appear broken.

Q. What is the difference between Radioray and Radioray GT models?

A. The Radioray GT series was introduced in 2019. The upgraded Radioray GT series features: updated exterior housing, higher torgue drivetrain, more precise pan/tilt control, upgraded stainless steel mounting bracket, enhanced resistance to vibration and impact, and new wiring harness.

Q. I own a halogen Radioray. Can I upgrade to a LED light or do I need to purchase a new light?

A. Yes. Halogen lights can be upgraded to LED by purchasing the GL-15444 LED module. This is compatible with GL-2XXX, GL-5XXX, GL-7XXX, and GL-9XXX models.

Q. What remote options are available for the Radioray?

A. We offer wireless handheld, wireless dash mount, and hard wired dash mount remotes for the GL-2XXX, GL-7XXX, and GL-9XXX series. The GL-5XXX series is only offered with a hard wired in-line remote.

Q. For wireless remotes, what is the operating distance and frequency?

A. The wireless handheld and wireless dash mount remotes operate up to 100' distance away from the light. The remote operates on 433 Mhz.

Q. Can I convert my hardwired light to a wireless remote?

A. If the light was originally manufactured as both wireless and hard-wired, you can purchase a replacement remote and program it to your light. If you purchased a military spec 24V light with no transceiver, the light cannot be converted to wireless.

Q. How long is the power cord?

A. For permament mount lights with wireless remotes, a 1-foot power cord is provided with tinned leads ready for installation. For portable models, a 15-foot power cord with a universal 12V cigarette plug is provided. We offer alternative cords for portable models that can be purchased separately, including ring terminals and battery clamps. For permament mount lights with hard wired remotes, we offer 20-foot and 32-foot remote cables.

Q. Can I control multiple lights from one remote?

A. Yes. For wireless remotes, both lights must be programmed to the same remote. See reprogramming instructions on GL-30100 for how to do this. For hard wired lights (excluding GL-5XXX series), a Y-splitter cable is needed. Part numbers for Y splitter varies by model. Contact sales to purchase a Y-splitter cable.

Q. Can I control one light from two remotes?

A. Yes. For wireless remotes, both remotes must be programmed to the same light. See reprogramming instructions on GL-30100 for how to do this. For hard wired lights (excluding GL-5XXX series), a X-splitter cable is needed. Part numbers for X splitter varies by product. Contact sales to purchase an X-splitter cable.

Q. Can I purchase a longer remote harness for my light with a hard wired remote?

A. Yes. We offer replacement cable and extension cable in 20-foot and 32-foot. An extension cable will plug in between your existing cable and the light. A replacement cable fully replaces your existing cable. Part numbers for these cables by product. Contact sales to purchase extension or replacement cables.

Q. What is the amp draw of my light?

A. Halogen lamps draw 5.5 amps at 12V DC. LED lamps draw 3.7 amps at 12V DC.

Q. Are replacement parts available for my existing light?

A. Yes. Replacement parts are available for most models. You can purchase them directly from our website, or contact sales.

Q. Can you repair my light for me?

A. Yes we can. Before sending in your light for repair, you must obtain a Return Authorization Number and include the RGA form in the packaging with your light. Service repair fees may apply.

Q. I purchased a military surplus 24V light, can you convert it to 12V?

A. The light can have the internal board converted to 12V. A cheaper and faster solution is to purchase our 12V to 24V transformer (part # DCP-12x24-10A-WP). This will be wired between the power source and light, and allow the 24V light to operate on a 12V vehicle.