Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

ETX-ATX-1P-220V-1KVA-24V-50HZ

1 kVA Explosion Proof Transformer - C1D1&2 - C2D1&2 - 1PH - 220V Primary - 24V Secondary - 50Hz

Product ID: 302503



Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

#SKU# Explosion Proof Transformer

Unit Type: Explosion Proof Transformer
Dimensions: 12" x 18" x 8" (Internal)
Phase: Single Phase
kVA: 1
Primary Voltage: 220V AC
Secondary Voltage: 24V DC
Frequency: 50 Hz
Primary/Secondary Configuration: Two Winding
Winding Material: Copper
Termination: Leadwires
Electrostatically Shielded: Yes
Temp Rise/Insulation: 115°C/180°C
Sound Level: Meets NEMA ST-20 Standards
Enclosure Material: Cast Aluminum
Input/Output Hubs: 3/4" NPT Input and 3/4" NPT Output Hubs
Mounting: Surface
Weight: 200 lbs

Ratings/Approvals

Class I, Division 1 & 2, Groups C & D
Class II, Division 1 & 2, Groups E, F, G
NEMA 4X

Special Orders - Requirements

Contact us for special requirements

Toll Free: 1-800-369-6671
Intl: 1-214-616-6180
Fax: 1-903-498-3364
E-mail: sales@larsonelectronics.com

The ETX-ATX-1P-220V-1KVA-24V-50HZ by Larson Electronics is an Explosion Proof 50 Hz Transformer for use in hazardous locations. Suitable for both indoor and outdoor applications, the ETX-ATX-1P-220V-1KVA-24V-50HZ provides increased reliablity, protection against critical equipment failures and an extra level of protection by isolating the power

source from the connected device.

PLEASE NOTE: ANY FREE SHIPPING OFFERS DO NOT APPLY TO POWER DISTRIBUTION PANELS, TRANSFORMERS, OR SUBSTATIONS

Transformer Features: With a transformer rating of 1 kVA, the ETX-ATX-1P-220V-1KVA-24V-50HZ is a single phase unit with a primary voltage of 220V AC. It also provides a secondary voltage of 24V DC. The transformer contains a two-winding primary and secondary configuration and reverse connectables, as well as electrostatically shielded components and wire leads connection. Featuring robust construction, the enclosure is made out of cast aluminum.

The explosion proof transformer comes with a NEMA 4X rating, which offers watertight protection and corrosion resistance. The following input/output hubs can be found on this unit: 3/4" NPT (input) and 3/4" NPT (output). The ETX-ATX-1P-220V-1KVA-24V-50HZ may be mounted on compatible surfaces in Class I and Class II environments. This transformer provides owners with significant energy savings as well as offering environmental benefits. Higher efficiency not only extends the life of the transformer, but also turn into cost savings for owners in the form of lower energy bills and decreased cost of ownership.

Applications: Chemical processing plants, oil refineries, wastewater facilities and other classified industrial facilities that adheres to the ratings of this unit.

Larson Electronics is a manufacturer and as such can build stationary and portable transformer systems to your specifications. Although we carry several models of power distribution transformer systems, we can deliver custom ordered units almost as quickly as our prebuilt units. If this model does not meet your needs, please contact us at 1-800-369-6671 or sales@larsonelectronics.com to discuss your specific requirements.




EPL-AEB-10.10.6





Frequently Asked Questions (FAQ)