Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

MPD-DS-WML-NFDS-3P-3W-480V-800A-DF-BM-N3R

800 Amp Non-Fused Manual AC Disconnect Safety Switch - 480V AC - 3-Pole - NEMA 3R - 1.2KV

Product ID: 304667

Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

MPD-DS-WML-NFDS-3P-3W-480V-800A-DF-BM-N3R Disconnect Switch - Non Fused Disconnect

Unit Type: Service Entrance Non Fused Disconnect Switch, Heavy Duty
Line-In: N/A (customer provided)
Line-In Cord Cap: N/A (customer provided)
Line-In Connections: Terminal Lugs
Line-In Orientation: Bottom Feed

Voltage (V): 600V AC Delta or Wye

Phase (PH): 3-Phase

Frequency (Hz): 60 Hz (60-Cycles)

Protection Method: N/A (customer provided)

Protection Type: N/A (customer provided)

Protection Ampacity: -

Mains Rating (Amps): 800A

Interrupting Rating: 100 kA @ 1200V AC

Horsepower (Standard): 200 HP at 240V, 500 HP at 480V, 500 HP at 600V

Max Motor Full Load Amps Rating: 480 FLA at 240V, 590 FLA at 480V, 472 FLA at 600V

Disconnect Means: Manual via Handle

Neutral Connection: -

Line-Out: N/A (customer provided)

Line-Out Cord Cap: N/A (customer provided)

Line-Out Connection: Terminal Lugs, Accepts 750MCM-1/0

Line-Out Orientation: Bottom Feed

Form Factor: Rectangular, Slim-profile Enclosure w/ Lockable Door

Ratings

NRTL Listed Service Equipment
NRTL Listed to UL 98 Dead Front Switch Boards
NEMA 3R Rated for Indoor and Outdoor Use
Made in the USA
Heavy Duty Construction for Commercial/Industrial Use

Door: (1) Left Hinged Door w/ Pad Lockable Handle

Enclosure Material: 11GA Sheet Steel

Enclosure Finish: ANSI 49 Grey

Enclosure Type: NEMA 3R Ventilated
Mount: Wall Mount
Dimensions: 26.420"-L x 16.826"-W x 58.965"-H
Weight: -
Shipping Dimensions: -
Shipping Weight: -

Larson Electronics manufactures a wide variety of custom power distribution systems. The pictures displayed for this unit are a general representation of form factor and may not accurately represent this exact configuration in every detail due to being custom builds. The specifics for this configuration are listed in the specification table and one-line diagram.

Special Orders - Special Requirements
Contact us for special requirements
Toll Free: 1-800-369-6671
Intl: 1-214-616-6180
Fax: 1-903-498-3364
E-mail: sales@larsonelectronics.com

All grounding shall comply with state and local codes and meet the minimum requirements of the National Electronic Code section 250

Made in the USA

The Larson Electronics MPD-DS-WML-NFDS-3P-3W-480V-800A-DF-BM-N3R Power Distribution Non Fused Disconnect Switch is designed for reliable, safe and convenient power distribution at industrial work sites. Designed for wall mounting installations, the disconnect switch is protected by a NEMA 3R rated, steel enclosure with a ventilated design.

PLEASE NOTE: ANY FREE SHIPPING OFFERS DO NOT APPLY TO POWER DISTRIBUTION PANELS, TRANSFORMERS, OR SUBSTATIONS*

The MPD-DS-WML-NFDS-3P-3W-480V-800A-DF-BM-N3R service entrance disconnect switch provides a safe and reliable way for operators in industrial settings to tap into and utilize power sources independently of the work area. Compatible with three-phase 600V AC Delta or Wye, the disconnect switch features a manual operating handle. This 3-pole, 3-wire disconnect carries a 100 kA at "1.2 KV" 1200V AC interrupt rating.

Operation: The dead front disconnect switch features a locking door. The door provides access to a permanently attached operating handle, which is used for manually disconnecting or connecting power.

Enclosure Design: The disconnect switch is protected by an 11GA sheet steel enclosure with ANSI 49 grey finish. A ventilated design promotes natural cooling and improves performance. The enclosure is NEMA 3R rated for protection against water, moisture and debris. This rating allows the non fused disconnect to be used in indoor and outdoor areas.

Certification: This disconnect switch is NRTL listed to UL 98 dead front switchboards and NRTL listed for service equipment.

Mount: Operators can mount the service entrance disconnect on walls.

Customization: The MPD-DS-WML-NFDS-3P-3W-480V-800A-DF-BM-N3R can be customized to meet specific operating and power requirements. Example of customizations include:

- Making the non-fused disconnect portable and certified to NRTL UL 1640 for portable equipment
- Adding single pole camlock connectors for quick connections
- Adding heaters for cold environments
- Aiding alarm relays for trip notification down stream
- Adding powering meters

Applications: This switchgear is suitable for indoor/outdoor use and applications including, but not limited to, construction sites, plant maintenance, plant turnarounds, hazardous location operations, shows, exhibits, and shipyard operations.

At Larson Electronics, we do more than meet your lighting needs. We also provide replacement, retrofit, and upgrade parts as well as industrial grade power accessories. Our craftsmen can custom build any lighting system and/or accessories to fit the unique demands of your operation. A commitment to honesty, quality, and dependability has made Larson Electronics a leader in the lighting and electronics business since 1973. Contact us today at 800-369-6671 or message sales@larsonelectronics.com for more information about our custom options tailored to meet your specific industry needs.

LARSON

WARNING
ALL DOORS MUST BE CLOSED AND FASTENED PRIOR TO LEAVING THE EQUIPMENT UNATTENDED
WARNING
FOR USE BY QUALIFIED PERSONNEL ONLY

Frequently Asked Questions (FAQ)