Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

MT-PSTC-R7-3P-DVS-1.6MVA-YK-HNT-LNT-A5-BM-CZ-2ZZ-M1

1.6 MVA Conservator Substation Transformer- 10000V Delta Primary, 400Y/231 Wye-N Secondary - ONAN - RAL 7033 - NEMA 4X - Wheels Mounted

Product ID: 312737



Image: MT-PSTC-R7-3P-DVS-1.6MVA-YK-HNT-LNT-A5-BM-CZ-2ZZ-M1

Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

MT-PSTC-R7-3P-DVS-1.6MVA-YK-HNT-LNT-A5-BM-CZ-2ZZ-M1 3PH Conservator Substation Transformer

Transformer Type: Substation Transformer, Conservator-Type
Transformer Configuration: Liquid Filled Substation
Transformer Feed Type: Radial Feed
Phase: Three Phase
Capacity: 1.6 MVA (1,600 KVA)
Vector Group: Dyn11
Primary Voltage: 11000V Delta
Primary Voltage Class: 15 kV Class
Primary Phasor: Delta
Primary BIL: 95 kV
Secondary Voltage: 400Y/231
Secondary Voltage Class: 1.2 kV
Secondary Phasor: Wye-N
Secondary BIL: 30 kV
Frequency: 50 Hz
Temperature Rise: 65°C
Cooling Class: ONAN; Self-Cooled
Forced Air (Fans): None
Tap Changer: 5-position Tap Changer
Tap Qty: (2) FCAN Above Taps, (2) FCBN Below Taps
Tap %: 2.5%
Tap Changer Switch Location: High Voltage (HV) Front Compartment

Ratings

Meets/Exceeds IEC 60076 Ratings
Non-PCB Insulating Fluid
Tamper Proof Housing
Class A Insulation

No Load Loss: 1.45 KW
Full Load Loss: 18 KW
Note: *Losses offered are typical only, not guaranteed*

Impedance (Typical): 5.0-7.5%

Primary Connection Type: Live Front

Primary Termination: 15 kV, 95 kV BIL, 600 A one piece dead-break bushings

Primary Connection Qty: (3)

Primary Terminals Arrangement: Top Mounted, Enclosed In Cable Connection Box, w/ Cable Glands

Primary Surge Arrestors: Included, High Voltage Elbow Surge Arrestors

Primary Surge Arrestor Voltage Rating: 10 kV Class

Primary Surge Arrestor MCOV Rating: 8.4 kV rms

Primary Over Current Protection (OCP): N/A

Primary Over Current Protection Method: N/A

Primary Over Current Protection Holder: N/A

Secondary Connection Type: Live Font

Secondary Connections: Cable Boxes

Secondary Connection Qty: (4)

Secondary Terminals Arrangement: Top Mounted, Enclosed In Cable Connection Box

Secondary Over Current Protection (OCP): N/A

Grounding Provisions: (1) Grounding lug, accepts #2 copper

Metering Current Transformer (CT): N/A

Metering Panel: N/A

Control Panel: Buchholz Relay (alarm and trip), Pressure Relief Device (alarm and trip), Oil Level Indicator (alarm and trip), Dehydrating Breather, Oil Temp (alarm and trip), Coil Winding Temp (alarm and trip)

Load Break Switch: N/A

Load Break Switch Qty: N/A

Load Break Switch Location: N/A

Load Break Switch Rating: N/A

Efficiency Standard(s): Meets ANSI/IEEE Standards

K-Factor Rating (Harmonic Mitigation): K-1 (Standard)

Pulse Drive Rating: N/A

Insulation Fluid: Mineral Oil Insulating Fluid, Type II, Non-PCB

Fluid Capacity: TBD

Liquid Level Indicator: Analog Dial Gauge

Temperature Indicator: Analog Dial Gauge, w/ (2) Changeover Contacts

Pressure/Vacuum Indicator: Analog Dial Gauge

Pressure Relief Device: Included, Top Mounted, Qualitrol series 208

Fill Valve: Removable Bolt

Fill Valve Location: Front Compartment

Drain Valve: Included, w/ Sampler

Drain Valve Location: Front Compartment

Dehydrating Breather: Included

Winding Material: Copper

Ambient Temperature Rating: 45°C

Sound Level: 61 dBA

Elevation Rating: 3300ft (1000 meters) Above Sea Level

Core Material: Iron

Tank Material: Coated Steel

Cabinet Material: Coated Steel

Base Platform Material: Coated Steel

Housing Type: NEMA 4X Compartmental Cabinet w/ Doors, HV Compartment Left, LV Compartment Right

Paint Type: Weatherproof and UV Resistant Epoxy Coating and Undercoating

Finish Color: RAL 7033

Mounting: Wheels

Conduit Opening: Bottom Feed Underground Entry/Exit

Dimensions: 79.1"-W x 57.5"-D x 103.74"-H

Special Orders - Special Requirements

Contact us for special requirements

Toll Free: 1-800-369-6671

Intl:

1-903-270-1187
Fax: 1-903-498-3364
E-mail: sales@larsonelectronics.com

Weight: TBD
*Please note that numbers are approximate and subject to change

The MT-PSTC-R7-3P-DVS-1.6MVA-YK-HNT-LNT-A5-BM-CZ-2ZZ-M1 Conservator Substation Transformer from Larson Electronics offers powerful, reliable and efficient power distribution in outdoor locations. The low operating costs, low heat emissions and low cost of ownership makes this transformer ideal for a wide range of applications and businesses. This transformer ensures extra space for storing oil and is equipped with breathers to facilitate air flow. The conservator transformer should be installed on supporting structures.

PLEASE NOTE: ANY FREE SHIPPING OFFERS DO NOT APPLY TO POWER DISTRIBUTION PANELS, TRANSFORMERS, OR SUBSTATIONS

Transformer Features: The industrial transformer features a primary voltage of three-phase 10000V Delta and a secondary voltage of three-phase 400Y/231 Wye-N. This system is rated for 1.6 MVA (1,600 KVA). This transformer features a 5-position tap changer with two, +/- 2.5% taps above and two, +/- 2.5% taps below to allow small changes for voltage. We offer systems with loop or radial feed, as well as dead front or live front primary connections.

The distribution transformer is equipped with a rigid tank with a level indicator and a rubber bag inside the unit. An accessible NEMA 3R rated weatherproof junction box with glands for single core cables from HV and LV connection is available.

The system features copper windings for high strength and thermal/electrical conductivity. This transformer consists of rectangular coil and five-legged wound core design with three coils and four core loops (this is for three-phase transformers only; single-phase units have one coil and two core loops).

The MT-PSTC-R7-3P-DVS-1.6MVA-YK-HNT-LNT-A5-BM-CZ-2ZZ-M1 does not have fans for forced air cooling. This non-sealed system features breathers for cooling when operating temperatures increase.

Temperature Rise: This unit features 65°C temperature rise for reduced heat waste, increased reliability and longer life. The transformer meets standard ANSI/IEEE efficiency requirements. The combination of low temperature rise and high efficiency makes this unit suitable for use in electrical rooms, air conditioned spaces in buildings, underground vaults and similar locations, in addition to outdoor areas.

Insulation Fluid: The MT-PSTC-R7-3P-DVS-1.6MVA-YK-HNT-LNT-A5-BM-CZ-2ZZ-M1 features mineral oil fluid (ONAN). We offer transformers with biodegradable or FR-3 fluids, if needed.

Biodegradable Fluid: Biodegradable cooling fluid (vegetable oil) has a higher heat capacity compared to mineral oil, making the liquid safer to use and more reliable during operations. Vegetable oil has a higher flash point and fire point than mineral oil, hydrocarbon oil, silicone oil and synthetic ester. This cooling fluid is also non-toxic and can tolerate higher breakdown voltages than mineral oil. When operating at high temperatures, biodegradable cooling liquid sustains up to 120% loan conditions, which helps preserve the transformer's lifespan and

performance.

Gauges: The following gauges are included with the system: liquid level, temperature and pressure/vacuum gauges. Standard liquid level, temperature and pressure/vacuum gauges are analog, manual reading types.

Fault Pressure Devices: There are no fault pressure devices on the unit. Fault pressure devices are used to detect high rates of pressure rise within the tank.

Rapid Rise Relay: There are no rapid rise relays on the unit. This safety component is designed for protection when a rapid increase in tank pressure occurs. The relay is suitable for detecting sudden pressure fluctuations above predetermined safe limits.

Surge arresters: This system comes with surge arresters on the primary side. Designed for over-voltage and transient voltage protection, the components prevent damage caused by lightning, internal switching or voltage surges. We can offer models without high elbow surge arresters that have mounting provisions for customer-provided surge arresters.

Load Break Switch: This transformer is not equipped with load break switches.

Valves: The MT-PSTC-R7-3P-DVS-1.6MVA-YK-HNT-LNT-A5-BM-CZ-2ZZ-M1 is equipped with a pressure relief valve, fill valve and drain valve with sampler port.

Protection Fuses: This transformer has bayonet protection fuses on the primary side. For units without protection fuses, up stream protection is provided. We recommend provisions for protection fuses when possible, as blown fuses may require more frequent oil changes.

Mount: This conservator substation should be installed on supporting structures, such as the roof of the transformer main tank.

Benefits: The MT-PSTC-R7-3P-DVS-1.6MVA-YK-HNT-LNT-A5-BM-CZ-2ZZ-M1 transformer offers many benefits to consumers. This transformer provides owners with significant energy savings, as well as offering environmental benefits. Higher efficiency not only extends the life of the transformer, but also turns into cost savings for owners in the form of lower energy bills and decreased cost of ownership.

Applications: General purposes, industrial sites, electrical rooms, underground vaults, manufacturing facilities, steel plants, offshore, commercial, military, processing plants, electric power distribution, utilities and more.

Larson Electronics is a manufacturer and as such can build stationary and portable transformer systems to your specifications. Although we carry several models of power distribution transformer systems, we can deliver custom ordered units almost as quickly as our prebuilt units. If this model does not meet your needs, please contact us at 1-800-369-6671 or sales@larsonelectronics.com to discuss your specific requirements.

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

Frequently Asked Questions (FAQ)

There are no Faqs