Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

MPD-DS-WML-NFDS-3P-3W-600V-400A-DF-BM-N4X-316SS-M1

Non-Fused Disconnect Switch, 400 Amp, 600V 3PH AC, 3-Pole 3-Wire, Wall Mount, NEMA 4X, 316 Stainless Steel

Product ID: 330579



Image: MPD-DS-WML-NFDS-3P-3W-600V-400A-DF-BM-N4X-316SS-M1

Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

MPD-DS-WML-NFDS-3P-3W-600V-400A-DF-BM-N4X-316SS-M1 Disconnect Switch - Non-Fused Disconnect

Unit Type: Service Entrance Non-Fused Disconnect Switch
Line-In: N/A (customer provided)
Line-In Cord Cap: N/A (customer provided)
Line-In Connections: Terminal Lugs
Line-In Orientation: Bottom Feed
Voltage: 600V AC Delta or Wye
Phase: 3-Phase
Frequency: 60 Hz (60-Cycles)
Protection Method: N/A
Protection Type: N/A
Protection Fuses: N/A
Protection Ampacity: N/A
Mains Rating (Amps): 400A
Interrupting Rating: 200,000 AIC RMS @ 600 V AC
Horsepower (Standard): 125 HP at 240V, 250 HP at 480V, 350 HP at 600V
Max Motor Full Load Amps Rating: 312 FLA at 240V, 302 FLA at 480V, 336 FLA at 600V
Disconnect Means: Manual via Handle
Neutral Connection: -
Line-Out: N/A (customer provided)
Line-Out Cord Cap: N/A (customer provided)
Line-Out Connection: Terminal Lugs, Accepts 600MCM or 2 x 350MCM
Line-Out Orientation: Bottom Feed
Form Factor: Rectangular, Slim-profile Enclosure w/ Lockable Door
Door: (1) Left Hinged Door w/ Pad Lockable Handle

Ratings

NRTL Listed Service Equipment
NRTL Listed to UL 98 Dead Front Switchboards
NEMA 4X Rated for Indoor and Outdoor Use
Made in the USA

Enclosure Material: 316 Stainless Steel
Enclosure Finish: Natural Finish
Enclosure Type: NEMA 4X
Mount: Wall Mount
Dimensions: -
Weight: -
Shipping Dimensions: -
Shipping Weight: -
Larson Electronics manufactures a wide variety of custom power distribution systems. The pictures displayed for this unit are a general representation of form factor and may not accurately represent this exact configuration in every detail due to being custom builds. The specifics for this configuration are listed in the specification table and one-line diagram.

Special Orders - Special Requirements
Contact us for special requirements
Toll Free: 1-800-369-6671
Intl: 1-903-270-1187
Fax: 1-903-765-7664
E-mail: sales@larsonelectronics.com

All grounding shall comply with state and local codes and meet the minimum requirements of the National Electronic Code section 250

Made in the USA

The MPD-DS-WML-NFDS-3P-3W-600V-400A-DF-BM-N4X-316SS-M1 from Larson Electronics is a Power Distribution Non-Fused Disconnect Switch that is designed for reliable, safe, and convenient power distribution at industrial work sites. Designed for wall mounting installations.

PLEASE NOTE: ANY FREE SHIPPING OFFERS DO NOT APPLY TO POWER DISTRIBUTION PANELS, TRANSFORMERS, OR SUBSTATIONS*

The MPD-DS-WML-NFDS-3P-3W-600V-400A-DF-BM-N4X-316SS-M1 service entrance disconnect switch provides a safe and reliable way for operators in industrial settings to tap into and utilize power sources independently of the work area. Compatible with three-phase 600V AC Delta or Wye, the disconnect switch features a manual operating handle. This 3-pole, 3-wire disconnect carries a 200,000 AIC RMS @ 600V AC interrupt rating.

Operation: The dead front non-fused disconnect switch features a locking door. The door provides access to a permanently attached operating handle, which is used for manually disconnecting or connecting power.

Time Delay vs. Fast Acting Fuses Two of the most common types of fuses found in power distribution equipment are time delay and fast acting fuses.

> **Time Delay:** Time delay fuses are tripped once overcurrent heat builds up enough to melt the fuse element over a period of time. That period of time varies between different time delay fuses depending on the application. Time delay fuses decrease the chances of false tripping. During startup, many components require a large current for a very short amount of time. In other words, a time delay fuse disconnects the circuit only when the overcurrent persists in the line.
>
> **Fast Acting:** Fast acting fuses are tripped immediately upon sensing an overcurrent or short circuit in the line. They are ideal for electronics, components, or systems that cannot withstand sudden changes in current. A fast acting fuse will not withstand a temporary overload such as one that occurs during the startup process.

Enclosure Design: The disconnect switch is protected by a 316 stainless steel housing with a finish. The enclosure is NEMA 4X rated for protection against water, moisture, external ice formation, corrosion and debris. This rating allows the non-fused disconnect to be used in indoor and outdoor areas.

Certification: This disconnect switch is NRTL listed to UL 98 dead front switchboards and

NRTL listed for service equipment.

Mount: Operators can mount the service entrance disconnect on walls.

Customization: The MPD-DS-WML-NFDS-3P-3W-600V-400A-DF-BM-N4X-316SS-M1 can be customized to meet specific operating and power requirements. Example of customizations include:

• Making the non-fused disconnect portable and certified to NRTL UL 1640 for portable equipment

• Adding single pole camlock connectors for quick connections

• Adding heaters for cold environments

• Aiding alarm relays for trip notification downstream

• Adding power meters

Applications: This disconnect switch is suitable for indoor/outdoor use and applications including, but not limited to, construction sites, plant maintenance, plant turnarounds, hazardous location operations, shows, exhibits, and shipyard operations.

At Larson Electronics, we do more than meet your lighting needs. We also provide replacement, retrofit, and upgrade parts as well as industrial grade power accessories. Our craftsmen can custom build any lighting system and/or accessories to fit the unique demands of your operation. A commitment to honesty, quality, and dependability has made Larson Electronics a leader in the lighting and electronics business since 1973. Contact us today at 800-369-6671 or message sales@larsonelectronics.com for more information about our custom options tailored to meet your specific industry needs.

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

Frequently Asked Questions (FAQ)

There are no Faqs