Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

## IND-SFC-1P-1KVA-120V-60HZ-230-50HZ

# 1 KVA Solid-State Frequency Converter - 120V 60Hz Input to 230V 50Hz Output - 1PH - Mobile w/ Wheels

**Product ID: 330601**

Image: IND-SFC-1P-1KVA-120V-60HZ-230-50HZ

**Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.**

**IND-SFC-1P-1KVA-120V-60HZ-230-50HZ Frequency Converter**

**Unit Type:** Solid-state Static Frequency Converter
**Dimensions:** 14" x 21.2" x 27"
**Weight:** 132.27 lb
**Input Voltage:** 120 V 1PH +/- 5%
**Input Frequency:** 60 Hz +/- 5%
**Capacity:** 1 KVA - 100% Load - 30 Mins
**Output Voltage:** 230 V 1PH +/- 2%
**Output Frequency:** 50 Hz +/- 5%
**Rectification:** IGBT
**Efficiency Ratio:** Up to 95%
**Load Stabilization Rate:** < +/- 1%
**Frequency Stability:** < +/- 0.01%
**Harmonic Distortion:** Pure Sine Wave < 2%
**4-digit Meters:** Digital Frequency Meter- Resolution 0.1Hz/Step; Digital Voltage Meter - Resolution 0.1V; Digital Ammeter - Resolution 0.1A; Digital Watt Meter- Resolution 0.1W
**Protection:** Overload, Short Circuit, Over Temp, Instant Power Failure Protection, Alarm
**Operating Temp:** 0°C - 40°C
**Humidity:** 0-90% (Non-condensation)
**Mounting:** Mobile Cart w/ Wheels
**Color:** Tan

**Features/Ratings**

NRTL Listed to UL 508A
Advance Microprocessor Control
True Online Double Conversion
Smart Fan Control
Low Input THDi < 3%

**Special Orders - Special Requirements**

Contact us for special requirements
**Intl:** 1-903-270-1187
**Toll Free:** 1-800-369-6671
**Fax:** 1-903-765-7664
**E-mail:** sales@larsonelectronics.com

**The Larson Electronics IND-SFC-1P-1KVA-120V-60HZ-230-50HZ Solid-State Frequency Converter is designed for voltage and frequency rectification in industrial locations. The 1 KVA static converter comes with an input voltage/frequency of 120 V single-phase 60 Hz and an output voltage/frequency of 230 V single-phase 50 Hz. This unit is mobile via four wheels at the bottom of the enclosure.**

The IND-SFC-1P-1KVA-120V-60HZ-230-50HZ can be used to accurately convert voltages and frequencies in industrial sites. This 1 KVA unit offers 120 V single-phase 60 Hz on the input side and 230V single-phase 50 Hz on the output side. During operation, rectification is completed via IGBT. The static frequency converter provides robust microprocessor control, true online double conversion and active input power factor correction.

This solid-state frequency converter is equipped with several protective features, including overload, short circuit, over temp, instant power failure connection and alarm. For efficient operation, the unit features smart fan control and ultra high efficiency (98% in Smart Eco Mode). Operators are provided access to a panel, which houses various controls for meters. Available meter components include digital frequency meter, digital voltage meter, digital ammeter and digital watt meter.

**Mounting:** The IND-SFC-1P-1KVA-120V-60HZ-230-50HZ is secured inside a mobile enclosure with wheels for seamless mobility around the work site.

**Applications:** Industrial facilities, laboratories, air compressor testing, power supply testing, motor equipment testing, quality assurance, lighting systems and more.

At Larson Electronics, we do more than meet your lighting needs. We also provide replacement, retrofit, and upgrade parts as well as industrial grade power accessories. Our craftsmen can custom build any lighting system and/or accessories to fit the unique demands of your operation. A commitment to honesty, quality, and dependability has made Larson Electronics a leader in the lighting and electronics business since 1973. Contact us today at 800-369-6671 or message sales@larsonelectronics.com for more information about our custom options tailored to meet your specific industry needs.

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

# Frequently Asked Questions (FAQ)

There are no Faqs