HID-22SL-REM-125
Mogul Socket w/ Bracket for HID-22 Series

WARNING
To avoid the risk of fire, explosion or electric shock, this product should be installed, inspected and maintained by a qualified electrician only, in accordance with all applicable electrical codes.

To avoid electric shock:
- Be certain electrical power is OFF before and during installation and maintenance.
- Luminaire must be connected to a wiring system with an equipment-grounding conductor.
- Make sure the supply voltage is within the luminaires' voltage rating.



INSTALLATIOn
Disconnect power and remove old light head.
1. Disable power to ballast and detach lamp cord.
2. Allow fixture to cool.
3. Remove front lens. There is a single set screw and ring holding lens in place. Loosen set screw and carefully remove lens ring and lens.
4. Remove bulb.
5. Remove socket and detach from wiring.
6. Replace new socket in same way.
7. Ensure cords are attached and socket is secure.
8. Replace bulb.
9. Replace lens and lens holder ring.
10. Reconnect power.
11. Power lamp to test.

REPLACING THE BULB


1. To replace the bulb, loosen the screw to remove the outer ring holding the lens
2. Carefully remove the outer ring, glass lens and rubber seal.
3. Remove the old bulb from the unit.
4. Replace with matching fixture lamp.
5. Replace the seal, glass lens and outer ring. Hand tight the outer ring until snug. Do not over tighten.

MAINTENANCE
Caution: To avoid personal injury, disconnect power to the light and allow the unit to cool down before performing maintenance.

Perform visual, mechanical and electrical inspections on a regular basis. We recommend routine checks to be made on a yearly basis. Frequency of use and environment should determine this. It is recommended to follow an Electrical Preventive Maintenance Program as described in NFPA 70B: Recommended practice for Electrical Equipment.

WARRANTY
Should further information not covered by these instructions be required, please contact Larson Electronics at 1-800-369-6671 or sales@larsonelectronics.com for further assistance.

Please visit LarsonElectronics.com for **Warranty** and **Return** information.