Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

**HL-85-MP2**

# 100W Handheld Halogen Spotlight - 5 Million Candlepower - Spot/Flood - 16' Cord w/ 2-Pin Marine Plug

**Product ID: 147393**

**Please see last page for supporting documentation for this product(certificates, CAD files & drawings, IES files, wiring diagrams, etc).**



**Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.**

**HL-85-MP2 Handheld Halogen Spotlight**
**Lamp Type: Halogen**
**Dimensions: 8" W x 9" H**
**Weight: 13 Ounces**
**Total Watts: 100 watts**
**Candlepower Rating: 5 Million CP**
**Lumens: 2100**
**Voltage: 12 or 24 Volts**
**Amps: 8.5 amps at 12 VDC, 4.25 amps at 24 volts**
**Wiring: 16 Foot Coil Cord w/ 2-Pin Marine Plug**

**Features**
Water Resistant
UV Resistant
Chemical Resistant

**Special Orders- Requirements**
Contact us for special requirements
**Toll Free:** 1-800-369-6671
**Intl:** 1-903-270-1187
**Fax:** 1-903-498-3364
**E-mail:** sales@larsonelectronics.com

**The HL-85-MP2 from Larson Electronics is a 100 Watt Halogen Handheld Spotlight that emits 1800 lumens. It is ideal for applications including recreational boating, fishing, hunting, search and rescue and security. This spotlight produces a beam capable of expanding to 900 feet. This lightweight, ultra rugged, ergonomic spotlight operates on 12 volts or 24 volts DC and can be used as a spot or flood light.**
The handle and lamp housing support of the HL-85-MP2 are made from high impact nylon. The polycarbonate lamp housing is thick and contoured for extra support. The 16 gauge internal wiring and connectors are simple and well constructed. The industrial grade, tungsten filament bulb is designed for 1200 hours of life while producing over 5 million candlepower in this configuration. The impact resistant polycarbonate lens is

lightweight, shatter resistant and thermal resistant. The materials used in the construction of the HL-85 handheld spotlight are UV, water, impact and chemical resistant.



Click Photo to Enlarge



Click Photo to Enlarge

The reflector is uniquely shaped and shallow, capturing and focusing the light efficiently and effectively. Combined with a convex lens and inset lens positioning, this light optimally and efficiently captures and projects the right amount of light where the operator wants it. The position of the bulb and the shape of reflector are different than most handheld lighting products. The difference is in how much of the emitted light is captured and focused. In many ways, light shares the properties of water. With many spotlights, a great deal of the light "spills" on the ground around the light source. While a beam continues to project, much of the light "spills" out around the source, robbing the desired, projected beam of power. With the HL-85 spotlight configuration, 90% of the emitted light is captured and focused. A side benefit of this is a reduction of "casting", a phenomenon that occurs when the light "spills" around the light source. Often times, when surrounded by water, snow or other reflective surfaces, the light spillage will cause "casting" which effectively prevents the human eye from adjusting and seeing the objects at distance the spotlight was used to see.



Click Photo to Enlarge

The operator can lift the locking tab behind the lamp housing and rotate the lamp head. Rotating the housing enables the operator to adjust the beam from a wide, soft flood pattern to a tight, spot beam that goes out to 900 feet. Continued rotation to the extreme disconnects the lamp head from the handle assembly, enabling the operator to replace the bulb when necessary.
The HL-85-MP2 is an ultra-durable handheld spotlight that weighs only 13 ounces, which makes it easy to carry and operate. The unit is balanced for ergonomic comfort and handling. The handle is 4.5 inches long, 1.5 inches deep and 5/8 inch thick, making it easy to hold, even in wet, slippery conditions. The nylon handle has a no-slip textured surface to improve grip as well. The booted push button is conveniently placed so the user can easily access the switch with their fore finger for quick on/off action.
We have changed the wiring and the plug on the current model. Internally, we added 2 strain reliefs and a wire tie. Externally, we modified the coil cord setup. The previous coil cord had a multi-layer jacket. We have switched to a single SPT-2 jacket which should prevent any failure issues that occur when the operator is compelled to stretch the cord beyond its limit. Each Larson Electronics HL-85-MP2 spotlight comes with a detachable 16 foot coil cord with a 2-pin marine plug. The equipped plug is compatible with Perko sockets and other similar marine sockets.
A 3/8-16 inch brass nut fixture is imbedded in the base of the handle enabling the

operator to mount a magnetic base, like our MM-2 or MM-5 to the light. Alternatively, the operator can tripod mount this light as well. It also comes equipped with a lanyard attachment at the top of the handle for users that want to secure the light in the event they lose their grip.
This spotlight can be configured to operate on 12 volts at 8.5 amps or 24 volts at 4.25 amps. This is done by using a 12 volt, H3 bulb or 24 volt, H# bulb. H3 replacement bulbs are readily available at any automotive store in the US. All consumer vehicles use 12 volts DC. Most military vehicles use 24 volts DC. There is no difference in light output, its only the matter of choosing the right voltage for your vehicle.



5 inch lens




Click Photos to Enlarge



7 inch lens (Optional)

We also now offer a 5 inch diameter and a 7 inch diameter lens. Although the difference is not significant, the 5 inch lens produces a tighter spot beam while the 7 inch lens produces a wider coverage flood pattern
**Note on Voltage:** Most vehicles are 12 Volt DC. 24 Volts ***DOES NOT*** mean more power. Running a 24V light from a 12V power source will result in a very dim or non-functioning light, and may cause internal damage to the light as well. For common vehicle use, please order 12V.
At Larson Electronics, we do more than meet your lighting needs. We also provide replacement, retrofit, and upgrade parts as well as industrial grade power accessories. Our craftsmen can custom build any lighting system and/or accessories to fit the unique demands of your operation. A commitment to honesty, quality, and dependability has made Larson Electronics a leader in the lighting and electronics business since 1973. Contact us today at 800-369-6671 or message sales@larsonelectronics.com for more information about our custom options tailored to meet your specific industry needs.

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

# Frequently Asked Questions (FAQ)









Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

**HL-85-MP2**

**Product ID: 147393**

**Harmonized System (HS) Code:** 8512.20.2080
**Export Control Classification Number (ECCN):** EAR99

**Options:**

**HL-85-MP2-Voltage-Lens Size**

**Example: HL-85-MP2-12V-5**

| Voltage | |
|---|---|
| 12 VOLTS | -12V |
| 24 VOLTS | -24V |

| Lens Size | |
|---|---|
| 5 | -5 |
| 7 | -7 |

Links (Click on the below items to view):

- **Catalog Page - Product Series**
- **Operations Manual**
- **SpecSheetSpanish**
- **HigResPic1**
- **HigResPic2**
- **HigResPic3**
- **HigResPic4**
- **HigResPic5**
- **HigResPic6**
- **HigResPic7**
- **HigResPic8**
- **HigResPic9**
- **HigResPic10**
- **ISO 9001 Certification**
- **Business Certificate**
- **Shipping Time Map**