

10 Watt Class I, Div. I & II Emergency Lighting System - 3 Hours - Explosion Proof Bug Eyes EXP-EMG-5W-2L



EXP-EMG-5W-2L

Listing: United States
Lamp Type: LED
Dimensions: 28.67"-H, 33.50"-W
Voltage: 120-277V AC 60Hz
Total Watts: 10
Total Lumens: 900
Luminous Efficacy: 90 Lm/W
Lamp Life: 50,000+ Hours
Color Temp: 6000K, 4300K, 3000K
Color Rendering Index: >75 CRI
Beam Angle: 360°
Lighting Configuration: "Bug Eyes" Dual light heads
Power Efficiency: 90%
Power Factor: >0.95
Amperage: 0.17A @ 120V, 0.08A @ 240V, 0.07 @ 277V
Lamp Ambient Operating Temp: -25°C to +50°C
Lamp Housing Material: Copper Free Aluminum Housing
Lens Material: Diffused Borsolite Glass
Mounting: Non-Sparking Aluminum Housing
Mounting: Wall/Flat Surface Mount
Wiring: 3/4" NPT Threaded for Conduit

Battery Backup Runtime: 180 Minutes
Test Switch: Yes - Momentary (single pole)
Battery Type: High Temp Nickel-Cadmium (Maintenance free)
Battery Input Voltage: 120/277V AC 60Hz
Battery Input Power Rating: 9.5 Watts
Battery Output Voltage: 120/277V AC 60Hz
Battery Output Current: 165 mA @ 120V, 72 mA @ 277V
Battery Output Power: 20 Watts (Max)
Battery Operating Temp: 0° to +50°C
Battery Recharge Time: 24 hours from full discharge
Battery Charge Current: 90 mA
Battery Life Expectancy: 10 years
Warranty: Yes - 3 Years*

U.L Ratings

Class I, Division I & II, Groups C & D
Class II, Division I & II, Groups E,F,G
Class III
IP67 (water proof) rating
UL 844
UL 924
T3C Temperature Rating
NFPA101 (Life Safety Code)

Special Orders- Requirements

Contact us for special requirements

Toll Free: 1-800-369-6671

Intl: 1-903-270-1187

E-mail: sales@larsonelectronics.com

Links (Click on the below items to view):

- [bottom view of the led emergency backup led lighting system](#)
- [large](#)
- [medium](#)
- [rear view of the led emergency ballast backup light](#)
- [side view of the emergency backup led light fixture](#)
- [SpecSheetRussian](#)
- [SpecSheetSpanish](#)
- [wall mount bracket for the led emergency backup light fixture](#)
- [HigResPic1](#)
- [HigResPic2](#)
- [HigResPic3](#)
- [HigResPic4](#)
- [HigResPic5](#)
- [HigResPic6](#)
- [HigResPic7](#)
- [HigResPic8](#)
- [HigResPic9](#)
- [HigResPic10](#)