

XLE-MH-PS-50-1227

Replacement Ballast - 50W Metal Halide - Programmed Start - 120/277

Product ID: 150742

Please see last page for supporting documentation for this product(certificates, CAD files & drawings, IES files, wiring diagrams, etc).



Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

Replacement ballast - 120-277V - 50W MH - PROGRAM PULSE START

Volts: 120-277

Watts: 50

Ballast Type: Electronic

Start Method: Programmed Start

Package Qty: 1

Case Qty: 20

Additional Info: 50W MH (ANSI CODE: M110, M148)
PROGRAM PULSE START
OPEN/SHORT CIRCUIT PROTECTION
HOT LAMP DETECTION
MIN. STARTING TEMP.: -30 DEGREES C
SOUND RATING A
TYPE 1 OUTDOOR
UL Listed
IP 65

Max Tc 90 Degrees C.

Frequently Asked Questions (FAQ)



XLE-MH-PS-50-1227

Product ID: 150742

Export Control Classification Number (ECCN): EAR99

Links (Click on the below items to view):

- [HigResPic1](#)
- [HigResPic2](#)
- [ISO 9001 Certification](#)
- [Business Certificate](#)
- [Shipping Time Map](#)