

IND-SW-3P-600V-30A

600V 3 Pole Standard Toggle Switch - 3 Phase - 30 Amp

Product ID: 151123

Please see last page for supporting documentation for this product(certificates, CAD files & drawings, IES files, wiring diagrams, etc).



Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

IND-SW-3P-600V-30A Emergency Push Button

Type: Motor Control Toggle Switch

Dimensions: 3.78" L x 3.56" W x 2.83" D

Weight: 0.8 lbs

Rated Voltage: 600V

Amps: 60A

Short Circuit Withstand Rating as Motor Controller: 125A Max RK5 Fuses

Short Circuit Withstand Rating as Motor Disconnect: 80A Max J Fuses 10,000 RMS

Operating Temperatures: -40° C to 60° C

Poles: 3 Poles

Phase: 3 Phase

Terminal Torque: 25 Inch Pounds

Electrical Life: 6,000 Cycles at Rated Switch Load

Max Voltage: 600V AC RMS

Dielectric Voltage: 2,200V AC Minimum for 1 Minute

Features/Ratings

CSA-C22.2 No. 14

UL 508

Special Orders - Special Requirements

Contact us for special requirements

Toll Free: 1-800-369-6671

Intl: 1-903-270-1187

E-mail: sales@larsonelectronics.com

Made in the USA

The Larson Electronics IND-SW-3P-600V-30A Toggle Motor Controller/Disconnect offers accurate control of connected equipment and machines in industrial facilities. The 600V-rated unit 60 amp unit provides operators with long-life reliability.

The IND-SW-3P-600V-30A is a standard toggle switch motor controller and disconnect with on/off quick make/slow break operation. This 3 Phase 600V-rated unit has a 10,000 amp high fault short circuit withstand rating, 125 amp rating as

a motor controller and an 80 amp max rating as a motor disconnect. This 3-Pole toggle motor controller is UL 508 and CSA listed, and offers a 6,000 cycle electrical life at the rated switch load.

At Larson Electronics, we do more than meet your lighting needs. We also provide replacement, retrofit, and upgrade parts as well as industrial grade power accessories. Our craftsmen can custom build any lighting system and/or accessories to fit the unique demands of your operation. A commitment to honesty, quality, and dependability has made Larson Electronics a leader in the lighting and electronics business since 1973. Contact us today at 800-369-6671 or message sales@larsonelectronics.com for more information about our custom options tailored to meet your specific industry needs.

Frequently Asked Questions (FAQ)



IND-SW-3P-600V-30A

Product ID: 151123

Export Control Classification Number (ECCN): EAR99

Links (Click on the below items to view):

- [HigResPic1](#)
- [ISO 9001 Certification](#)
- [Business Certificate](#)
- [Shipping Time Map](#)