Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

MT-TX-DC-48V-1KVA-12V-83A-N3R

1 KVA DC to DC Transformer - 48V DC to 12V DC - 83 Amps, Fan Cooled - N3R

Product ID: 272830

Please see last page for supporting documentation for this product(certificates, CAD files & drawings, IES files, wiring diagrams, etc).



Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

MT-TX-DC-48V-1KVA-12V-83A-N3R - DC to DC Step-down Transformer

Unit Type: Industrial DC to DC Transformer
Dimensions: 12" W x 6" D x 18"H
Weight: -
Input Voltage: 48V DC
Output Voltage: 12V DC
Output Amps: 83A
Max Capacity: 1 KVA
Cooling: Fan
Operating Temp: -40°C to +65°C
Materials: Steel
Finish: Powder Coated
Mount: Wall
Input/Output Connections: Terminal Blocks

Ratings

Certified to United States and Canada
NRTL Certified to UL 508A
NRTL Certified to CSA C22.2 No. 14
Class A/B EMC Filter
NEMA 3R Weatherproof

Special Orders - Special Requirements

Contact us for special requirements

Intl: 1-903-270-1187
Toll Free: 1-800-369-6671
Fax: 1-903-498-3364
E-mail: sales@larsonelectronics.com

The Larson Electronics MT-TX-DC-48V-1KVA-12V-83A-N3RWeatherproof DC to DC Step-down Transformer converts 48V DC electrical current to 12V DC at 83 amps max. This converter includes terminal block connections for input/output terminations. The unit takes 48 volts DC and converts it to 12 volts DC, allowing users to use 48V DC power to operate equipment like our LED light bars and Golights.

The MT-TX-DC-48V-1KVA-12V-83A-N3R power converter provides a safe and effective way for users to tap into and utilize 48V DC power sources and step down this current to 12V DC. This unit can be operated with 48V DC input current and will output 12V DC current to power lights and equipment. The small size of this unit makes it ideal for indoor-outdoor operation of Larson Electronics LED light bars, Golights and other equipment that requires 12V DC current in locations where 48V DC power is readily available.

Features: The MT-TX-DC-48V-1KVA-12V-83A-N3Rconverter can be operated with 48V DC. The unit converts this DC power input to 1 KVA, 12V DC at 83 amps. This power device is equipped with a Class A/B EMC filter and utilizes fan cooling. The transformer is enclosed in a powder coated steel housing for durability. The power converter has a -40°C to +65°C operating temperature range. This converter is equipped with terminal block connections for input/output terminations. Operators can mount the unit on walls.

NOTE: In order to obtain the best performance and the longest operational life from these units, it is recommended that you do not exceed 75% of the unit's output amperage. To determine if this converter suits your desired application, add together the total wattage of the equipment you intend to use with this unit and divide this total by 36 volts to find the total amperage draw that will be placed upon the converter. Running these units at 100% of their capacity can create excess heat and lead to shortened converter life.

At Larson Electronics, we do more than meet your lighting needs. We also provide replacement, retrofit, and upgrade parts as well as industrial grade power accessories. Our craftsmen can custom build any lighting system and/or accessories to fit the unique demands of your operation. A commitment to honesty, quality, and dependability has made Larson Electronics a leader in the lighting and electronics business since 1973. Contact us today at 800-369-6671 or message sales@larsonelectronics.com for more information about our custom options tailored to meet your specific industry needs.

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

Frequently Asked Questions (FAQ)

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364



Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364







MT-TX-DC-48V-1KVA-12V-83A-N3R

Product ID: 272830

Harmonized System (HS) Code: 85043300

Export Control Classification Number (ECCN): EAR99

Links (Click on the below items to view):

- HigResPic1
- HigResPic2
- HigResPic3
- HigResPic4
- HigResPic5
- HigResPic6
- HigResPic7
- HigResPic8
- HigResPic9
- ISO 9001 Certification
- Business Certificate
- Shipping Time Map