Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

MTPC-HD-RB-240V-28HP-15HP-N3R

28 KVA Rotary Phase Converter for Hard Loads, 240V 1PH to 3PH, 120 Amps 1-Ph Full Load Current, 28 HP Motor HP, 15 HP Load, NEMA 3R

Product ID: 313826

Please see last page for supporting documentation for this product(certificates, CAD files & drawings, IES files, wiring diagrams, etc).



Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

MTPC-HD-RB-240V-28HP-15HP-N3R Rotary Phase Converter

Unit Type: Rotary Phase Converter
Phase Conversion: Single Phase to Three Phase
Converter Capacity: 28 KVA
Single Phase Voltage Input: 240V
Largest 3-Ph Motor Horse Power: 25 HP
Total 3-Ph Motor Horse Power: 28 HP
Load Horse Power: 15 HP
Full Load Input (1-Ph) Current: 120A
Service Load Type: Hard motor loads
Three Phase Voltage Output: 240V
Optimal Output Amps: -
Maximum Output Amps: -
Maximum Resistive Amps: -
Voltage Balance: 2-5%
Minimum Wire to Device Load: 3 AWG
Enclosure Rating: NEMA 3R
Form Factor: Rectangular Enclosure, Cylindrical Idler w/ Four Legs
Color: Natural Gray
Weight: 445 lbs
Converter Dimensions: 20-7/8"-W x 21-1/8"-D x 15-5/8"-H
Enclosure Dimensions: 25-1/2"-W x 10-15/16"-D x 17-5/8"-H
Shipping Weight: -

Ratings/Approvals

Indoor/Outdoor Use (NEMA 3R)
Built-in Motor Starter
Accurate Voltage Balancing
Power Indicator Light
Start/Stop Push Button Switch
Made in the USA

Special Orders - Special Requirements

Contact us for special requirements

Toll Free: 1-800-369-6671

Intl: 1-903-270-1187

Shipping Dimensions: -

Fax: 1-903-498-3364

E-mail: sales@larsonelectronics.com

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

Frequently Asked Questions (FAQ)



Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364



Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364





Export Control Classification Number (ECCN): EAR99

Links (Click on the below items to view):

- HigResPic1
- HigResPic2
- HigResPic3
- HigResPic4
- HigResPic5
- HigResPic6
- HigResPic7
- HigResPic8
- HigResPic9
- HigResPic10
- Video1
- ISO 9001 Certification
- Business Certificate
- Shipping Time Map