

MPD-PNL-3P-MCB-400A-480V-2X3P.B-N1

Power Distribution Panel – 480V AC 3PH – 400A MCB – (2) Breakers – NEMA 1

Product ID: 327191

Please see last page for supporting documentation for this product (certificates, CAD files & drawings, IES files, wiring diagrams, etc).



Image: MPD-PNL-3P-MCB-400A-480V-2X3P.B-N1

Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

MPD-PNL-3P-MCB-400A-480V-2X3P.B-N1 Power Distribution Panel

Line In: Customer Provided

Max Primary OCP: 400A @ 480V

Panel: 400A 480V 3PH MCB NEMA 1

Circuits: 18 Poles

Breakers: (1) 125A 3P Circuit Breaker, (1) 50A 3P Circuit Breaker

Breaker Type: Bolt-on

Feed Type: Top or Bottom

Interrupting Rating: 14 kAIC

Operating Temperature: 40°C

Materials: Steel, Copper

Bus Material: Copper

Ground Bar Material: Aluminum (Bolted)

Form Factor: Slim-profile NEMA 1 Surface-Mount Enclosure w/ Lockable Door

Input Wire Size: -

Dimensions: 20" W x 56" H x 6" D

Weight: 900 lbs

Shipping Weight: -

Larson Electronics manufactures a wide variety of custom power distribution systems. The pictures displayed for this unit are a general representation of form factor and may not accurately represent this exact configuration in every detail due to being custom builds. The specifics for this configuration are listed in the specification table and one-line diagram.

Ratings

UL 1640 Power-Distribution Equipment

NEMA 1 Indoor Use

Made in the USA

Special Orders - Special Requirements

Contact us for special requirements

Intl: 1-903-270-1187

Toll Free: 1-800-369-6671

Fax: 1-903-765-7664

E-mail: sales@larsonelectronics.com

All grounding shall comply with state and local codes and meet the minimum requirements of the National Electronic Code section 250

The Larson Electronics MPD-PNL-3P-MCB-400A-480V-2X3P.B-N1 Power Distribution Panel is designed for reliable, safe and convenient power distribution at industrial work sites. This 400-amp unit provides 480V three phase via a main circuit breaker panel. The power distribution panel provides operators the ability to safely tap into and distribute 480V AC power from a variety of sources including generators and direct grid power.

****PLEASE NOTE: ANY FREE SHIPPING OFFERS DO NOT APPLY TO POWER DISTRIBUTION PANELS, TRANSFORMERS, OR SUBSTATIONS****

The MPD-PNL-3P-MCB-400A-480V-2X3P.B-N1 power distribution panel provides a safe and reliable way for operators in industrial settings to tap into and utilize power sources independently of the work area. The power distribution panels require operators to provide their own line-in cables for use. Knockouts are provided for convenient installation of operator provided cables.

The panel is designed to operate with 480V three phase voltage. Power distribution for this panel runs 480V through a 400-amp main circuit breaker panel. The main circuit breaker panel contains 18, 3-pole molded case circuit breakers.

Enclosure Design: This power distribution panel is housed in a space-saving NEMA 1 enclosure for protection against dust, dirt and moisture in indoor locations. Constructed of steel, the unit's slim, rectangular profile is compatible with plug-in mounting configurations. A lockable opening deters the possibility of tampering. We also offer similar power distribution panels on dolly carts with wheels, powder coated cube frames with lifting eyelets/skid pockets or stand-alone with handles for faster turnarounds and completion of temporary tasks.

Certification: Larson Electronics is a UL 1640 panel shop and certified to build power distribution systems. All units are built in accordance to NFPA 70 (National Electric Code) and certified to UL 1640. All equipment is NEMA 1 rated for indoor use and provide a degree of protection against dirt, water, and ice. NEMA 3R, NEMA 4 and NEMA 4X equipment can be equipped upon request.

Grounding: Transformer is grounded to the frame and we provide a grounding lug on the frame for the earth ground.

~Please check all motor loads for dual rated motors that will work 208 or 240.~

Applications: This power distribution system is NEMA 1 rated and ideal for indoor use and applications including but not limited to; construction sites, plant maintenance, plant turnarounds, hazardous location operations, shows, exhibits, and shipyard operations.

At Larson Electronics, we do more than meet your lighting needs. We also provide replacement, retrofit, and upgrade parts as well as industrial grade power accessories. Our craftsmen can custom build any lighting system and/or accessories to fit the unique demands of your operation. A commitment to honesty, quality, and dependability has made Larson Electronics a leader in the lighting and electronics business since 1973. Contact us today at 800-369-6671 or message sales@larsonelectronics.com for more information about our custom options tailored to meet your specific industry needs.



Frequently Asked Questions (FAQ)

There are no Fags



Export Control Classification Number (ECCN): EAR99



Links (Click on the below items to view):

- **HigResPic1**(<https://www.larsonelectronics.com/images/product/HigResPic1/327191.JPG>)
- **ISO 9001 Certification**(<http://larsonelectronics.com/images/pdfdocs/ISO9001.PDF>)
- **Business Certificate**(<https://www.larsonelectronics.com/images/pdfdocs/w9.PDF>)
- **Shipping Time Map**(<https://www.larsonelectronics.com/images/product/ShippingTimeMap/ShippingTimeMap.pdf>)