

MT-ISX-FP-1P-120V-2KVA-132V-N3R

2 kVA Isolation Transformer - 120V AC Primary - 132V AC Secondary - NEMA 3R - 1 Phase - Fully Potted

Product ID: 335494

Please see last page for supporting documentation for this product (certificates, CAD files & drawings, IES files, wiring diagrams, etc).



Image: MT-ISX-FP-1P-120V-2KVA-132V-N3R

Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

MT-ISX-FP-1P-120V-2KVA-132V-N3R Fully Potted Isolation Transformer

Phase: Single Phase
Frequency: 60 Hz
Capacity: 2 kVA
Primary Voltage: 120V AC
Secondary Voltage: 132V AC
Current Rating: 15A Steady, 2000A for 60 ms
Winding Material: Aluminum
Impedance: 1 - 5%
Insulation: 180°C
Temperature Rise: 115°C
Seismic Zone: -
Primary Termination: Leadwires
Secondary Termination: Leadwires
Mounting: Wall
Sound Level: Meets NEMA ST-20 Standards
Enclosure Material: NEMA Type 3R
Finish: ANSI 61 Grey Finish
Dimensions: 11.75"H x 7.06"W x 6.25"D
Weight: 55 lbs

Approvals/Ratings

NRTL Listed for United States and Canada
NEMA 3R Rated
Fully Potted / Encapsulated
Isolation Transformer
UL Listed

Special Orders - Special Requirements

Contact us for special requirements
Toll Free: 1-800-369-6671
Intl: 1-903-270-1187
E-mail: sales@larsonelectronics.com

The MT-ISX-FP-1P-120V-2KVA-132V-N3R 2 kVA 1 Phase Energy Efficient Fully Potted Isolation Transformer from Larson Electronics is powerful, reliable and designed with the environment in mind. Suitable for both indoor and outdoor applications, the MT-ISX-FP-1P-120V-2KVA-132V-N3R provides increased reliability, protection against critical equipment failures and an extra level of protection by isolating the power source from the connected device. The lower operating costs, lower heat emissions and lower cost of ownership make this transformer ideal for a wide range of applications and businesses.

PLEASE NOTE: ANY FREE SHIPPING OFFERS DO NOT APPLY TO POWER DISTRIBUTION PANELS, TRANSFORMERS, OR SUBSTATIONS

Transformer Features: With a transformer rating of 2 kVA (2000 Volt Amps), the MT-ISX-FP-1P-120V-2KVA-132V-N3R isolation transformer is a single phase unit with a primary voltage of 120V. It also provides a secondary voltage of 132V. Featuring robust construction, this unit's cores are manufactured with non-aging, cold-rolled silicon steel laminations using state of the art technology.

This fully potted unit boasts a low cost of ownership and is highly energy efficient. Lower heat emissions mean less cooling is needed as well. The standard type 3R enclosure makes the unit suitable for both indoor and outdoor applications and it can be wall mounted. The unit also features 180°C insulation with a 115°C temperature rise.

Benefits: The MT-ISX-FP-1P-120V-2KVA-132V-N3R isolation transformer offers many benefits to the consumer. Precision cut aluminum transformer winding material helps to improve performance. The close tolerances used during manufacturing also eliminate burrs, which hinder performance. Each core is specially coated to prevent the ingress of moisture and is electrically balanced to minimize axial forces during short circuit situations.

This encapsulated transformer provides owners with significant energy savings as well as offering environmental benefits. Higher efficiency not only extends the life of the transformer, but also turns into cost savings for owners in the form of lower energy bills and decreased cost of ownership. This transformer is designed for panel mounting.

Safety: The MT-ISX-FP-1P-120V-2KVA-132V-N3R is an isolation transformer which means that it provides operators with an increased level of protection against electric shock. An isolation transformer can also suppress electrical noise in sensitive devices and transfer power between two circuits which must not be connected. The MT-ISX-FP-1P-120V-2KVA-132V-N3R achieves these safety features by separating or "isolating" the powered device from the power source and insulation between the primary and secondary power sources.

Applications: Power supplies for sensitive equipment such as computers, medical devices, or laboratory instruments.

Larson Electronics is a manufacturer and as such can build stationary and portable transformer systems to your specifications. Although we carry several models of power distribution transformer systems, we can deliver custom ordered units almost as quickly as our prebuilt units. If this model does not meet your needs, please contact us at 1-800-369-6671 or sales@larsonelectronics.com to discuss your specific requirements.



Frequently Asked Questions (FAQ)

There are no Fags



Image: MT-ISX-FP-1P-120V-2KVA-132V-N3R



Image: MT-ISX-FP-1P-120V-2KVA-132V-N3R



Image: MT-ISX-FP-1P-120V-2KVA-132V-N3R



Image: MT-ISX-FP-1P-120V-2KVA-132V-N3R



Export Control Classification Number (ECCN): EAR99



Links (Click on the below items to view):

- **Operations Manual**(<https://www.larsonelectronics.com/images/product/Manual/335494.PDF>)
- **Wiring Diagram**(<https://www.larsonelectronics.com/images/product/WiringDiagram/335494.PDF>)
- **HigResPic1**(<https://www.larsonelectronics.com/images/product/HigResPic1/335494.JPG>)
- **HigResPic2**(<https://www.larsonelectronics.com/images/product/HigResPic2/335494.JPG>)
- **HigResPic3**(<https://www.larsonelectronics.com/images/product/HigResPic3/335494.JPG>)
- **HigResPic4**(<https://www.larsonelectronics.com/images/product/HigResPic4/335494.JPG>)
- **HigResPic5**(<https://www.larsonelectronics.com/images/product/HigResPic5/335494.JPG>)
- **HigResPic6**(<https://www.larsonelectronics.com/images/product/HigResPic6/335494.JPG>)
- **HigResPic7**(<https://www.larsonelectronics.com/images/product/HigResPic7/335494.JPG>)
- **ISO 9001 Certification**(<http://larsonelectronics.com/images/pdfdocs/ISO9001.PDF>)
- **Business Certificate**(<https://www.larsonelectronics.com/images/pdfdocs/w9.PDF>)
- **Shipping Time Map**(<https://www.larsonelectronics.com/images/product/ShippingTimeMap/ShippingTimeMap.pdf>)