

MT-CTX-3P-480D-100VA-400D

100 VA Control Transformer - Three Phase - 480D Input Voltage - 400D Output Voltage - 50/60 Hz

Product ID: 339694

Please see last page for supporting documentation for this product (certificates, CAD files & drawings, IES files, wiring diagrams, etc).



Image: MT-CTX-3P-480D-100VA-400D

Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

MT-CTX-3P-480D-100VA-400D Control Transformer

Phase: Three Phase

Frequency: 50/60 Hz

Capacity: 100 VA (0.10 kVA)

Primary Voltage: 480V AC Delta

Primary Connection: Series (V)

Primary FCAN (Std.): 0 x 0%

Primary FCBN (Std.): 0 x 0%

Secondary Voltage: 400V AC Delta

Secondary Connection: Parallel x Series (Vx2V)

Material: Copper

Primary Termination: Terminal Block

Secondary Termination: Terminal Block

Insulation: 130°C

Temperature Rise: 80°C

Enclosure Material: Injection Molded Cover

Mounting: Heavy Steel Feet

Dimensions: 3.38"-H x 3.75"-W x 3.50"-D

Weight: 5.9 lbs

Approvals/Ratings

NRTL Listed for United States and Canada

NRTL Certified to CSA 22.2 NO 66.1

NRTL Certified to CSA 22.2 NO 66.2

NRTL Certified to UL 5085-1

NRTL Certified to 5085-2

Control Transformer

Special Orders - Special Requirements

Contact us for special requirements

Toll Free: 1-800-369-6671

Intl: 1-903-270-1187

E-mail: sales@larsonelectronics.com

The MT-CTX-3P-480D-100VA-400D from Larson Electronics is a 100 VA Three Phase Control Transformer that is powerful, reliable, and innovatively designed. With high-quality silicon steel laminations providing optimal performance, the MT-CTX-3P-480D-100VA-400D provides increased reliability and protection against critical equipment failures. This control transformer features an innovative design with a unique terminal block design that allows for a quick and easy hookup along with the ability to easily install fuse clips to the unit. The uniquely designed molded coil covers give this control transformer superior cooling abilities and a sleek appearance.

Transformer Features: With a transformer rating of 100 VA (0.10 kVA), the MT-CTX-3P-480D-100VA-400D is a machine tool industrial three phase control transformer with primary voltages of 480V AC Delta. It also provides secondary voltage of 400V AC Delta. Featuring compact and innovative construction, this unit's cores are manufactured with high-quality silicon steel laminations using state of the art technology.

This unit boasts an innovative terminal block design that allows for easy hookup. Connecting this unit is a simple task thanks to the terminal connection numbers being molded into the terminal block which corresponds to the nameplate and wiring diagrams. A unique fin-shaped, injection molded coil cover gives this unit superior cooling abilities. The unit also features a 130°C insulation class with an 80°C temperature rise.

Benefits: The MT-CTX-3P-480D-100VA-400D control transformer offers many benefits to the consumer. Full encapsulation of the windings and internal terminations ensures that the unit is protected from moisture, dirt, dust, and other contaminants. Removeable finger safe terminal covers contribute towards the overall clean and sleek look of the unit. The compact and innovative design features make this a great choice for industrial tool applications.

This control transformer has heavy steel mounting feet that are either welded or bolted to the core. This transformer features terminal block terminations.

Applications: Power Managment, Industrial

Larson Electronics is a manufacturer and as such can build stationary and portable transformer systems to your specifications. Although we carry several models of power distribution transformer systems, we can deliver custom ordered units almost as quickly as our prebuilt units. If this model does not meet your needs, please contact us at 1-800-369-6671 or sales@larsonelectronics.com to discuss your specific requirements.



Frequently Asked Questions (FAQ)

There are no Fags



Image: MT-CTX-3P-480D-100VA-400D



Image: MT-CTX-3P-480D-100VA-400D



Image: MT-CTX-3P-480D-100VA-400D



Image: MT-CTX-3P-480D-100VA-400D



Export Control Classification Number (ECCN): EAR99



Links (Click on the below items to view):

- **HigResPic1**(<https://www.larsonelectronics.com/images/product/HigResPic1/339694.JPG>)
- **HigResPic2**(<https://www.larsonelectronics.com/images/product/HigResPic2/339694.JPG>)
- **HigResPic3**(<https://www.larsonelectronics.com/images/product/HigResPic3/339694.JPG>)
- **HigResPic4**(<https://www.larsonelectronics.com/images/product/HigResPic4/339694.JPG>)
- **HigResPic5**(<https://www.larsonelectronics.com/images/product/HigResPic5/339694.JPG>)
- **HigResPic6**(<https://www.larsonelectronics.com/images/product/HigResPic6/339694.JPG>)
- **HigResPic7**(<https://www.larsonelectronics.com/images/product/HigResPic7/339694.JPG>)
- **HigResPic8**(<https://www.larsonelectronics.com/images/product/HigResPic8/339694.JPG>)
- **ISO 9001 Certification**(<http://larsonelectronics.com/images/pdfdocs/ISO9001.PDF>)
- **Business Certificate**(<https://www.larsonelectronics.com/images/pdfdocs/w9.PDF>)
- **Shipping Time Map**(<https://www.larsonelectronics.com/images/product/ShippingTimeMap/ShippingTimeMap.pdf>)