Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

MPD-NFMDS-120.240V-30A-2P-N12-M1

30 Amp Non-Fused Manual AC Disconnect Safety Switch - 120/240V AC - 2-Pole - NEMA 12

Product ID: 313885



Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

MPD-NFMDS-120.240V-30A-2P-N12-M1 Non-Fused AC Disconnect Switch

Use: Non-Fused AC Disconnect Switch
Type: Power Distribution System Accessory
Max Amp Rating: 30 Amps
Disconnect Type: Non-Fused
Enclosure Type: Metallic
Enclosure Rating: NEMA 12
Receptacles: None
Mounting Type: Surface
Poles: 2-Poles
Terminal Type: Screw
Voltage Rating: 120/240V AC
Wiring Configuration: 3-Wire
Finish Powder Coated, SAE-AMS-STD-595 Standard Color No. 22563.

Ratings/Features:

UL Listed
NEMA 12 Enclosure
30 Amp Rating
120/240V AC Voltage Rating
Indoor Metallic Enclosure
Mounts to Any Flat Surface
Provides Overload Protection to Transformers

Special Orders - Special Requirements

Contact us for special requirements
Toll Free: 1-800-369-6671
Intl: 1-903-270-1187
E-mail: sales@larsonelectronics.com

The MPD-NFMDS-120.240V-30A-2P-N12-M1 is an AC Disconnect Switch that is an accessory for power distribution systems. This AC disconnect switch power distribution accessory acts as an overload breaker that will protect operators from overloading a transformer. The MPD-NFMDS-120.240V-30A-2P-N12-M1 is encased in a NEMA 12 enclosure and is UL listed.

The MPD-NFMDS-120.240V-30A-2P-N12-M1 is a non-fused AC disconnect switch that is rated for 30 amps and features a safety disconnect switch. This power distribution accessory has a 2-pole 3-wire configuration along with a 120/240V AC voltage rating. The MPD-NFMDS-120.240V-30A-2P-N12-M1 can be securely mounted to any flat surface.

Applications: Residential and light commercial applications, air conditioning units and any other power distribution systems that require overload breaker protection.

At Larson Electronics, we do more than meet your lighting needs. We also provide replacement, retrofit, and upgrade parts as well as industrial grade power accessories. Our craftsmen can custom build any lighting system and/or accessories to fit the unique demands of your operation. A commitment to honesty, quality, and dependability has made Larson Electronics a leader in the lighting and electronics business since 1973. Contact us today at 800-369-6671 or message sales@larsonelectronics.com for more information about our custom options tailored to meet your specific industry needs.



Frequently Asked Questions (FAQ)