Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

IND-SFC-3P-10KVA-208V-60HZ-200.115-400HZ-N1

10 KVA Solid-state Voltage Frequency Converter - 208V 60Hz to 200/115V 400Hz - 3PH Delta - Floor Mounted - NEMA 1

Product ID: 316347



Image: IND-SFC-3P-10KVA-208V-60HZ-200.115-400HZ-N1

Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

IND-SFC-3P-10KVA-208V-60HZ-200.115-400HZ-N1 Frequency Converter

Unit Type: Solid-state Voltage Frequency Converter
Dimensions: 22" W x 63" H x 32" D
Weight: 850 lbs
Input Voltage: 208V 3PH Delta +/- 5% 3P3W+G
Input Frequency: 60 Hz +/- 5%
Capacity: 10 KVA - 100% Load - 30 Mins
Output Voltage: 200V 3PH (L-L), 115V (L-N) +/- 2% 3P4W+G
Output Frequency: 400 Hz +/- 5%
Rectification: IGBT
Efficiency Ratio: Up to 95%
Load Stabilization Rate: < +/- 1%
Frequency Stability: < +/- 0.01%
Harmonic Distortion: Pure Sine Wave < 2%
4-digit Meters: Digital Frequency Meter- Resolution 0.1Hz/Step; Digital Voltage Meter- Resolution 0.1V; Digital Ammeter- Resolution 0.1A; Digital Watt Meter- Resolution 0.1W
Protection: Overload, Short Circuit, Over Temp, Instant Power Failure Protection, Alarm
Operating Temp: 0-40°
Humidity: 0-90% (Non-condensation)
Enclosure: NEMA 1
Mounting: Pad/floor mount, freestanding
Color: Tan

Features/Ratings

NRTL Listed to UL 508A
Advance Microprocessor Control
True Online Double Conversion
Smart Fan Control
Low Input THDi < 3%

Special Orders - Special Requirements

Contact us for special requirements
Intl: 1-903-270-1187
Toll Free: 1-800-369-6671
Fax: 1-903-765-7664
E-mail:

sales@larsonelectronics.com

The Larson Electronics IND-SFC-3P-10KVA-208V-60HZ-200.115-400HZ-N1 Solid-state Voltage Frequency Converter is designed for voltage and frequency rectification in industrial locations. The 10 KVA converter comes with an input voltage/frequency of three-phase 208V Delta, 60 Hz and an output voltage/frequency of three-phase 400V Delta, 50 Hz. This unit is floor mounted freestanding NEMA 1 enclosure.

The IND-SFC-3P-10KVA-208V-60HZ-200.115-400HZ-N1 can be used to accurately convert voltages and frequencies in industrial sites. This 10 KVA unit offers three-phase 208V Delta, 60 Hz on the input side and three-phase 200/115V Wye, 400 Hz on the output side. During operation, rectification is completed via IGBT. The frequency converter provides robust microprocessor control, true online double conversion and active input power factor correction.

This solid-state frequency converter is equipped with several protective features, including overload, short circuit, over temp, instant power failure connection and alarm. For efficient operation, the unit features smart fan control and ultra high efficiency (98% in Smart Eco Mode). Operators are provided access to a panel, which houses various controls for meters. Available meter components include digital frequency meter, digital voltage meter, digital ammeter and digital watt meter.

Mounting: The IND-SFC-3P-10KVA-208V-60HZ-200.115-400HZ-N1 is Pad/Floor Mounted.

Applications: Industrial facilities, laboratories, air compressor testing, power supply testing, motor equipment testing, quality assurance, lighting systems and more.

At Larson Electronics, we do more than meet your lighting needs. We also provide replacement, retrofit, and upgrade parts as well as industrial grade power accessories. Our craftsmen can custom build any lighting system and/or accessories to fit the unique demands of your operation. A commitment to honesty, quality, and dependability has made Larson Electronics a leader in the lighting and electronics business since 1973. Contact us today at 800-369-6671 or message sales@larsonelectronics.com for more information about our custom options tailored to meet your specific industry needs.

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

Frequently Asked Questions (FAQ)

There are no Faqs