Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

EPL-BZ-PL.R-STRB-DB-1224-N7

Explosion Proof LED Indicator Light and Buzzer Alarm - Red - 10-28V AC/DC - DB Mount, NEMA 7

Product ID: 319261



Image: EPL-BZ-PL.R-STRB-DB-1224-N7

Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

EPL-BZ-PL.R-STRB-DB-1224-N7 Indicator Light w/ Buzzer
Listing: NRTL Listed for United States and Canada
Lamp Technology: LED
Dimensions: 3.87"- L x 1.96" OD
Weight: 0.29 lbs
Voltage: 12-24V AC/DC (10V-28V AC/DC)
Frequency: 50/60 Hz
Total Watts: -
Total Lumens: -
Luminous Efficacy: -
LED Life Expectancy: 50,000+ Hours
Color Temp/Lamp Color: Red
Color Rendering Index: -
Lamp Type: -
Lamp Base: -
Replacement Lamp: -
Beam Angle: -
Lighting Configuration: Flashing
Power Efficiency: -
Power Factor: -
Sound Level: 60 dB @ 12"
Ambient Temp: -40°C to +50°C
Operating Temp: -40°C to +90°C

Ratings
Class I, Division 1
NEMA 7

Temp Rating: -
Housing Material: Polyamide
Housing Finish: -
Lens Material: -
Mounting: Device Box/Enclosure Mount - 1.2" (30.6mm) Mounting Pitch
Connections: (2) Terminals (2.5mm)
Entry Size: (1) M30 x 1.5

Special Orders - Special Requirements
Contact us for special requirements
Intl: 1-903-270-1187
Toll Free: 1-800-369-6671
Fax: 1-903-765-7664
E-mail: sales@larsonelectronics.com

The Larson Electronics EPL-BZ-PL.R-STRB-DB-1224-N7 Explosion Proof LED Indicator Light and Buzzer Alarm offers visual and audible notification in explosive environments. This device provides a red, flashing light and 60 dB sound output. Constructed of polyamide, the LED indicator light is NEMA 7 rated.

The explosion proof LED indicator light with buzzer alarm is designed for Class I, Division 1 rated combustible sites. The low-voltage device operates on 12V and 24V AC/DC (10V-28V AC/DC) @ 50/60 Hz. When in use, the compact unit emits a red, flashing light. The buzzer alarm feature provides 60dB of output at a distance of 12" (30 cm). This LED indicator light with alarm is constructed of polyamide to deter sparking. A NEMA 7 rating ensures protection in rugged facilities.

LED Benefits: Unlike gas burning and arc type lamps that have glass bulbs, LEDs have no filaments or fragile housings to break during operation and/or transportation. Instead of heating a small filament or using a combination of gases to produce light, light emitting diodes (LEDs) use semi-conductive materials that illuminate when electric current is applied, providing instant illumination with no warm up or cool down time before re-striking. Because there is no warm up period, this light can be cycled on and off with no reduction in lamp life.

LED lights run at significantly cooler temperatures than traditional metal halide and high pressure sodium lights and contain no harmful gases, vapors, or mercury, making them both safer and more energy efficient. No extra energy is wasted in cooling enclosed work areas due to external heat emissions from bulb type lights, and the operator risks associated with traditional lighting methods, such as accidental burns and exposure to hazardous substances contained in the glass bulbs, are eliminated. In addition, LEDs are also safer for the environment as they are 100% recyclable, which eliminates the need for costly special disposal services required with traditional gas burning and arc type lamps.

Wiring: The EPL-BZ-PL.R-STRB-DB-1224-N7 is equipped with two terminals (2.5mm) for completing electrical connections.

Mounting: This LED light is compatible with device box and enclosure mounting applications. The unit is suitable for M30 x 1.5 sizes.

At Larson Electronics, we do more than meet your lighting needs. We also provide replacement, retrofit, and upgrade parts as well as industrial grade power accessories. Our craftsmen can custom build any lighting system and/or accessories to fit the unique demands of your operation. A commitment to honesty, quality, and dependability has made Larson Electronics a leader in the lighting and electronics business since 1973. Contact us today at 800-369-6671 or message sales@larsonelectronics.com for more information about our custom options tailored to meet your specific industry needs.

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

Frequently Asked Questions (FAQ)

There are no Faqs