Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

MT-VCT-208VAC-30KW-125VDC-N12

30KW AC to DC Rectifier - 208V AC to 125V DC - NEMA 12

Product ID: 320513

Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

MT-VCT-208VAC-30KW-120VDC-N12 AC to DC Converter
Unit Type: AC to DC Converter
Dimensions: 70.9"-H, 48.43"-W, 25"-D
Weight: 33.1 lbs
Input Voltage: 208V AC ±10%
Input Freuency: 60 Hz
Output Power: 30 KW
Output Voltage: 125V DC ±5%
Maximum Fluctuation: ±2%
Minimum Power Factor: 0.8
Fluctuation Without Connecting Battery: ±1% Vn
Equalizing Timer: 0-24 Hrs
Undervoltage Protection: Included
DC Digital Voltmeter: Included, 1.5% precision
AC Digital Voltmeter: Included, 1.5% precision
Equalizing Voltage Adjustment: Included
Floating voltage adjustment: Included
Auto/Manual Control For Equalizing Voltage: Included
Protection Level : NEMA 12
Cable Entry: Bottom Entry
Operating Temperature: -10 / +40 °C
Relative humidity : 5 - 90 %
Operating Altitude: Max.9850ft
Noise Level: Max. 60 dBA

Ratings/Features
IP20NEMa 12 Rated
Natural Forced Cooling
Compatible with MasterBus
V6 HF Switch Mode
Complies with EN 50091-2 (EMC)
Complies with EN 50091-1 (Security)
LED Display

Special Orders - Special Requirements
Contact us for special requirements
Toll Free: 1-800-369-6671
Intl: 1-903-270-1187
Fax: 1-903-498-3364
E-mail: sales@larsonelectronics.com

The Larson Electronics MT-VCT-208VAC-30KW-125VDC-N12 AC to DC converter converts AC input to DC output in industrial sites. This power converter is rated at 30,000 watts continuous and offers 208V AC input and 125V DC output. The NEMA 12 rated device offers the following

protective features: short circuit, overload, over temperature, high battery and low battery.
The MT-VCT-208VAC-30KW-125VDC-N12 provides a safe and effective way for users to tap into and utilize 208V AC voltage to be converted to 125V DC. Rated at 30,000 watts (continuous), this true sine wave unit can be operated with low voltage 208V AC input voltage and 125V DC output voltage. The transformer provides short circuit, overload, over temperature, high battery and low battery protection. Peak wattage for this unit is 30,000W (short-term use only, not for extended periods). The recommended battery capacity is 850aH minimum.
This AC to DC transformer offers a -10°C to 40°C operating temperature range. The unit has a 92% conversion efficiency and is Master-Bus compatible. Cooling is facilitated by natural and forced mechanisms.
Wiring/Connections: AC connections can be completed inside the unit. This inverter accepts 70 mm^2 minimum cable size.
Mounting: The MT-VCT-208VAC-30KW-125VDC-N12 caters to surface and wall mounting applications via openings on the back of the transformer.
Applications: Voltage rectification, power conversion, AC to DC transformer, AC to DC conversion, solar-powered systems, power supply, engine rooms and more.
At Larson Electronics, we do more than meet your lighting needs. We also provide replacement, retrofit, and upgrade parts as well as industrial grade power accessories. Our craftsmen can custom build any lighting system and/or accessories to fit the unique demands of your operation. A commitment to honesty, quality, and dependability has made Larson Electronics a leader in the lighting and electronics business since 1973. Contact us today at 800-369-6671 or message sales@larsonelectronics.com for more information about our custom options tailored to meet your specific industry needs.

Frequently Asked Questions (FAQ)