Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

MT-PSU-ADC-R7-1P-220VAC-1KW-125VDC-IP65-M1

1000W AC to DC Power Supply - 220V AC to 0-125V DC - Digital

Product ID: 322676

Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

MT-PSU-ADC-R7-1P-220VAC-1KW-125VDC-IP65-M1 AC to DC Power Supply

Unit Type: AC/DC Power Supply (Digital)
Dimensions: 14.843" L x 8.268" W x 5.118" H
Weight: 20.3 lbs
Input Voltage: 220V AC +/- 10% @ 50/60Hz
Output Voltage: 0-125V DC (Adjustable)
Rated Power: 1000W
Ripple: 3mV rms, 15mV p-p
Voltage Regulation - Line: 0.05%
Voltage Regulation - Load: 0.01%
Current Regulation - Line: 0.01%
Display Type: Digital
Number of Characters: (2) 4, 4
Interfaces: Constant Current and Constant Voltage Indicators/PowerFlex Regulation
Digital Remote Control: USB, RS232, LAN & GPIB
Driver Software: Included
Operating Temp: +5ºC to +40ºC
Materials: -
Mount: Rack Mount or Standalone
Outputs: (2)
Color: White

Ratings
Bus Programmable

Special Orders - Special Requirements
Contact us for special requirements
Intl: 1-903-270-1187
Toll Free: 1-800-369-6671
Fax: 1-903-765-7664
E-mail: sales@larsonelectronics.com

The MT-PSU-ADC-R7-1P-220VAC-1KW-125VDC-IP65-M1 from Larson Electronics is an AC/DC Power Supply that provides accurate voltage control and power management features for industrial operations. This 20-amp unit is compatible with 220V AC @ 50-60 Hz input voltage and provides 0-125V DC output voltage. This power supply is compatible with rack mounting installations or can be used as a standalone unit.

The MT-PSU-ADC-R7-1P-220VAC-1KW-125VDC-IP65-M1 is a compact AC/DC power supply with a digital interface for industrial facilities. The dual output unit accepts an input voltage range of 220V AC +/-10% @ 50/60Hz and offers an output voltage range of 0-125V DC. This 1000W device contains two displays for dedicated output controls. Monitoring interfaces include the following: constant current indicators, constant voltage indicators and powerFlex regulation. Digital remote control is facilitated by USB, RS-232, GPIB and LAN (LXI). Operators may access two sets of +/- DC outputs on the unit.

Mounting: The MT-PSU-ADC-R7-1P-220VAC-1KW-125VDC-IP65-M1 is suitable for rack

mounting applications or standalone use on flat surfaces.

Applications: Industrial sites, factory control, automation, laser machines, manufacturing, voltage control, power management, digital broadcasting, RF applications, computerized systems and more.

At Larson Electronics, we do more than meet your lighting needs. We also provide replacement, retrofit, and upgrade parts as well as industrial grade power accessories. Our craftsmen can custom build any lighting system and/or accessories to fit the unique demands of your operation. A commitment to honesty, quality, and dependability has made Larson Electronics a leader in the lighting and electronics business since 1973. Contact us today at 800-369-6671 or message sales@larsonelectronics.com for more information about our custom options tailored to meet your specific industry needs.

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.498.3364

Frequently Asked Questions (FAQ)

There are no Faqs