Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

MTPC-HD-RB-120V-2.4HP-1.2HP-N1-M2

Portable Rotary Phase Converter for 1.2HP Hard Loads, 120V 1PH to 3PH, 4.8 Amps Output, 2.4HP Idler, Yellow Powder Coated Mobile Cart, NEMA 1

Product ID: 325884



Image: MTPC-HD-RB-120V-2.4HP-1.2HP-N1-M2

Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

MTPC-HD-RB-120V-2.4HP-1.2HP-N1-M2 Portable Rotary Phase Converter

Unit Type: Portable Rotary Phase Converter
Phase Conversion: Single Phase to Three Phase
Kilowatt Rating: 900 W
Kilo Volt-Amp Rating: 1 KVA
Idle Motor Horse Power: 2.4 HP
Single Phase Voltage Input: 120V
Minimum Fuse/Circuit Breaker Size: 10
Maximum Fuse/Circuit Breaker Size: 25
Minimum Wire (Input) to Converter: 10 AWG
Minimum Electrical Service Required: 5 KVA
Idle Amps: -
Service Load Type: Hard motor loads
Three Phase Voltage Output: 120
Maximum Single Motor Load HP: 1.2 HP
Recommended Combined HP: 1.2 HP
Optimal Output Amps: 4.8A
Maximum Output Amps: 8.3A
Maximum Resistive Amps: 5A
Voltage Balance: 2-5%
Minimum Wire to Device Load: 12 AWG
Form Factor: Rectangular Enclosure, Cylindrical Idler; Yellow Powder Coated Portable Cart w/ (4) Casters & Horizontal Handle
Color: Natural Gray
Weight: -
Dimensions: 38"-W x 27"-D x 35.29"-H

Ratings/Approvals

Indoor Use (NEMA 1)
Built-in Motor Starter
Start/Stop Push Button Switch
Accurate Voltage Balancing
Power Indicator Light
Portable Design
Made in the USA

Special Orders - Special Requirements

Contact us for special requirements
Toll Free: 1-800-369-6671
Intl: 1-214-616-6180

Shipping Weight: -
Shipping Dimensions: -

Fax: 1-903-765-7664
E-mail: sales@larsonelectronics.com

Made in the USA

The MTPC-HD-RB-120V-2.4HP-1.2HP-N1-M2 from Larson Electronics is a Portable 3 Horsepower Rotary Phase Converter that is designed to convert single phase power to three phase power for Hard motor loads. This phase converter accepts a single-phase 120V input and provides a three-phase 120V output. Operators may use this rotary phase converter to power equipment and machines with Hard motor loads up to 1.2 horsepower and 4.8 amps that require three phase power in locations where only single phase power is available. A portable cart design makes this unit simple to move around the work location.

Applications: The MTPC-HD-RB-120V-2.4HP-1.2HP-N1-M2 is ideal for applications that utilize Hard motor loads. This includes CNC laser table, CNC lathe, CNC mill, CNC plasma table, CNC router, CNC turning machine, CNC waterjet, cooling fan, exhaust fan, gearhead lathe, industrial fan, laser cutter, laser table, plasma cutter, plasma table, plastic grinder, printing press and any other application that induces a Hard motor load up to a recommended 1.2 horsepower.

The MTPC-HD-RB-120V-2.4HP-1.2HP-N1-M2 rotary phase converter is suitable for converting single phase 120V on-site power to three phase 120V power for equipment. This 3 HP idler motor phase converter connects to existing 120V/* single phase. After conversion, the phase converter provides three-phase 120V on the output side at 4.8 continual amps with a maximum of 8.3 inrush amps. All MTPC series phase converters provide +/- 2-5% voltage balance on the output side, depending on the single phase input power, for maximum efficiency and reduced stress on the motor. This rotary phase converter features a built-in motor starter with a start/stop push button switch for seamless activation. The power distribution blocks are oversized for easy installation in the preferred location.

The MTPC-HD-RB-120V-2.4HP-1.2HP-N1-M2 control panel is housed in a NEMA 1 enclosure, making it suitable for indoor environments. This level of protection allows the rotary phase converter to withstand the ingress of solid objects, such as falling dirt. All of Larson Electronics LLC's phase converter control panels are NRTL certified to UL 508A. The entire phase converter is designed to be portable. This unit is mounted to a yellow powder coated cart equipped with four casters and a horizontal handle.


The MTPC series of rotary phase converters are designed to operate based on overall load size. This includes operating multiple devices from one rotary phase converter, providing the combined horsepower of all devices being operated simutaniously does not exceed the horsepower rating for the load type. This includes fractional motors up to 1.5 HP motors, and any combination of motor sizes in between. Instant reversal motors are no problem for the MTPC series phase converters. Each phase converter comes ready to install.

Rotary Sizing: The MTPC-HD-RB-120V-2.4HP-1.2HP-N1-M2 is sized for heavy/hard motor loads up to 1.2 horsepower. When correctly sized, Larson Electronics phase converters will provide years of trouble free service for your equipment. Larson Electronics offers single phase to three phase static and rotary phase converters for easy, medium, hard, and very hard motor loads. The motor load is dependant on the devices intended to operate on the

phase converter. For additional load types or for additional sizes, please see the below links or call us today.

- Single Phase to Three Phase Rotary Converters for Easy Motor Loads
  - Single Phase to Three Phase Converters for Medium Motor Loads
  - Single Phase to Three Phase Converters for Hard Motor Loads
  - Single Phase to Three Phase Converters for Very Hard Motor Loads

At Larson Electronics, we do more than meet your lighting and power distribution needs. We also provide replacement, retrofit, and upgrade parts as well as industrial grade power accessories. Our craftsmen can custom build any lighting or power distribution system and/or accessories to fit the unique demands of your operation. A commitment to honesty, quality, and dependability has made Larson Electronics a leader in the lighting and electronics business since 1973. Contact us today at 800-369-6671 or message sales@larsonelectronics.com for more information about our custom options tailored to meet your specific industry needs.



LARSON ELECTRONICS


PART NUMBER:

FAB0000288250

SIZE		REV
A		1

DIMENSIONS ARE IN INCHES				
DO NOT SCALE DRAWING	DATE	10/1/2025	SCALE: NTS	SHEET 1 OF 15

PROPRIETARY AND CONFIDENTIAL
THE INFORMATION CONTAINED IN THIS DRAWING IS THE SOLE PROPERTY OF LARSON ELECTRONICS LLC. ANY REPRODUCTION IN PART OR AS A WHOLE WITHOUT THE WRITTEN PERMISSION OF LARSON ELECTRONICS LLC IS PROHIBITED.



LARSON ELECTRONICS

PART NUMBER:

FAB0000288250

SIZE		REV
A		1

DIMENSIONS ARE IN INCHES			SCALE: NTS	SHEET 2 OF 15
DO NOT SCALE DRAWING	DATE	10/1/2025		

PROPRIETARY AND CONFIDENTIAL
THE INFORMATION CONTAINED IN THIS DRAWING IS THE SOLE PROPERTY OF LARSON ELECTRONICS LLC. ANY REPRODUCTION IN PART OR AS A WHOLE WITHOUT THE WRITTEN PERMISSION OF LARSON ELECTRONICS LLC IS PROHIBITED.

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

Frequently Asked Questions (FAQ)

There are no Faqs