

MTPC-HD-RB-110V-4HP-2HP-N1-M1

Rotary Phase Converter for 2HP Hard Loads, 110V 1PH to 3PH, 15.8 Amps Output, 4HP Idler, NEMA 1

Product ID: 325943



Image: MTPC-HD-RB-110V-4HP-2HP-N1-M1

Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

MTPC-HD-RB-110V-4HP-2HP-N1-M1 Rotary Phase Converter

Unit Type: Rotary Phase Converter

Phase Conversion: Single Phase to Three Phase

Kilowatt Rating: 3 KW

Kilo Volt-Amp Rating: 3 KVA

Idle Motor Horse Power: 4 HP

Single Phase Voltage Input: 110V

Minimum Fuse/Circuit Breaker Size: 40

Maximum Fuse/Circuit Breaker Size: 60

Minimum Wire (Input) to Converter: 8 AWG

Minimum Electrical Service Required: 5 KVA

Idle Amps: -

Service Load Type: Hard motor loads

Three Phase Voltage Output: 110V

Maximum Single Motor Load HP: 2 HP

Recommended Combined HP: 2 HP

Optimal Output Amps: 15.75 A

Maximum Output Amps: 18 A

Maximum Resistive Amps: 9.5 A

Voltage Balance: 2-5%

Minimum Wire to Device Load: 12 AWG

Form Factor: Rectangular Enclosure, Cylindrical Idler w/ Four Legs

Color: Natural Gray

Weight: - lbs

Ratings/Approvals

Indoor Use (NEMA 1)

Built-in Motor Starter

Start/Stop Push Button Switch

Accurate Voltage Balancing

Power Indicator Light

Made in the USA

Special Orders - Special Requirements

Contact us for special requirements

Toll Free:

Dimensions: -
Shipping Weight: - lbs
Shipping Dimensions: -

1-800-369-6671
Intl: 1-903-270-1187
Fax: 1-903-765-7664
E-mail: sales@larsonelectronics.com

Made in the USA

The Larson Electronics MTPC-HD-RB-110V-4HP-2HP-N1-M1 4 horsepower rotary phase converter is designed to convert single phase power to three phase power for Hard motor loads. This phase converter accepts a single-phase 110V input and provides a three-phase 110V output. Operators may use this rotary phase converter to power equipment and machines with Hard motor loads up to 2 horsepower and 8.3 amps that require three phase power in locations where only single phase power is available.

Applications: The MTPC-HD-RB-110V-4HP-2HP-N1-M1 is ideal for applications that utilize Hard motor loads. This includes CNC laser table, CNC lathe, CNC mill, CNC plasma table, CNC router, CNC turning machine, CNC waterjet, cooling fan, exhaust fan, gearhead lathe, industrial fan, laser cutter, laser table, plasma cutter, plasma table, plastic grinder, printing press and any other application that induces a Hard motor load up to a recommended 2 horsepower.

The MTPC-HD-RB-110V-4HP-2HP-N1-M1 rotary phase converter is suitable for converting single phase 110V on-site power to three phase 110V power for equipment. This 3 HP idler motor phase converter connects to existing 110V/* single phase. After conversion, the phase converter provides three-phase 110V on the output side at 15.8 continual amps with a maximum of 18 inrush amps. All MTPC series phase converters provide +/- 2-5% voltage balance on the output side, depending on the single phase input power, for maximum efficiency and reduced stress on the motor. This rotary phase converter features a built-in motor starter with a start/stop push button switch for seamless activation. The power distribution blocks are oversized for easy installation in the preferred location.

The MTPC-HD-RB-110V-4HP-2HP-N1-M1 control panel is housed in a NEMA 1 enclosure, making it suitable for indoor environments. This level of protection allows the rotary phase converter to withstand the ingress of solid objects, such as falling dirt. All of Larson Electronics LLC's phase converter control panels are NRTL certified to UL 508A.

The MTPC series of rotary phase converters are designed to operate based on overall load size. This includes operating multiple devices from one rotary phase converter, providing the combined horsepower of all devices being operated simultaneously does not exceed the horsepower rating for the load type. This includes fractional motors up to 2 HP motors, and any combination of motor sizes in between. Instant reversal motors are no problem for the MTPC series phase converters. Each phase converter comes ready to install.

Rotary Sizing: The MTPC-HD-RB-110V-4HP-2HP-N1-M1 is sized for heavy/hard motor loads up to 2 horsepower. When correctly sized, Larson Electronics phase converters will provide years of trouble free service for your equipment. Larson Electronics offers single phase to three phase static and rotary phase converters for easy, medium, hard, and very hard motor loads. The motor load is dependant on the devices intended to operate on the phase converter. For additional load types or for additional sizes, please see the below links or call us today.

- [Single Phase to Three Phase Rotary Converters for Easy Motor Loads](#)
- [Single Phase to Three Phase Converters for Medium Motor Loads](#)
- [Single Phase to Three Phase Converters for Hard Motor Loads](#)
- [Single Phase to Three Phase Converters for Very Hard Motor Loads](#)

At Larson Electronics, we do more than meet your lighting and power distribution needs. We also provide replacement, retrofit, and upgrade parts as well as industrial grade power accessories. Our craftsmen can custom



build any lighting or power distribution system and/or accessories to fit the unique demands of your operation. A commitment to honesty, quality, and dependability has made Larson Electronics a leader in the lighting and electronics business since 1973. Contact us today at 800-369-6671 or message sales@larsonelectronics.com for more information about our custom options tailored to meet your specific industry needs.

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671



www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671



www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664









Frequently Asked Questions (FAQ)

There are no Faqs