

MT-CTX-12470V-5KVA-120.240V-N1-TP-M1

5 KVA Control Transformer - 12470V Input Voltage, 120/240V Output Voltage - 1PH, Taps/60Hz - Prim. Fuse Blocks, NEMA 1

Product ID: 327365



Image: MT-CTX-12470V-5KVA-120.240V-N1-TP-M1

Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

MT-CTX-124700V-5KVA-120.240V-N1-TP-M1 Control Transformer

Phase: Single Phase

Frequency: 60 Hz

kVA: 5 kVA

Primary Voltage: 12470V

Primary Connection: Series (V)

Taps: +/- 7.5%

Secondary Voltage: 120/240V

Secondary Connection: Parallel x Series (Vx2V)

BIL: 95 kV

Fuse Block: Primary Side

Winding Material: Copper

Primary Termination: Terminal Block

Secondary Termination: Terminal Block

Insulation: 130°C

Temperature Rise: 80°C

Enclosure Type: NEMA 1

Enclosure Material: Injection Molded Cover

Mounting: Heavy Steel Feet

Dimensions: (*Please note that dimensions are approximate and subject to change*) 15.38" x 11.50" x 17.88"

Weight: (*Please note that weight is approximate and subject to change*) 250 lbs

Approvals/Ratings

NRTL Listed for United States and Canada

NRTL Certified to CSA 22.2 NO 66.1

NRTL Certified to CSA 22.2 NO 66.2

NRTL Certified to UL 5085-1

NRTL Certified to 5085-2

Control Transformer

Special Orders - Special Requirements

Contact us for special requirements

Toll Free: 1-800-369-6671

Intl: 1-214-616-6180

E-mail: sales@larsonelectronics.com

The MT-CTX-12470V-5KVA-120.240V-N1-TP-M1 from Larson Electronics is a 12470V

Single Phase Control Transformer that is powerful, efficient, and designed for dependable performance in indoor industrial environments. Featuring a NEMA 1 enclosure for protection in clean, dry locations, this unit provides reliable power management and protection against critical equipment failures. Built with high-quality silicon steel laminations for superior performance and reduced losses, the MT-CTX-12470V-5KVA-120.240V-N1-TP-M1 ensures long service life and operational reliability.

Transformer Features: With a transformer rating of 5 kVA, the MT-CTX-12470V-5KVA-120.240V-N1-TP-M1 is a machine tool industrial single phase control transformer with a primary voltage of 12470V. It also provides secondary voltage of 120/240V. Featuring compact and innovative construction, this unit's cores are manufactured with high-quality silicon steel laminations using state of the art technology.

This unit boasts an innovative terminal block design that allows for easy hookup. Connecting this unit is a simple task thanks to the terminal connection numbers being molded into the terminal block which corresponds to the nameplate and wiring diagrams. A unique fin-shaped, injection molded coil cover gives this unit superior cooling abilities. The unit also features a 130°C insulation class with a 80°C temperature rise.


Benefits: The MT-CTX-12470V-5KVA-120.240V-N1-TP-M1 control transformer offers many benefits to the consumer. Full encapsulation of the windings and internal terminations ensures that the unit is protected from moisture, dirt, dust, and other contaminants. Removable finger safe terminal covers contribute towards the overall clean and sleek look of the unit. The compact and innovative design features make this a great choice for industrial tool applications.


This control transformer has heavy steel mounting feet that are either welded or bolted to the core. This transformer features terminal block terminations.

Applications: Power Management, Industrial

Larson Electronics is a manufacturer and as such can build stationary and portable transformer systems to your specifications. Although we carry several models of power distribution transformer systems, we can deliver custom ordered units almost as quickly as our prebuilt units. If this model does not meet your needs, please contact us at 1-800-369-6671 or sales@larsonelectronics.com to discuss your specific requirements.







Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671



www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664





Frequently Asked Questions (FAQ)

There are no Faqs