

MT-UPM-XX-SP9578

Replacement Bushing Gasket for MT-UPM Series Transformers

Product ID: 330980

Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

MT-UPM-XX-SP9578 Bushing Gasket

Unit Type: Bushing Gasket, O-Ring Type

Application: Installed Between Bushing and Tank

Dimensions: 4.0"-W x 4.0"-D x 0.25"-H

Weight: 0.10 lbs

Material: Nitrile (NBR)

Operating Temperature Range: -40°C to + 100°C

Special Orders - Special Requirements

Contact us for special requirements

Toll Free: 1-800-369-6671

Intl: 1-903-270-1187

Fax: 1-903-765-7664

E-

mail: sales@larsonelectronics.com

Replacement Bushing Gasket for MT-UPM Series Transformers



Frequently Asked Questions (FAQ)

There are no Faqs