Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

MT-MCB-20A-1P-120V-35KAIC-TM

20A Miniature Circuit Breaker – 120V AC 50/60 Hz – Thermal-Magnetic, 35 kAIC – 1-Pole, Bolt-On

Product ID: 332766



Image: MT-MCB-20A-1P-120V-35KAIC-TM

Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

MT-MCB-20A-1P-120V-35KAIC-TM Miniature Circuit Breaker
Unit Type: MCB
Voltage: 120V AC
Current Rating: 20 A
No. Of Poles: 1-Pole
Interrupt Rating: 35 kAIC
Trip Type: Thermal-Magnetic (Fixed Long-Time & Instantaneous)
Frequency: 50/60 Hz
Ambient Temperature Range: -
Mounting: Bolt-On Panel Mount
Terminals: Pressure Plate / Screw Clamp, Cu/Al Rated
Overall Dimensions: Approx. 3.0" - H, 2.0" - W, 2.9" - D
Overall Weight: Approx. 0.75 lbs
Shipping Dimensions: -
Shipping Weight: -
Larson Electronics manufactures a wide variety of custom power distribution systems. The pictures displayed for this unit are a general representation of form factor and may not accurately represent this exact configuration in every detail due to being custom builds. The specifics for this configuration are listed in the specification table and one-line diagram.

Ratings
UL 1077
CSA Std. C22.2 No.235
IEC 60947-2
Made in the USA

Special Orders - Special Requirements
Toll Free: 1-800-369-6671
Intl: 1-903-270-1187
Fax: 1-903-765-7664
E-mail: sales@larsonelectronics.com

All grounding shall comply with state and local codes and meet the minimum requirements of the National Electronic Code section 250

Made in the USA

The MT-MCB-20A-1P-120V-35KAIC-TM Larson Electronics miniature circuit breaker offers high performance in a compact design. This breaker is available as a one pole

configuration and rated for 20 amps.

PLEASE NOTE: ANY FREE SHIPPING OFFERS DO NOT APPLY TO POWER DISTRIBUTION PANELS, TRANSFORMERS, OR SUBSTATIONS

The MT-MCB-20A-1P-120V-35KAIC-TM circuit breaker provides safe and reliable branch circuit protection for commercial and industrial panelboard applications. Compatible with 120V AC, 50/60 Hz systems, this 1-pole miniature circuit breaker is rated for 20 amps with a 35 kAIC interrupt rating. The unit features a thermal-magnetic trip mechanism for overload and short-circuit protection and is designed for bolt-on mounting in compatible panelboards. Pressure plate terminals ensure secure copper or aluminum conductor connections.

Applications: This MT-MCB-20A-1P-120V-35KAIC-TM is used in power distribution, telecom, transportation, marine, generators, power supplies and medical equipment.

At Larson Electronics, we do more than meet your lighting needs. We also provide replacement, retrofit, and upgrade parts as well as industrial grade power accessories. Our craftsmen can custom build any lighting system and/or accessories to fit the unique demands of your operation. A commitment to honesty, quality, and dependability has made Larson Electronics a leader in the lighting and electronics business since 1973. Contact us today at 800-369-6671 or message sales@larsonelectronics.com for more information about our custom options tailored to meet your specific industry needs.

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

Frequently Asked Questions (FAQ)

There are no Faqs