Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

MT-CTX-120V-50VA-12V

50 VA Control Transformer - 120V Input Voltage - 12V AC Output Voltage

Product ID: 344339



Image: MT-CTX-120V-50VA-12V

Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

MT-CTX-120V-50VA-12V Control Transformer
Phase: Single Phase
Frequency: 60 Hz
Capacity: 50 VA
Primary Voltage: 120V
Primary Connection: Series (V)
Primary FCAN (Std.): 0 x 0%
Primary FCBN (Std.): 0 x 0%
Secondary Voltage: 12V AC
Secondary Connection: Parallel x Series (Vx2V)
Material: Copper
Primary Termination: (2) 18 AWG Lead Wires (Black-White), 12" ± 0.5" Length, 0.75 ± 0.063 Strip
Secondary Termination: (2) 18 AWG Lead Wires (Yellow-Yellow), 12" ± 0.5" Length, 0.75 ± 0.063 Strip
Insulation: 130°C
Temperature Rise: 80°C
Enclosure Material: Injection Molded Cover
Mounting: 2-Hole Horizontal Mounting
Dimensions: 3.38"-H x 3.75"-W x 3.50"-D
Weight: 5.9 lbs

Approvals/Ratings
NRTL Listed for United States and Canada
NRTL Certified to CSA 22.2 NO 66.1
NRTL Certified to CSA 22.2 NO 66.2
NRTL Certified to UL 5085-1
NRTL Certified to 5085-2
Control Transformer

Special Orders - Special Requirements
Contact us for special requirements
Toll Free: 1-800-369-6671
Intl: 1-214-616-6180
Fax: 1-903-765-7664
E-mail: sales@larsonelectronics.com

The MT-CTX-120V-50VA-12V from Larson Electronics is a 50 VA single-phase control transformer that is powerful, reliable, and innovatively designed. With high-quality silicon steel laminations providing optimal performance, the MT-CTX-120V-50VA-12V

provides increased reliability and protection against critical equipment failures. This control transformer features an innovative design with a unique terminal block design that allows for a quick and easy hookup along with the ability to easily install fuse clips to the unit. The uniquely designed molded coil covers give this control transformer superior cooling abilities and a sleek appearance.

Transformer Features: With a transformer rating of 50 VA, the MT-CTX-120V-50VA-12V is a machine tool industrial single-phase control transformer with primary voltages of 120 V. It also provides a secondary voltage of 12V AC. Featuring compact and innovative construction, this unit's cores are manufactured with high-quality silicon steel laminations using state-of-the-art technology.

This unit boasts an innovative terminal block design that allows for easy hookup. Connecting this unit is a simple task thanks to the terminal connection numbers being molded into the terminal block, which corresponds to the nameplate and wiring diagrams. A unique, fin-shaped, injection-molded coil cover gives this unit superior cooling abilities. The unit also features a 130°C insulation class with an 80°C temperature rise.

Benefits: The MT-CTX-120V-50VA-12V control transformer offers many benefits to the consumer. Full encapsulation of the windings and internal terminations ensures that the unit is protected from moisture, dirt, dust, and other contaminants. Removable finger-safe terminal covers contribute towards the overall clean and sleek look of the unit. The compact and innovative design features make this a great choice for industrial tool applications.

This control transformer has heavy steel mounting feet that are either welded or bolted to the core. This transformer features terminal block terminations.

Applications: Power Management, Industrial

Larson Electronics is a manufacturer and, as such, can build stationary and portable transformer systems to your specifications. Although we carry several models of power distribution transformer systems, we can deliver custom-ordered units almost as quickly as our prebuilt units. If this model does not meet your needs, please contact us at 1-800-369-6671 or sales@larsonelectronics.com to discuss your specific requirements.

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664




Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

Frequently Asked Questions (FAQ)

There are no Faqs