Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

## MT-SMB-UPS-WM-3P-480V-10KVA-M1

# 10 KVA Maintenance Bypass Panel for UPS – 480V AC 3PH – 3-Breaker, Kirk-Key Interlocked – Wall Mount

**Product ID: 344367**



Image: MT-SMB-UPS-WM-3P-480V-10KVA-M1

**Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.**

---

**MT-UPS-SMB-WM-3P-480V-10KVA-M1 Maintenance Bypass and Power Output Distribution Unit**

**Unit Type:** Maintenance bypass panel (3-breaker configuration)

**Dimensions:** 30″ W × 10.8″ D × 42″ H

**Weight:** 200 lbs

**Input Voltage:** 480V AC, Three Phase, 3-Wire + Ground

**Output Voltage:** 480V AC, Three Phase, 3-Wire + Ground

**Power Capacity:** Suitable for UPS systems rated up to 10 KVA (switching/bypass only)

**Breakers Installed:**
- **Maintenance Bypass Breaker (MBP)**: 40A, 3-Pole
- **UPS Input Breaker (MIB):** 40A, 3-Pole
- **UPS Output Breaker (MIS):** 40A, 3-Pole

**Interlocking:** Kirk-Key mechanical interlock system to prevent unsafe operating sequences

**Function:** Provides a **manual,** Kirk-Key interlocked maintenance bypass path allowing isolation of the UPS for service while maintaining continuity of power to the load. Designed for safe maintenance operations without simultaneous connection of UPS and bypass sources.

**Form Factor:** Wall Mount

**Enclosure Type:** NEMA 1 – Indoor Rated, steel enclosure

**Mounting Orientation:** Surface-Mounted Panel

**Ratings/Approvals**

UL 508A Industrial Control Panel

**Special Orders - Special Requirements**

Contact us for special requirements

**Intl:** 1-903-270-1187
**Toll Free:** 1-800-369-6671

**Cooling:** Natural convection (fanless)
**Grounding:** Internal equipment grounding lug provided

**Fax:** 1-903-765-7664
**E-mail:** sales@larsonelectronics.com

*All grounding shall comply with state and local codes and meet the minimum requirements of the National Electronic Code section 250*

**The MT-SMB-UPS-WM-3P-480V-10KVA-M1 is a wall-mounted, three-breaker maintenance bypass panel designed for use with an online double-conversion industrial Uninterruptible Power Supply (UPS) rated up to 10 kVA, 480V AC, 3-phase, 50/60 Hz.**

The MT-SMB-UPS-WM-3P-480V-10KVA-M1 enables safe, manual transfer between utility power and UPS power during maintenance without interrupting power to critical equipment. This unit utilizes a Kirk-Key mechanical interlock system to prevent unsafe operating sequences and features a three-breaker configuration consisting of a maintenance bypass breaker (MBP), UPS input breaker (MIB), and UPS output breaker (MIS). This panel is intended for bypass and isolation only and does not include internal power distribution or load branch circuitry.

**Wiring:** Utility power is connected to the panel's input terminals using appropriately sized conductors in accordance with applicable electrical codes. The UPS input is connected through the MIB and the UPS output through the MIS. Critical loads are connected downstream of the UPS. During normal operation, power flows through the UPS. During maintenance, the MBP provides a safe bypass path allowing the UPS to be isolated without interruption to the load.

**Mounting:** The MT-SMB-UPS-WM-3P-480V-10KVA-M1 is wall-mounted for easy integration with standard three-phase UPS installations in industrial and commercial electrical rooms.

At Larson Electronics, we do more than meet your lighting needs. We also provide replacement, retrofit, and upgrade parts as well as industrial grade power accessories. Our craftsmen can custom build any lighting system and/or accessories to fit the unique demands of your operation. A commitment to honesty, quality, and dependability has made Larson Electronics a leader in the lighting and electronics business since 1973. Contact us today at 800-369-6671 or message sales@larsonelectronics.com for more information about our custom options tailored to meet your specific industry needs.

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664



Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671

www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664

# Frequently Asked Questions (FAQ)

There are no Faqs