

EPL-XX-TRK

Tube Repair Kit for EPL Series explosion proof lights

Product ID: 48267



Image: EPL-XX-TRK

Larson Electronics LLC manufactures a wide variety of products, including custom built to spec designs. The pictures displayed for this unit are a general representation of form factor for the product line and may not accurately represent this exact configuration in every detail due to custom builds and changes between similar products in our standard catalog. The specifics for this configuration are listed in the specification table and supporting documentation (CAD files, Dimensional Drawing, Name Plate Diagram, Wiring Diagram, etc.). This means that specific details (receptacles, plugs, wires, connections, mounting brackets, external finishes, etc.) may not be accurately represented in images vs specifications. Please review specifications and do not order based solely on images.

Tube repair kit for EPL-48 and EPL-24 series explosion proof fluorescent or LED lights. 1 kit is required for 2 lamp fixtures. 2 kits are required for 4 lamp fixtures. Each kit has (2) glass tubes, (4) O-rings, and the chiko powder compound.



Larson Electronics LLC www.LarsonElectronics.com sales@larsonelectronics.com
9419 E US HWY 175, Kemp, TX 75143 - P: (800) 369-6671 - F: (903) 498-3364

Tube Repair Instructions for Larson Electronics EPL Series

- 1) Using appropriate safety precautions remove both Pyrex tubes. Chip out and remove all glass and cement (Chico) that remains in the fixture tube ends.
- 2) Thoroughly clean all cavities and ensure all surfaces are clean of glass and Chico (cement).
- 3) Lay the fixture down on the surface, face up with re-lamping end towards you. Insert gaskets and tubes. Place blind casting (no hub side) on the other end of the Pyrex tubing. If possible, apply tension or weight to blind casting end, pushing fixture together.
- 4) Mix cement per instructions on container and pour in between the glass and castings.
- 5) Allow cement to dry
- 6) Rotate lamp 180 degrees and repeat steps 1–5.

Larson Electronics LLC
9419 E US HWY 175, Kemp, TX 75143
Phone: 800.369.6671



www.LarsonElectronics.com
Email: sales@LarsonElectronics.com
Fax: 903.765.7664







Frequently Asked Questions (FAQ)

There are no Faqs